

BellSouth Interconnection Services

675 West Peachtree Street
Atlanta, Georgia 30375

Carrier Notification**SN91084236**

Date: September 17, 2004

To: Competitive Local Exchange Carriers (CLEC)

Subject: CLECs – (Documentation/Guides) - Update to the BellSouth Local Ordering Handbook (LOH) Version **17.0**, New Local Service Ordering Guide 6 (LSOG 6) and EDI Local Mechanization Specifications 6 (ELMS 6) for Release 17.0

This is to advise that BellSouth has identified the following documentation defects in the LOH Version **17.0** for ELMS 6 Release 17.0.

CCP Number	Description Of The Change
1960	Remove the LCSC Contact Telephone Numbers table from the LOH and updated verbiage around url: http://interconnection.bellsouth.com/centers/html/lcsc.html .
1996	Change DQTY field from "Conditional" to "Optional".
1997	Modify Data Dictionary for DL and LSR [sections] for the LACT and ACT fields.
2011	LSO field: Modify Conditional Usage Note for LSO field on LSR Data Dictionary
2036	Add note to TNAQ-MISC field and add Usage Note to CITY field on the TNAQ-MISC query in the TAG Business Rules, and in the EDI Data Dictionary
2037	SPEC [field] update for Dark Fiber Combo for Data Dictionary.
2038	R/C/O changes from Ordering LOH Audit: Changes to R/C/O tables as the result of an audit of the Ordering LOH by the documentation team. (ELMS6 Release 17. only). Add Conditional Usage Notes to Data Dictionary for FB-ROOM, FB-FLOOR, and FB-SBILLNM.
2039	REQTYP A UCL-ND (If ACT is tables): Modify the UCL=ND REQ TYP A (IF ACT is tables) to indicate that LNA = D 'N/A' and LS form is prohibited.
2040	Add new fields to the Pre-Order Data Dictionary for both TAG and EDI Data Dictionary. Add the EATN and LEATN fields to the Estimated Service Date Query (table) in the TAG and EDI Business Rules.
2043	Contract Assumption Agreements: Create a section for Contract Service Agreements in the General Local Service Ordering section and remove the section for Local Resale contract assumption agreements.
2045	DDDO field: Modify DDDO field in Data Dictionary and R/C/O tables.

2046	Modify R/C/O tables for LD1, LD2, LD3, LV1, LV2, LV3 fields; change "Optional" occurrences of these fields LD1, LD2, LD3, LV1, LV2, LV3 to "Conditional".
2047	UNE-P to Resale (ACT W): Remove ACT W, update UNE-P to Resale - Remove ACT W (not valid).
2048	R/C/O Table for MegaLink Channelized Trunk Service: /C/O Table for MegaLink Channelized Trunk Service.

Please refer to the attachments for specific details of the changes listed above.

These changes will be reflected in the next update of the ELMS 6 Release 17.0/LOH Version **17.0a** scheduled to be posted September 17, 2004.

A summary of all changes within this document will be listed in the **Summary of Changes** Section. This update can be found on the BellSouth Interconnection Services Web site in the Customer Guides Section at:

<http://www.interconnection.bellsouth.com/guides/html/leo.html>

Please contact your BellSouth local support manager with any questions.

Sincerely,

ORIGINAL SIGNED BY JERRY HENDRIX

Jerry Hendrix – Assistant Vice President
BellSouth Interconnection Services

Attachments

CCP 1960 Attachment Listed Below

TCIF9 & ELMS6

General Local Service Ordering section

Manual and Electronic Ordering

Manual LSRs (Local Service Request) are requests for local service submitted by a CLEC to the LCSC. There are two options available to the CLEC for submitting manual LSRs to the LCSC:

- Option 1: Fax directly to the LCSC for manual input. Manually submitted LSR's are manually handled and tracked.
- Option 2: Web Based LSR Web Based LSR's are submitted to the LCSC via the LENS GUI and are manually handled and tracked. (Refer to LENS User Guide for information on WEB Based LSR's)

Note: Alternate method of receipt for individual LSR's greater than 100 pages must be pre-arranged by the CLEC with LCSC management.

CLECs can submit orders either manually or electronically. Depending upon the method chosen, the CLEC may have to provide different information to BellSouth®, that is, some data elements may be applicable only to manual or electronic orders, not both. For example, many of the data elements in the Administrative section of the LSR are repeated on each of the manual forms and must be completed to match the information on the LSR. These fields include PON, VER, AN, and ATN. When submitting an electronic request, however, these fields are populated once and the data flows through to all subsequent screens used in the order. Watch for these types of distinctions as they are made throughout this document.

~~LCSC/LCSC/CRSG Contact Telephone Numbers~~

~~The Local Carrier Service Center (LCSC) is the single point of contact for a CLEC when manually submitting orders. Use the telephone numbers [link](#) below to find to contact numbers for the LCSC and CRSG. for questions relating to manually submitted local service requests and billing inquiries. All completed local service ordering forms may be sent via facsimile to the number indicated below. Prior to submitting service requests each CLEC will be assigned to either the Atlanta, Georgia or Birmingham, Alabama LCSC.~~

Click here for LCSC/CRSG Contact Telephone Numbers:

<http://interconnection.bellsouth.com/centers/html/lcsc.html>

Note: Local Service Requests that are sent to the incorrect fax server will be returned as rejected.



Attachment
SN91084236

For questions/disputes concerning an LSR rejection, clarification or jeopardy notification the initial point of contact is the Fleming Island LCSC at 800-872-3116 (select appropriate ACD option to be transferred to Service Representative). In the event the LCSC is unable to resolve the issue the CLEC should follow normal escalation procedures. Click here for escalation procedures:

<http://interconnection.bellsouth.com/centers/html/lcsc.html>

Note: Local Service Requests that are sent to the incorrect fax server will be returned as rejected.

Atlanta LCSC	Telephone Number	Fax Number
Resale – Consumer	800-872-3116	800-872-7059
Resale – Small Business/Coin	800-872-3116	800-303-4426
UNE Switched Combos (Non-Complex) Wholesale Local Platform Services (WLP)	800-872-3116	877-711-0855
Billing	800-872-3116	205-321-2724

Birmingham LCSC	Telephone Number	Fax Number
Resale – Consumer	800-773-4967	888-704-9368
Resale – Small Business/Coin	800-773-4967	800-773-4970
Unbundled Network Elements and Local Number Portability	800-773-4967	888-792-6271
Wireless LNP	888-285-6123	877-711-0378
UNE Switched Combos, Non- Complex Wholesale Local Platform Services (WLP)	800-773-4967	888-704-9368
LNP to Resale, UNE-P/WLP Migrations, Non-Complex, Complex CRSG	800-773-4967 800-773-4967 205-321-7702	888-792-6271 877-672-0132 800-365-8101 or email ersg@bellsouth.com
Complex Services-Resale & UNE Switched Combos Wholesale Local Platform Services (WLP)	800-773-4967	877-672-0132
Billing	800-773-4967	205-321-2817

CCP 1996 Attachment Listed Below**ELMS6**

ACT Tables: Reqtyp N, DID Resale Service

ACT= C: LSR**Required**

ACT	ATN	BAN1
BCS (E)	CC	CCNA
D/TSENT	DDD	IMPCON
INIT	INIT-FAX NO.	INIT-TEL NO.
LSO	P	PG_OF_ (M)
PON	REQTYP	SC
TOS		

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST	IMPCON-TEL NO.	LOCQTY (E)
LSP AUTH DATE	LSP AUTH NAME	MEU (M)
NOR	PROJECT	RPON
SUP	VER	

Optional

ALBR	ALT-IMPCON*	APPTIME-DDD
BAN2	DFDT	EXP
HTQTY	LSCP	LSP AUTH
LST	REMARKS	RORD
SCA	VTA	

ACT Tables: Reqtyp N, DID Resale Service**ACT= C: EU**Required

ATN (M)	LOCNUM (M)	LOCNUM DETAIL (E)
NAME	PG_OF_ (M)	PON (M)

Conditional

AAI	ACC (M)	CITY
DQTY	EUA (M)	IWBAN
IWCON	IWCON-TEL NO.	IWO
LD1	LD2	LD3
LV1	LV2	LV3
SANO	SASD	SASF
SASN	SASS	SATH
STATE	VER (M)	ZIP (M)

Optional

LCON-NAME	LCON-TEL NO.	LOCNUM HEADER* (E)
REMARKS (M)	DQTY	

ACT= D: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSO (M)	LSP AUTH DATE (M)	LSP AUTH NAME (M)
MEU (M)	NOR (M)	PROJECT (M)
RPON (M)	SUP (M)	VER (M)

ACT Tables: Reqtyp N, DID Resale ServiceOptional

ALT-IMPCON* (M)	APPTIME-DDD (M)	BAN2 (M)
EXP (M)	IMPCON* (M)	LST (M)
REMARKS (M)	RORD (M)	VTA (M)

ACT= D: EURequired

ATN (M)	LOCNUM (M)	NAME (M)
PG_OF_ (M)	PON (M)	

Conditional

AAI (M)	DQTY (M)	EUA (M)
LD1 (M)	LD2 (M)	LD3 (M)
LV1 (M)	LV2 (M)	LV3 (M)
SANO (M)	SASD (M)	SASF (M)
SASN (M)	SASS (M)	SATH (M)
VER (M)		

Optional

LCON-NAME	LCON-TEL NO.	REMARKS (M)
DQTY (M)		

ACT= N: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	IMPCON (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	LSO (M)
P (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSP AUTH DATE (M)	LSP AUTH NAME (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

ACT Tables: Reqtyp N, DID Resale ServiceOptional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DFDT (M)	EXP (M)
LSCP (M)	LST (M)	REMARKS (M)
RORD (M)	SCA (M)	VTA (M)

ACT= N: EURequired

ATN (M)	CITY (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	ACC (M)	EUA (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
IWO (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	NCON (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	REMARKS (M)
---------------	------------------	-------------

ACT= T: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	DDDO (M)	IMPCON (M)
INIT (M)	INIT-FAX NO. (M)	INIT-TEL NO. (M)
LSO (M)	P (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		



Attachment
SN91084236

ACT Tables: Reqtyp N, DID Resale Service

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSP AUTH DATE (M)	LSP AUTH NAME (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DFDT (M)	EXP (M)
LSCP (M)	LST (M)	REMARKS (M)
RORD (M)	SCA (M)	VTA (M)

ACT= T: EU

Required

ATN (M)	CITY (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	ACC (M)	EUA (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
IWO (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	NCON (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	REMARKS (M)
---------------	------------------	-------------

ACT Tables: Reqtyp N, DID Resale Service**ACT= V: LSR**Required

ACT	ATN	BAN1
BCS (E)	CC	CCNA
D/TSENT	DDD	IMPCON
INIT	INIT-FAX NO.	INIT-TEL NO.
LSO	MI	P
PG_OF_ (M)	PON	REQTYP
SC	TOS	

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST	IMPCON-TEL NO.	LOCQTY
LSP AUTH DATE	LSP AUTH NAME	MEU (M)
NOR	PROJECT	RPON
SUP	VER	

Optional

ALBR	ALT-IMPCON*	APPTIME-DDD
BAN2	DDDO	DFDT
EXP	HTQTY	LSCP
LSP AUTH*	LST	REMARKS
RORD	VTA	

ACT= V: EURequired

ATN (M)	ELT	LOCNUM (M)
LOCNUM DETAIL (E)	NAME	PG_OF_ (M)
PON (M)	SASN	STATE
ZIP		



Attachment
SN91084236

ACT Tables: Reqtyp N, DID Resale Service

Conditional

AAI	ACC	CITY
DDDO	DQTY	EAN
EATN	EUA (M)	EUMI
FB-BILLCON	FB-BILLCON TEL NO.	FB-BILLNM
FB-CITY	FB-FLOOR	FBI
FB-ROOM	FB-SBILLNM	FB-STATE
FB-STREET	FB-ZIP	IWBAN
IWCON	IWCON-TEL NO.	IWO
LD1	LD2	LD3
LV1	LV2	LV3
NCON	SANO	SASD
SASF	SASS	SATH
VER (M)		

Optional

LCON-NAME	LCON-TEL NO.	LOCNUM HEADER (E)
REMARKS (M)	DQTY	

ACT= W: LSR

Required

ACT	ATN	BAN1
CC	CCNA	D/TSENT
DDD	INIT	INIT-FAX NO.
INIT-TEL NO.	LSO	P
PG_OF_ (M)	PON	REQTYP
SC	TOS	

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST	IMPCON-TEL NO.	LOCQTY
LSP AUTH DATE	LSP AUTH NAME	NOR
PROJECT	RPON	SUP
VER		



Attachment
SN91084236

ACT Tables: Reqtyp N, DID Resale Service

Optional

ALT-IMPCON*	APPTIME-DDD	BAN2
EXP	IMPCON*	LSP AUTH*
LST	REMARKS	RORD
VTA		

ACT= W: EU

Required

ATN (M)	LOCNUM (M)	LOCNUM DETAIL (E)
NAME	PG_OF_ (M)	PON (M)
SASN	STATE	ZIP

Conditional

AAI	CITY	DQTY
EAN	EATN	LD1
LD2	LD3	LV1
LV2	LV3	SANO
SASD	SASF	SASS
SATH	VER (M)	

Optional

LCON-NAME	LCON-TEL NO.	LOCNUM HEADER (E)
REMARKS (M)	DQTY	

Release 16.0 ELMS6 Map Ordering Source Document

ACT Tables: Reqtyp N, 2-wire DID UNE Combination

ACT= C: LSR**Required**

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	IMPCON (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	LSO (M)
P (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
MEU (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DFDT (M)	EXP (M)
HTQTY (M)	LSCP (M)	LST (M)
REMARKS (M)	RORD (M)	SCA (M)
VTA (M)		

ACT Tables: Reqtyn N, 2-wire DID UNE Combination**ACT= C: EU**Required

ATN (M)	LOCNUM (M)	NAME (M)
PG_OF_ (M)	PON (M)	

Conditional

AAI (M)	ACC (M)	CITY (M)
DQTY (M)	EUA (M)	LD1 (M)
LD2 (M)	LD3 (M)	LV1 (M)
LV2 (M)	LV3 (M)	SANO (M)
SASD (M)	SASF (M)	SASN (M)
SASS (M)	SATH (M)	STATE (M)
VER (M)	ZIP (M)	

Optional

IWO (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)	DQTY (M)	

ACT= D: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	DFDT (M)	IMPCON-TEL NO. (M)
LOCQTY (M)	LSO (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

Optional

ALT-IMPCON* (M)	APPTIME-DDD (M)	BAN2 (M)
EXP (M)	IMPCON* (M)	LST (M)
REMARKS (M)	RORD (M)	VTA (M)



Attachment
SN91084236

ACT Tables: Reqtyp N, 2-wire DID UNE Combination

ACT= D: EU

Required

ATN (M)	NAME (M)	PG_OF_ (M)
PON (M)		

Conditional

AAI (M)	DQTY (M)	EUA (M)
LD1 (M)	LD2 (M)	LD3 (M)
LV1 (M)	LV2 (M)	LV3 (M)
SANO (M)	SASD (M)	SASF (M)
SASN (M)	SASS (M)	SATH (M)
VER (M)		

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	REMARKS (M)
DQTY (M)		

ACT= N: LSR

Required

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	IMPCON (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	LSO (M)
P (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
MEU (M)	NOR (M)	PROJECT (M)
RPON (M)	SUP (M)	VER (M)

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DFDT (M)	EXP (M)
LSCP (M)	LST (M)	REMARKS (M)
RORD (M)	SCA (M)	VTA (M)

ACT Tables: Reqtyp N, 2-wire DID UNE Combination**ACT= N: EU**Required

ATN (M)	CITY (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	ACC (M)	EUA (M)
IWCON (M)	IWCON-TEL NO. (M)	LD1 (M)
LD2 (M)	LD3 (M)	LV1 (M)
LV2 (M)	LV3 (M)	NCON (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)		

ACT= V: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	IMPCON (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	LSO (M)
MI (M)	P (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSP AUTH DATE (M)	LSP AUTH NAME (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	



Attachment
SN91084236

ACT Tables: Reqtyp N, 2-wire DID UNE Combination

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DDDO (M)	DFDT (M)
EXP (M)	HTQTY (M)	LSCP (M)
LSP AUTH* (M)	LST (M)	REMARKS (M)
RORD (M)	VTA (M)	

ACT= V: EU

Required

ATN (M)	ELT (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	ACC (M)	CITY (M)
DQTY (M)	EAN (M)	EATN (M)
EUA (M)	EUMI (M)	FB-BILLCON (M)
FB-BILLCON TEL NO. (M)	FB-BILLNM (M)	FB-CITY (M)
FB-FLOOR (M)	FBI (M)	FB-ROOM (M)
FB-SBILLNM (M)	FB-STATE (M)	FB-STREET (M)
FB-ZIP (M)	IWCON (M)	IWCON-TEL NO. (M)
LD1 (M)	LD2 (M)	LD3 (M)
LV1 (M)	LV2 (M)	LV3 (M)
NCON (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)	DQTY (M)	

Release 16.0 ELMS6 Map Ordering Source DocumentACT Tables: Reqtyn N, PBX Resale Service**ACT= C: LSR****Required**

ACT	ATN	BAN1
BCS (E)	CC	CCNA (E)
D/TSENT	DDD	IMPCON
INIT	INIT-FAX NO.	INIT-TEL NO.
LSO	P	PG_OF_ (M)
PON	REQTYP	SC
TOS		

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST	IMPCON-TEL NO.	LOCQTY
LSP AUTH DATE	LSP AUTH NAME	MEU (M)
PROJECT	RPON	SUP
VER		

Optional

ALBR	ALT-IMPCON*	APPTIME-DDD
BAN2	DFDT	EXP
HTQTY	LSCP	LSP AUTH
LST	REMARKS	RORD
SCA	VTA	

ACT Tables: Reqtyp N, PBX Resale Service**ACT= C: EU**Required

ATN (M)	LOCNUM (M)	LOCNUM DETAIL (E)
NAME	PG_OF_ (M)	PON (M)

Conditional

AAI	ACC	CITY
DQTY	EUA	IWBAN
IWCON	IWCON-TEL NO.	IWO
LD1	LD2	LD3
LV1	LV2	LV3
SANO	SASD	SASF
SASN	SASS	SATH
STATE	VER (M)	ZIP

Optional

LCON-NAME	LCON-TEL NO.	LOCNUM HEADER (E)
REMARKS (M)	DQTY	

ACT= D: LSRRequired

ACT	ATN	BAN1
CC	CCNA (E)	D/TSENT
DDD	INIT	INIT-FAX NO.
INIT-TEL NO.	P	PG_OF_ (M)
PON	REQTYP	SC
TOS		

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST	IMPCON-TEL NO.	LOCQTY
LSO	LSP AUTH DATE	LSP AUTH NAME
MEU (M)	NOR	PROJECT
RPON	SUP	VER



Attachment
SN91084236

ACT Tables: Reqtyp N, PBX Resale Service

Optional

ALT-IMPCON*	APPTIME-DDD	BAN2
DFDT	EXP	IMPCON*
LSP AUTH	LST	REMARKS
RORD	VTA (M)	

ACT= D: EU

Required

ATN (M)	LOCNUM (M)	NAME
PG_OF_ (M)	PON (M)	

Conditional

AAI	DQTY (M)	EUA
LD1	LD2	LD3
LV1	LV2	LV3
SANO	SASD	SASF
SASN	SASS	SATH
VER (M)		

Optional

LCON-NAME	LCON-TEL NO.	REMARKS (M)
DQTY (M)		

ACT= N: LSR

Required

ACT	ATN	BAN1
CC	CCNA (E)	D/TSENT
DDD	IMPCON	INIT
INIT-FAX NO.	INIT-TEL NO.	P
PG_OF_ (M)	PON	REQTYP
SC	TOS	

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST (E)	IMPCON-TEL NO.	LOCQTY
LSP AUTH DATE	LSP AUTH NAME	MEU (M)
NOR	PROJECT	RPON
SUP	VER	



Attachment
SN91084236

ACT Tables: Reqtyp N, PBX Resale Service

Optional

ALBR	ALT-IMPCON*	APPTIME-DDD
BAN2	DFDT	EXP (M)
HTQTY	LSCP	LSP AUTH
LST	REMARKS	RORD (M)
RPON (M)	SCA (M)	VTA (M)

ACT= N: EU

Required

ATN (M)	CITY	LOCNUM (M)
NAME	PG_OF_ (M)	PON (M)
SASN	STATE	ZIP

Conditional

AAI	ACC	EUA
IWBAN	IWCON	IWCON-TEL NO.
IWO	LD1	LD2
LD3	LV1	LV2
LV3	NCON	SANO
SASD	SASF	SASS
SATH	VER (M)	

Optional

LCON-NAME	LCON-TEL NO.	REMARKS (M)
-----------	--------------	-------------

ACT= T: LSR

Required

ACT	ATN	BAN1
CC	CCNA (E)	D/TSENT
DDD	DDDO	IMPCON
INIT	INIT-FAX NO.	INIT-TEL NO.
LSO	P	PG_OF_ (M)
PON	REQTYP	SC
TOS		



Attachment
SN91084236

ACT Tables: Reqtyp N, PBX Resale Service

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST (E)	IMPCON-TEL NO.	LOCQTY
LSP AUTH DATE	LSP AUTH NAME	MEU (M)
NOR	PROJECT	RPON
SUP	VER	

Optional

ALBR	ALT-IMPCON*	APPTIME-DDD
BAN2	DFDT	EXP (M)
HTQTY	LSCP (M)	LSP AUTH
LST	REMARKS (M)	RORD
RPON	SCA	VTA (M)

ACT= T: EU

Required

ATN (M)	CITY	LOCNUM (M)
NAME	PG_OF_ (M)	PON (M)
SASN	STATE	ZIP

Conditional

AAI	ACC	EUA
IWBAN	IWCON	IWCON-TEL NO.
IWO	LD1	LD2
LD3	LV1	LV2
LV3	NCON	SANO
SASD	SASF	SASS
SATH	VER (M)	

Optional

LCON-NAME	LCON-TEL NO.	REMARKS (M)
-----------	--------------	-------------

ACT Tables: Reqtyp N, PBX Resale Service**ACT= V: LSR**Required

ACT	ATN	BAN1
BCS (E)	CC	CCNA (E)
D/TSENT	DDD	IMPCON
INIT	INIT-FAX NO.	INIT-TEL NO.
LSO	MI	P
PG_OF_ (M)	PON	REQTYP
SC	TOS	

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST	IMPCON-TEL NO.	LOCQTY
LSP AUTH DATE	LSP AUTH NAME	MEU (M)
NOR	PROJECT	RPON
SUP	VER	

Optional

ALBR	ALT-IMPCON*	APPTIME-DDD
BAN2	DDDO	DFDT
EXP (M)	HTQTY	LSCP
LSP AUTH	LST	REMARKS
RORD (M)	VTA (M)	

ACT= V: EURequired

ATN (M)	ELT	LOCNUM (M)
LOCNUM DETAIL (E)	NAME	PG_OF_ (M)
PON (M)	SASN	STATE
ZIP		

ACT Tables: Reqtyp N, PBX Resale ServiceConditional

AAI	ACC	CITY
DQTY	EAN	EATN
EUA	EUMI	FB-BILLCON
FB-BILLCON TEL NO.	FB-BILLNM	FB-CITY
FB-FLOOR	FBI	FB-ROOM
FB-SBILLNM	FB-STATE	FB-STREET
FB-ZIP	IWBAN	IWCON
IWCON-TEL NO.	IWO	LD1
LD2	LD3	LV1
LV2	LV3	NCON
SANO	SASD	SASF
SASS	SATH	VER (M)

Optional

LCON-NAME	LCON-TEL NO.	LOCNUM HEADER (E)
REMARKS (M)	DQTY	

ACT= W: LSRRequired

ACT	ATN	BAN1
CC	CCNA (E)	D/TSENT
DDD	INIT	INIT-FAX NO.
INIT-TEL NO.	LSO	P
PG_OF_ (M)	PON	REQTYP
SC	TOS	

Conditional

ALT-IMPCON-TEL NO.	BI1	BI2
CUST (E)	IMPCON-TEL NO.	LOCQTY
LSP AUTH DATE	LSP AUTH NAME	NOR
PROJECT	RPON	SUP
VER		



Attachment
SN91084236

ACT Tables: Reqtyp N, PBX Resale Service

Optional

ALT-IMPCON*	APPTIME-DDD	BAN2
EXP	IMPCON*	LSP AUTH
LST	REMARKS	RORD (M)
VTA (M)		

ACT= W: EU

Required

ATN (M)	LOCNUM (M)	LOCNUM DETAIL (E)
NAME	PG_OF_ (M)	PON (M)
SASN	STATE	ZIP

Conditional

AAI	CITY	DQTY
EAN	EATN	LD1
LD2	LD3	LV1
LV2	LV3	SANO
SASD	SASF	SASS
SATH	VER (M)	

Optional

LCON-NAME	LCON-TEL NO.	LOCNUM HEADER (E)
REMARKS (M)	DQTY	

Release 16.0 ELMS6 Map Ordering Source Document*ACT Tables: Reqtyp N, PBX Stand Alone Port***ACT= C: LSR****Required**

ACT (M)	ACTL (M)	ATN (M)
BAN1 (M)	CC (M)	CCNA (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
INIT (M)	INIT-FAX NO. (M)	INIT-TEL NO. (M)
LSO (M)	P (M)	PBT (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
BI1 (M)	BI2 (M)	CUST (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	LSP AUTH DATE (M)
LSP AUTH NAME (M)	MEU (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DFDT (M)	EXP (M)
HTQTY (M)	LSCP (M)	LSP AUTH (M)
LST (M)	PORTTYP (M)	REMARKS (M)
RORD (M)	SCA (M)	VTA (M)

ACT Tables: Reqtyp N, PBX Stand Alone Port**ACT= C: EU**Required

ATN (M)	LOCNUM (M)	NAME (M)
PG_OF_ (M)	PON (M)	

Conditional

AAI (M)	ACC (M)	CITY (M)
DQTY (M)	EUA (M)	IWCON (M)
IWCON-TEL NO. (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	SANO (M)	SASD (M)
SASF (M)	SASN (M)	SASS (M)
SATH (M)	STATE (M)	VER (M)
ZIP (M)		

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)	DQTY (M)	

ACT= D: LSRRequired

ACT (M)	ACTL (M)	ATN (M)
BAN1 (M)	CC (M)	CCNA (M)
D/TSENT (M)	DDD (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	LST (M)
P (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
BI1 (M)	BI2 (M)	CUST (M)
LOCQTY (M)	LSO (M)	LSP AUTH DATE (M)
LSP AUTH NAME (M)	MEU (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

ACT Tables: Reqtyp N, PBX Stand Alone PortOptional

ALT-IMPCON* (M)	APPTIME-DDD (M)	BAN2 (M)
EXP (M)	IMPCON* (M)	LSP AUTH (M)
LST (M)	REMARKS (M)	RORD (M)
VTA (M)		

ACT= D: EURequired

ATN (M)	LOCNUM (M)	NAME (M)
PG_OF_ (M)	PON (M)	

Conditional

AAI (M)	ACC (M)	DQTY (M)
EUA (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	SANO (M)	SASD (M)
SASF (M)	SASN (M)	SASS (M)
SATH (M)	VER (M)	

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	REMARKS (M)
DQTY (M)		

ACT= N: LSRRequired

ACT (M)	ACTL (M)	ATN (M)
BAN1 (M)	CC (M)	CCNA (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
INIT (M)	INIT-FAX NO. (M)	INIT-TEL NO. (M)
LSO (M)	P (M)	PBT (M)
PG_OF_ (M)	PON (M)	PORTTYP (M)
REQTYP (M)	SC (M)	TOS (M)



Attachment
SN91084236

ACT Tables: Reqtyp N, PBX Stand Alone Port

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSP AUTH DATE (M)	LSP AUTH NAME (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DFDT (M)	EXP (M)
LSCP (M)	LSP AUTH (M)	LST (M)
REMARKS (M)	RORD (M)	SCA (M)
VTA (M)		

ACT= N: EU

Required

ATN (M)	CITY (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	ACC (M)	IWCON (M)
IWCON-TEL NO. (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)		

Release 16.0 ELMS6 Map Ordering Source DocumentACT Tables: Reqttyp N, PBX UNE Combo**ACT= C: LSR****Required**

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	IMPCON (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	LSO (M)
P (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSP AUTH DATE (M)	LSP AUTH NAME (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DFDT (M)	EXP (M)
HTQTY (M)	LSCP (M)	LSP AUTH (M)
LST (M)	REMARKS (M)	RORD (M)
SCA (M)	VTA (M)	

ACT Tables: Reqtyp N, PBX UNE Combo**ACT= C: EU**Required

ATN (M)	LOCNUM (M)	NAME (M)
PG_OF_ (M)	PON (M)	

Conditional

AAI (M)	ACC (M)	CITY (M)
DQTY (M)	EUA (M)	IMPCON-TEL NO. (M)
IWCON (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	SANO (M)	SASD (M)
SASF (M)	SASN (M)	SASS (M)
SATH (M)	STATE (M)	VER (M)
ZIP (M)		

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)	DQTY (M)	

ACT= D: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSO (M)	LSP AUTH DATE (M)	LSP AUTH NAME (M)
MEU (M)	NOR (M)	PROJECT (M)
RPON (M)	SUP (M)	VER (M)

ACT Tables: Reqtyp N, PBX UNE ComboOptional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	EXP (M)	IMPCON* (M)
LSP AUTH (M)	LST (M)	REMARKS (M)
RORD (M)	VTA (M)	

ACT= D: EURequired

ATN (M)	LOCNUM (M)	NAME (M)
PG_OF_ (M)	PON (M)	

Conditional

AAI (M)	DQTY (M)	EUA (M)
LD1 (M)	LD2 (M)	LD3 (M)
LV1 (M)	LV2 (M)	LV3 (M)
SANO (M)	SASD (M)	SASF (M)
SASN (M)	SASS (M)	SATH (M)
VER (M)		

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	REMARKS (M)
DQTY (M)		

ACT= N: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	IMPCON (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	P (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSP AUTH DATE (M)	LSP AUTH NAME (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

ACT Tables: Reqtyp N, PBX UNE ComboOptional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DFDT (M)	LSCP (M)
LSP AUTH (M)	LST (M)	REMARKS (M)
RORD (M)	SCA (M)	VTA (M)

ACT= N: EURequired

ATN (M)	CITY (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	EUA (M)	IWCON (M)
IWCON-TEL NO. (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	NCON (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)		

ACT= V: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	IMPCON (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	MI (M)
P (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

ACT Tables: Reqtyp N, PBX UNE ComboConditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	BI2 (M)
CUST (M)	IMPCON-TEL NO. (M)	LOCQTY (M)
LSP AUTH DATE (M)	LSP AUTH NAME (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
BAN2 (M)	DDDO (M)	DFDT (M)
EXP (M)	HTQTY (M)	LSCP (M)
LSP AUTH (M)	LST (M)	REMARKS (M)
RORD (M)	VTM (M)	

ACT= V: EURequired

ATN (M)	ELT (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	ACC (M)	CITY (M)
DQTY (M)	EAN (M)	EATN (M)
EUA (M)	EUMI (M)	FB-BILLCON (M)
FB-BILLCON TEL NO. (M)	FB-BILLNM (M)	FB-CITY (M)
FB-FLOOR (M)	FBI (M)	FB-ROOM (M)
FB-SBILLNM (M)	FB-STATE (M)	FB-STREET (M)
FB-ZIP (M)	IWCON (M)	IWCON-TEL NO. (M)
LD1 (M)	LD2 (M)	LD3 (M)
LV1 (M)	LV2 (M)	LV3 (M)
NCON (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)	DQTY (M)	

ELMS6

**Reqtyp M, Complex
UNE-P/WLP Digital Direct Integration Termination Service
(DDITS) - Trunk Service DDITS UNE Combinations (Trunk
Service)****RCO Tables***ACT Tables: Reqtyp M, UNE-P/WLP DDITS - Trunk Service***ACT= C: LSR****Required**

ACT (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

Conditional

ALT-IMPCON-TEL NO. (M)	AN (M)	ATN (M)
BAN2 (M)	BI2 (M)	CIC (M)
DFDT (M)	LOCQTY (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
LSCP (M)	LST (M)	REMARKS (M)
SCA (M)	VTA (M)	

ACT= C: EU**Required**

NAME (M)	PG_OF_ (M)	PON (M)
----------	------------	---------

ACT Tables: Reqtyp M, UNE-P/WLP DDITS - Trunk ServiceConditional

AN (M)	ATN (M)	DNUM (M)
DQTY (M)	IWCON (M)	IWCON-TEL NO. (M)
SASS (M)	VER (M)	

Optional

DISC NBR* (M)	IWO* (M)	LCON-NAME (M)
LCON-TEL NO. (M)	LOCNUM HEADER (M)	DQTY (M)

ACT= D: LSRRequired

ACT (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
INIT (M)	INIT-FAX NO. (M)	INIT-TEL NO. (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

ALT-IMPCON-TEL NO. (M)	AN (M)	ATN (M)
BAN2 (M)	BI2 (M)	CIC (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	NOR (M)
RPON (M)	SUP (M)	VER (M)

Optional

ALT-IMPCON* (M)	DFDT (M)	IMPCON* (M)
-----------------	----------	-------------

ACT= D: EURequired

NAME (M)	PG_OF_ (M)	PON (M)
----------	------------	---------

Conditional

AN (M)	ATN (M)	DISC NBR (M)
DNUM (M)	DQTY (M)	TC NAME (M)
TC PER (M)	TC TO PRI (M)	TC TO SEC (M)
TCID (M)	VER (M)	

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	LOCNUM HEADER (M)
TC OPT* (M)	TER (M)	DQTY (M)

ACT Tables: Reqtyp M, UNE-P/WLP DDITS - Trunk Service**ACT= N: LSR****Required**

ACT (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

Conditional

ALT-IMPCON-TEL NO. (M)	AN (M)	ATN (M)
BAN2 (M)	BI2 (M)	CIC (M)
DFDT (M)	LOCQTY (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
LSCP (M)	LST (M)	REMARKS (M)
SCA (M)	VTA (M)	

ACT= N: EU**Required**

CITY (M)	NAME (M)	PG_OF_ (M)
PON (M)	SASN (M)	STATE (M)
ZIP (M)		

Conditional

AAI (M)	ACC (M)	AN (M)
ATN (M)	IWCON (M)	IWCON-TEL NO. (M)
LD1 (M)	LD2 (M)	LD3 (M)
LV1 (M)	LV2 (M)	LV3 (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
LOCNUM HEADER (M)	WSOP (M)	

ACT Tables: Reqtyp M, UNE-P/WLP DDITS - Trunk Service**ACT= V: LSR****Required**

ACT (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
DSGCON (M)	DSGCON-TEL NO. (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

Conditional

ALT-IMPCON-TEL NO. (M)	AN (M)	ATN (M)
BAN2 (M)	BI2 (M)	CIC (M)
DFDT (M)	DSGCON-CITY (M)	DSGCON-STATE (M)
DSGCON-STREET (M)	LOCQTY (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
CHC* (M)	EXP (M)	LSCP (M)
MI (M)	REMARKS (M)	VTA (M)

ACT= V: EU**Required**

CITY (M)	ELT (M)	NAME (M)
PG_OF_ (M)	PON (M)	SASN (M)
STATE (M)	ZIP (M)	

ACT Tables: Reqtyp M, UNE-P/WLP DDITS - Trunk Service**Conditional**

AAI (M)	ACC (M)	AN (M)
ATN (M)	DISC NBR (M)	DNUM (M)
DQTY (M)	EAN (M)	EATN (M)
EUMI (M)	FB-BILLCON TEL NO. (M)	FB-BILLNM (M)
FB-CITY (M)	FB-FLOOR (M)	FBI (M)
FB-ROOM (M)	FB-SBILLNM (M)	FB-STATE (M)
FB-STREET (M)	FB-ZIP (M)	IWCON (M)
IWCON-TEL NO. (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
TC NAME (M)	TC PER (M)	TC TO PRI (M)
TC TO SEC (M)	VER (M)	

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
LOCNUM HEADER (M)	TC OPT* (M)	WSOP (M)
DQTY (M)		

UNE-P/WLP 4-Wire DS1 Loop with Channelization with Port (Trunk Service)

RCO TablesACT Tables: Reqtyp M, UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)**ACT= C: LSR****Required**

ACT (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

Conditional

ALT-IMPCON-TEL NO. (M)	AN (M)	ATN (M)
BAN2 (M)	BI2 (M)	CIC (M)
DFDT (M)	LOCQTY (M)	NOR (M)



Attachment
SN91084236

PROJECT (M)
VER (M)

RPON (M)

SUP (M)

Optional

ALBR (M)
LSCP (M)
SCA (M)

ALT-IMPCON* (M)
LST (M)
VTA (M)

APPTIME-DDD (M)
REMARKS (M)

ACT= C: EU

Required

NAME (M)

PG_OF_ (M)

PON (M)

ACT Tables: Reqtyp M, UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)Conditional

AAI (M)	AN (M)	ATN (M)
DNUM (M)	DQTY (M)	IWCON (M)
IWCON-TEL NO. (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		

Optional

DISC NBR* (M)	IWO* (M)	LCON-NAME (M)
LCON-TEL NO. (M)	LOCNUM HEADER (M)	SASN (M)

DQTY (M)**ACT= D: LSR**Required

ACT (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
INIT (M)	INIT-FAX NO. (M)	INIT-TEL NO. (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

ALT-IMPCON-TEL NO. (M)	AN (M)	ATN (M)
BAN2 (M)	BI2 (M)	CIC (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	NOR (M)
RPON (M)	SUP (M)	VER (M)

Optional

ALT-IMPCON* (M)	DFDT (M)	IMPCON* (M)
-----------------	----------	-------------

ACT= D: EURequired

NAME (M)	PG_OF_ (M)	PON (M)
----------	------------	---------

Conditional

AN (M)	ATN (M)	DISC NBR (M)
DNUM (M)	DQTY (M)	TC NAME (M)
TC PER (M)	TC TO PRI (M)	TC TO SEC (M)
TCID (M)	VER (M)	

ACT Tables: Reqtyp M, UNE-P/WLP 4-wire DSI Loop with Channelization with Port (Trunk Service)**Optional**

FBI* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
LOCNUM HEADER (M)	TC OPT* (M)	TER (M)
DQTY (M)		

ACT= N: LSR**Required**

ACT (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

Conditional

ALT-IMPCON-TEL NO. (M)	AN (M)	ATN (M)
BAN2 (M)	BI2 (M)	CIC (M)
DFDT (M)	LOCQTY (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
LSCP (M)	LST (M)	REMARKS (M)
SCA (M)	VTA (M)	

ACT= N: EU**Required**

CITY (M)	NAME (M)	PG_OF_ (M)
PON (M)	SASN (M)	STATE (M)
ZIP (M)		

ACT Tables: Reqtyp M, UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)**Conditional**

AAI (M)	ACC (M)	AN (M)
ATN (M)	DNUM (M)	DQTY (M)
IWCON (M)	IWCON-TEL NO. (M)	LD1 (M)
LD2 (M)	LD3 (M)	LV1 (M)
LV2 (M)	LV3 (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

DISC NBR* (M)	IWO* (M)	LCON-NAME (M)
LCON-TEL NO. (M)	LOCNUM (M)	WSOP (M)

DQTY (M)**ACT= V: LSR****Required**

ACT (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	MI (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

ALT-IMPCON-TEL NO. (M)	AN (M)	ATN (M)
BAN2 (M)	BI2 (M)	CIC (M)
DFDT (M)	DSGCON-CITY (M)	DSGCON-STATE (M)
DSGCON-STREET (M)	LOCQTY (M)	MI (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
CHC* (M)	DFDT (M)	DRC* (M)
DSGCON-FAX NO. (M)	EXP (M)	LSCP (M)
REMARKS (M)	VTA (M)	

ACT Tables: Reqty M, UNE-P/WLP 4-wire DSI Loop with Channelization with Port (Trunk Service)

ACT= V: EU**Required**

CITY (M)	ELT (M)	NAME (M)
PG_OF_ (M)	PON (M)	SASN (M)
STATE (M)	ZIP (M)	

Conditional

AAI (M)	ACC (M)	AN (M)
ATN (M)	DISC NBR (M)	DNUM (M)
DQTY (M)	EAN (M)	EATN (M)
EUMI (M)	FB-BILLCON TEL NO. (M)	FB-BILLNM (M)
FB-CITY (M)	FB-FLOOR (M)	FBI (M)
FB-ROOM (M)	FB-SBILLNM (M)	FB-STATE (M)
FB-STREET (M)	FB-ZIP (M)	IWCON (M)
IWCON-TEL NO. (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
TC NAME (M)	TC PER (M)	TC TO PRI (M)
TC TO SEC (M)	VER (M)	

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
LOCNUM HEADER (M)	TC OPT* (M)	WSOP (M)
DQTY (M)		

CCP 1997 Attachment Listed Below**LOH-17.0A-ELMS6****ACT – Activity Type****LSR Form/Screen**

(LSOG6 / ELMS6 map)

Definition:

Identifies the activity involved in this service request.

Definition Notes:

None

Valid Entries:

Entry	Description
Activity	Activity Description
N	New Installation and or account
C	Change an existing account, e.g., rearrangement, partial disconnect or addition
D	Disconnection
L	Suspend full account
T	Move of an end user location to a new location, where LSP is not changing
R	Record activity - ordering administrative changes
V	Conversion of service to a new LSP
W	Conversion of service to new LSP as is
S	Suspend / restore partial account
B	Restore full account / restore denied account
Y	Deny

Valid Entry Notes:

NOTE 1: REQ TYP AB / ACT is V is only applicable for conversions from Retail, Resale, Non-Complex UNE-P/WLP services, Complex UNE-P/WLP, BRI or PBX services where the Telephone Number resides in the BellSouth® switch.

NOTE 2: When the REQ TYP is A and the ACT is T, the serving wire center (Central Office) cannot be changed.

NOTE 3: When the ACT is T, the LSP may not be changed.

NOTE 4: Valid entry of C is used for INP to LNP conversions when the NPT is D (LNP).

NOTE 5: When the CC or NNSP field is populated with a wireless OCN the only valid entry in this field is V.

NOTE 6: [BULK] ACT of V is only valid ACT for Reqtyp B UNE to UNE Bulk.

NOTE 7: When the request is for directory delivery only, the ACT data must be R.

NOTE 8: ACT of V is only valid ACT for LNP to Resale UNE-P/WLP Migration (REQTYP E or M), and the SC=LCSL

Data Characteristics:

1 alpha character

Examples:

V

Conditional Usage Notes:

None

Business Rules

Rule 1: On a supplement to a request this field carries the original activity type.

Rule 2: When the ACT field involves a change, the PON should be canceled and a new PON submitted.

Rule 3: When ACT is S, the LNA must equal "L" or "B". This allows the end user to seasonally suspend or restore some of the lines on an account.

Manual:

Rule ~~4~~### : For split billing of a multi-line account, it is necessary to submit 2 LSR's.
LSR#1 - (ACT=C, LNA=D) Removes the line from the existing account.
LSR#2 - (ACT=N, LNA=N) Establishes the NEW account.

Rule ~~5~~###: (REQTYP B and C) Use ACT of C, when NPT is D (LNP) on LSNP or NP form/screen for INP to LNP conversions.

***** End of definition for ACT / LSR form screen *****

LACT – Listing Activity Indicator

DL Form/Screen

(LSOG6 / ELMS6 map)

Definition:

Identifies the activity involved for this listing request.

Definition Notes:

None

Valid Entries:

Entry	Description
N	New Listing
D	Delete Listing
I	Change Listing (new data to be inserted)
O	Change Listing (old data)
Z	No change to listing

ACT / LACT COMBINATIONS

If ACT is: Then LACT is: (If there is Listing activity)

B	Prohibited
C	N, D, I or O
D	Prohibited
L	Prohibited
N	N
R	N, D, I or O
S	Prohibited
T	N
V	N, D or Z
W	Prohibited
Y	Prohibited

Valid Entry Notes:

NOTE 1: An LACT entry of Z is prohibited if there is no existing listing for the LTN.

NOTE 2: When the LNA, TACT or TNA is D, LACT must be D and the LTN must match the TNS.

NOTE 3: When the LNA, TACT or TNA is N and the telephone number being added matches the LTN , then if LACT is populated the LACT data must be N.

NOTE4: The valid entry of D is only allowed for ACT V with REQ TYP E or M, when it is being used for a listing other than the main listing for the account **and the request is not changing from Residence to Business or Business to Residence.**

NOTE 5: When REQ TYP is B or C and the ACT is V the only valid values are N or Z.

NOTE 6: When the REQ TYP is E or M and the ACT is V and the class of service is not changing from residence to business or business to residence, the only valid values are D, N or Z.

NOTE 7: The valid entry of "D" is prohibited when the ACT is R and the 2nd and 3rd characters of the RTY field are ML.

NOTE 8: The valid entry of "O" and "I" are prohibited when the ACT is "V".

NOTE 9: When the ACT is "N" the only valid entry for this field is "N" .

NOTE 10: LACT of Z is prohibited when the REQ TYP is E (Non-Complex) or M (Switched Combinations RES/BUS) with ACT of C when the request is changing from a residence to business or business to residence class of service.

NOTE 11: When the REQ TYP IS E or M and the ACT is V and the class of service is changing from residence to business or business to residence, the only valid values are D and/or N.

NOTE 12: When RTY 2nd and 3rd characters are ML, and ACT=V, and MI=A, LACT N is required.

Data Characteristics:

1 alpha character

Examples:

N

SW

Conditional Usage Notes:

Note 1: Required when establishing, deleting or changing data in the listing control, listing indicator or listing instructions, otherwise prohibited.

Note 2: Required when the DLNUM is populated.

Note 3: When the LACT is O, the LACT of I is required.

Note 4: When the LACT is I, the LACT of O is required.

Note 5: Prohibited when ELT is populated with A or B.

Note 6: Required when ELT is populated with C.

Business Rules

Rule 1: When changing an existing customer end user listing, two transactions listing segments are required. The first transaction would have a LACT entry of O to specify the data to be deleted. The second transaction would have a LACT entry of I to specify the new data.

REQTYP – Request Type

LSR Form/Screen

(LSOG6 / ELMS6 map)

Definition:

Identifies the type of service being requested and the status of the request.

Definition Notes:

None

Valid Entries:

Entry	Description
-------	-------------

REQTYP (1st character)

A	Loop
---	------

B	Loop with Number Portability
---	------------------------------

C	Number Portability
---	--------------------

E	Resale
---	--------

F	Port
---	------

J	Directory Listing and Directory Assistance
---	--

K	Private Line/Synchronet
---	-------------------------

M	Unbundled Network Element Switched Combinations
---	---

N	DID/PBX
---	---------

P	BellSouth® CENTREX Resale, ESSX®, and MultiServ®/MultiServ PLUS®
---	--

REQTYP (2nd character)

B	Firm Order
---	------------

Valid Entry Notes:

NOTE 1: The first character of the REQTYPE specifies the type of service.

NOTE 2: The second character of REQTYPE is always 'B'.

NOTE 3: When the CC or NNSP field is populated with a wireless OCN the only valid entry allowed in this field is "CB".

NOTE 4: When the 1st character of the REQTYPE begins with K or P, the LSR must be submitted manually.

NOTE 5: When the request is for directory delivery only, the REQTYPE must be J.

Data Characteristics:

2 alpha characters

Examples:

AB

Conditional Usage Notes:

None

Business Rules

Rule 1: A submitted request is always a Firm Order.



Attachment
SN91084236

Rule 2: If a change in REQTyp is being made, the original PON must be canceled and a new PON sent with the new REQTyp.

Rule 3: Stand-alone wireless listing request must be submitted to the Wireless Service Center via a Wireless Service Request (WSR). When submitted to the LCSC, a stand-alone listing request for Wireless listings will be returned to the originator.

Rule 4: A request for wireless listings may be submitted to the LCSC for processing when the REQTyp is C, and the CC or NNSP field is populated with a wireless OCN.

Rule ##: When REQTyp is J and the LSR request is changing the service type from Residence to Business or Business to Residence, the existing class of service (CS) on the existing CSR must be LNPRL or LNPBL.

***** End of definition for REQTyp / LSR form screen *****

CCP 2011 Attachment Listed Below**ELMS6****LSO – Local Service Office****LSR Form/Screen**

(LSOG6 / ELMS6 map)

Definition:

Identifies the NPA / NXX of the local or alternate serving central office of the customer location or primary location of the end user.

Definition Notes:

None

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

6 numeric characters

Examples:

201885

Conditional Usage Notes:

Note 1: Excluding (REQTYP A Local Channels , EELS and Interooffice Channels) this field is required when the ACT is C, D, N, T or V and the LNA is not N.

Note 2: Required when the REQTYP is E and the 2nd character of the TOS is H.

Note 3: Required when the REQTYP is F.

Electronic:

Note 4: Required **on REQTYP N**, when the 2nd character of the TOS is Q, and the ACT is C, V or W.

Manual:

Note 5: Required when USOCs RCF++, RD5++, UEPVB or UEPVR are populated.

Note 6: Required when 4th character of TOS code is F.

Note 7: Required for REQTYP E (Non-Complex) and M (Non-Complex) and the product type is On/Off Premise extensions/ Different Premise Address (DPA).



Attachment
SN91084236

Note 8: Excluding (REQTYP A Local Channels, EELS and Interoffice Channels), this field is optional when the ACT is C, D, N, T or V and the LNA is N.

Business Rules

Rule 1: Must be a valid BellSouth® NPA NXX.

***** End of definition for LSO / LSR form screen **

CCP 2036 Attachment Listed Below**TAG/LENS****ELMS6*****Parsed Customer Record Response (PCSRR)***

This message is used to return customer record information in a parsed format. Since customer records can be very large, this message size will be limited to one (1) MG of data. The parsed CSR response contains the parsed sections and will also contain unparsed sections in a block of data. The following sections will return parsed and unparsed and the unparsed sections will be returned in a block of data (see table).

The Bellsouth Parsed CSR transaction is intended for noncomplex accounts. The Parse transaction supports POTS accounts and currently doesn't support complex accounts.

IDENT section

LISTING section

DIRECTORY section

TRAFFIC section

BILLING section

Note: Local Service Freeze (LSF) will be returned when indicated on the CSR in states where LSF is a valid offering.

S&E section

Ported out lines

Related account information

Billing transfer section

Completed activity section

Remarks section

Error message information

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
PCSRR Message								
TXNUM (Replaces INQ- NUM)	TXNUM	Up to 16	A/N	Transaction Number – Identifies the customer provided tracking number to link the inquiry with the response	X	X		0, 1
TXTYP	TXTYP	1	A	Transaction Type – Identifies the type of transaction.	X	X	E or T	0, 1
ATN	ATN	10	N	Account telephone Number – Identifies the account telephone number of the end user.	X	X		0, 1
AN	AN	10 or 13	A/N	Account Number - Identifies the customer account number.	X	X		0, 1

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
PSO		Up to 10	A/N	<p>Pending Service Order</p> <p>Identifies pending service orders for this account.</p> <p>Note 1: This field is returned on a response when a pending service order condition exists on the CSR account being requested.</p> <p>The PSO Indicator will indicate if there is either a pending service order, multiple service orders or no service order as follows:</p> <p>A pending service order = The PSO Indicator will provide the SHAK number.</p> <p>Multiple service orders= "MULTI" will be returned</p> <p>No pending service orders="NONE" will be returned</p>				
Customer Record Info								
DT-SENT	DT-SENT	8	N	Date Sent transaction is sent.	X	X	CCYYMMDD	0, 1

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
TM-SENT	TM-SENT	6	N	Time transaction is sent	X	X	HHMMSS	0, 1
CCNA	CCNA	3	A	Carrier Name Abbreviation - Identifies the Common Language IAC Code for the customer submitting the inquiry and receiving the response.		X	X	0, 1
CC	CC	4	A/N	Company Code Identifies the exchange carrier generating the inquiry.				0, 1
Identification Section								
ATN	ATN	10	N	Account Telephone Number -	X	X		0, 1
AN	AN	10 or 13	A/N	Account Number -	X	X		0, 1
TOS	TOS	4	A/N	Type of Service - Identifies the type of service for the line offered. Can be identified as residence, business, government or coin from the data following TYPE in the IDENT section of the CSR. The second and third characters will not be derived and returned. The TAG return format will be number, space, space, space	X	X	TAG: Character 1: 1,2,3,4 Character 2: space Character 3: space Character 4: space	0, 1

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
CS	CS	3 or 5	A/N	Class of Service - Identifies the basic class of service for the line ordered. Can be identified from the unfielded IDENT section in the first line of the CSR after EXCH. When found, return the data in the CS field of the BCS field.	X	X	3-5 character class of service	0, 1
IDENT-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Identification Section Data Block (unparsed data)
Listing Section: End User Location								
SANO	SANO	Up to 8	A/N	Service Address Number Identifies the number of the service address.	X	X		0, 1
SASF	SASF	Up to 4	A/N	Service Address Number Suffix Identifies the suffix for the address number of the service address.	X	X		0, 1
SASD	SASD	Up to 2	A	Service Address Street Directional Prefix Identifies the street directional prefix of the service address.	X	X		0, 1
SASN	SASN	Up to 44	A/N	Service Address Street Name Identifies the street name of the service address.	X	X		0, 1

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
SATH	SATH	Up to 6	A/N	Service Address Street Type Identifies the thoroughfare portion of the street name of the service address.	X	X		0, 1
SASS	SASS	Up to 2	A	Service Address Street Directional Suffix Identifies the street directional suffix for the service address.	X	X		0, 1
CSR-AAI	CSR-AAI	Up to 60	A/N	Additional Address Information Identifies additional location information about the address.	X	X		0, 1
CSR-NAME	CSR-NAME	Up to 151	A/N	End User Name - Identifies the name of the end user. Can be identified from the left-handed data following the FID LN, NL, or NP in the LIST section of the CSR. Definition Note: The data in this field is created by concatenating the data in the LNLN field and the data in the LNFN fields. The data in the LNLN field will also appear in the LNLN field and the data in the LNFN field will also appear in the LNFN field.	X	X	N/A	0, 1

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
LD1	LD1	Up to 4	A	LOCATION DESIGNATOR 1 - Identifies additional specific information related to the address (e.g., building).				0, 1
LV1	LV1	Up to 10	A/N	LOCATION DESIGNATOR 1 - Identifies the value associated with the first location designator (LD1) of the address.				0, 1
LD2	LD2	Up to 4	A	LOCATION DESIGNATOR 2 - Identifies additional specific information related to the address (e.g., floor).	X	X		0, 1
LV2	LV2	Up to 10	A/N	LOCATION VALUE 2 - Identifies the value associated with the second location designator (LD2) of the address.				0, 1
LD3	LD3	Up to 4	A	LOCATION DESIGNATOR 3 - Identifies additional specific information related to the address (e.g., room).	X	X		0, 1
LV3	LV3	Up to 10	A/N	LOCATION VALUE 3 - Identifies the value associated with the third location designator (LD3) of the address.				0, 1


Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
CITY	CITY	Up to 32	A/N	City - Identifies the city, village or township, etc.	X	X		0, 1
STATE	STATE	2	A	State - Identifies the abbreviation for the state of province.	X	X		0, 1
ZIP	ZIP	5	N	Zip/Postal Code - Identifies the zip code, zip code or postal code.	X	X		0, 1
Listing Section: Listed Name								
RTY	RTY	3	A	Record Type - Identifies the type of listing that exists with respect to pricing and tariffs.	X	X		0, N
ALI	ALI	Up to 3	A	Alpha/Numeric Listing - Identifier Code Identifier assigned to each listing to uniquely identify a listing for a MTN from a customer.	X	X		0, N
DML	DML	1	A	Direct Mail List - Identifies whether this listing is to be omitted from any direct mail lists.	X	X		0, N
LTY	LTY	1	N	Listing Type - Identifies the type of listing that exists with respect to publication and Directory Assistance (DA) appearance rules.	X	X		0, N

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
LNPL	LNPL	1	A	Listed Name Placement - Identifies by placement of semi-colon (;) and the finding word is a single letter.	X	X	L	0, N
LNLN	LNLN	Up to 50	A/N	Listed Name Last - Identifies the first word for business listings or the complete last name for residence listings.	X	X		0, N
STYC	STYC	2	A	Style Code - Identifies whether the listing is a straight line, caption, etc.	X	X		0, N
TOA	TOA	Up to 2	A	Type of Account - Identifies the type of account for this listing.	X	X	B, R, BP, RP	0, N
BRO	BRO	1	A	Business/Residence Placement Override - Identifies an override of the normal placement of business listings.	X	X	B, R	0, N
LNFN	LNFN	Up to 100	A/N	Listed Name First - Identifies all except the first word for business listings or all of the first name or names and middle name/initials for residence listings.	X	X		0, N

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
DLNM	DLNUM	1	A	Dual Name Listing - Indicates that this listing contains multiple first names, e.g., Smith, Betty & John and that both should appear in directory assistance.	X	X		0, N
NICK	NICK	Up to 12	A/N	Listing Nickname - Indicates the listed person's nickname.	X	X		0, N
TL	TL	Up to 12	A/N	Title of Lineage - Indicates a phrase used to designate lineage of a listed person, (e.g., Jr., Sr., III, etc.).	X	X		0, N
TITLE1	TITLE 1	Up to 12	A/N	Title of Address 1 - Identifies the title of address 1 of a directory listing user, (e.g., Mr., Fr., DDS, etc.).	X	X		0, N
TITLE2	TITLE2	Up to 12	A/N	Title of Address 2 - Identifies the additional title of address of a directory listing user, (e.g., Mr., Fr., DDS, etc.).	X	X		0, N
CSR-PLA	CSR-PLA	Up to 150	A/N	Place Listing As - Identifies the special filing words that should be used instead of the listed name if the customer wishes to override the normal sequencing.	X	X		0, N


Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
DES	DES	Up to 25	A/N	Designation - Identifies the professional designation phrase of the business listing	X	X		0, N
WPP	WPP	Up to 3	A	White Page Products - Identifies information about the White Page Products, Signature Listings, Personality Logo and Lines of Distinction.	X	X		0, N
DIRNAME	DIRNAME	Up to 35	A/N	Directory Name - Identifies the name of a directory in which the listing exists.	X	X		0, N
DIRSUB	DIRSUB	Up to 35	A/N	Directory Subsection - Identifies the subsection of a directory in which to place the listing.	X	X		0, N
Listing Section Listed Name: Listed Text								
LXTY	LXTY	Up to 3	A	Listed Text Type - Identifies the type of the associated text that will appear in the directory to assist the end user.	X	X		0, N
LTEXT	LTEXT	UP to 250	A/N	Listing Text - Identifies the descriptive or informative text that will appear in the directory to assist the end user.	X	X		0, N

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
LPHRASE	LPHRASE	UP to 3	A/N	Listing PHRASE Identifies the pre-defined phrase associated with a listing. Valid Entry Note: Stated Character type does not match character type of valid values. However, valid values are correct for BST	X	X		0, N
Listing Section: Listed Address								
LAPR	LAPR	Up to 6	A/N	Listed Address House Prefix - Identifies the prefix for the house number of the listed address.	X	X		0, N
LANO	LANO	Up to 10	A/N	Listed Address House Number - Identifies the house number of the listed address.	X	X		0, N
LASF	LASF	Up to 4	A/N	Listed Address House Number Suffix - Identifies the suffix for the house number of the listed address.	X	X		0, N
LASD	LASD	Up to 2	A	Listed Address Street Directional - Identifies the street directional of the listed address.	X	X		0, N



Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S9	TAG	Valid Values	Occurrences
LASN	LASN	Up to 60	A/N	Listed Address Street Name - Identifies the street name of the listed address.	X	X		0, N
LATH	LATH	Up to 10	A/N	Listed Address Thoroughfare - Identifies the thoroughfare portion of the street name of the listed address.	X	X		0, N
LASS	LASS	Up to 2	A	Listed Address Street Suffix - Identifies the street suffix to the street name of the listed address.	X	X		0, N
LALOC	LALOC	Up to 35	A/N	Listed Address Locality - Identifies the locality or community to be listed.	X	X		0, N
LAST	LAST	2	A	Listed Address State	X	X		0, N NOTE: This data will only be returned if it is found in the Listed Address field on the CSR, in the 2 Alpha format. (Example = GA) Otherwise the field will be blank

Listing Section:
Additional Listing Data




Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
YPH	YPH	6	N	Yellow Page Heading Code - Identifies the heading under which a business listing will appear in the yellow pages.	X	X		0, N
SIC	SIC	4 or 5	N	Standard Industrial Classification - Identifies the primary function of a customer's business.	X	X		0, N
LTN	LTN	10	N	Listing Telephone Number - Indicates the telephone number to be placed in the directory and quoted in Directory Assistance (DA).	X	X	10 numeric characters	0, N
NSTN	NSTN	3 N or 10 A/N		Non Standard Telephone Number - Identifies a telephone number which is not in the standard North American Numbering Plan format, (e.g., vanity numbers, Enterprise, 911).	X	X		0, N
ADI	ADI	1	A	Address Indicator - Identifies that listing address elements should be omitted from directory assistance and published directories.	X	X		0, N

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
LISTING-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Listing Section Data Block (unparsed data)
Directory Section Information								
Directory Section: Delivery Address								
NAME-DEL	NAME-DEL	Up to 30	A/N	End User Name - Identifies the name of the end user to whom the directory is delivered.	X	X		0, 1
DDAPR	DDAPR	Up to 6	A/N	Delivery Address House Prefix - Identifies the prefix for the house number of the delivery address.	X	X		0, 1
DDANO	DDANO	Up to 10	A/N	Delivery Address House Number - Identifies the house number of the delivery address.	X	X		0, 1
DDASF	DDASF	Up to 5	A/N	Delivery Address House Number Suffix - Identifies the suffix for the house number of the delivery address.	X	X		0, 1
DDASD	DDASD	Up to 2	A	Delivery Address Street Directional - Identifies the street directional of the delivery address.	X	X		0, 1
DDASN	DDASN	Up to 60	A/N	Delivery Address Street Name - Identifies the street name of the delivery address.	X	X		0, 1

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
DDATH	DDATH	Up to 7	A/N	Delivery Address Thoroughfare - Identifies the thoroughfare portion of the street name of the delivery address.	X	X		0, 1
DDASS	DDASS	Up to 2	A/N	Delivery Address Street Suffix - Identifies the street suffix to the street name of the delivery address. Valid Entry Note: Stated Character type does not match character type of valid values. However, valid values are correct for BST	X	X		0, 1
LD1	LD1	Up to 4	A	LOCATION DESIGNATOR 1 - Identifies additional specific information related to the address (e.g., bldg).	X	X		0, 1
LV1	LV1	Up to 10	A/N	LOCATION VALUE 1 - Identifies the value associated with the first location designator (LD1) of the address.	X	X		0, 1
LD2	LD2	Up to 4	A	LOCATON DESIGNATOR 2 - Identifies additional specific information related to the address (e.g., floor).	X	X		0, 1

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
LV2	LV2	Up to 10	A/N	LOCATION VALUE 2 - Identifies the value associated with the second location designator (LD2) of the address.	X	X		0, 1
LD3	LD3	Up to 4	A	LOCATION DESIGNATOR 3 - Identifies additional specific information related to the address (e.g., room)	X	X		0, 1
LV3	LV3	Up to 10	A/N	LOCATION VALUE 3 - Identifies the value associated with the third location designator (LD3) of the address.	X	X		0, 1
CITY	CITY	Up to 32	A/N	CITY - Identifies the city, village or township etc.	X	X		0, 1
STATE	STATE	2	A	STATE or State or Province - Identifies the abbreviation for the state or province.	X	X		0, 1
ZIP	ZIP	5	N	ZIP CODE - Identifies the zip code or postal code.	X	X		0, 1
Directory Section: Directory Type								
DIRTYP	DIRTYP	1	A	Directory ID Type - Identifies the type of the directory (e.g., W, Y, B, O) to be delivered.	X	X		0, N

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
DIRQTYA	DIRQTYA	Up to 4	N	Number of Directories for Annual Delivery - Identifies the number of directories to be delivered on an annual basis.	X	X		0, N
Directory Section: Directory Data Block								
DIRECTORY-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Directory Section Data Block (unparsed data)
Traffic Section								
TRAFFIC-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Traffic Section Data Block (unparsed data)
Billing Section								
BILLING-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Billing Section Data Block (unparsed data)




Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
LSCP	N/A	1	A	<p>Local Service Provider Change Prohibited Identifies that the end user has requested the option of prohibiting the change of their current service provider</p> <p>This field will be returned when the Transaction Type = E.</p> <p>When the FID LSF is not found in the Bill Section of the CSR, no data will be returned in this field.</p> <p>Data will only be returned in those states where LSF is valid</p>			A = Prohibit a change of current local service provider	0, 1
Service & Equipment Section Information								
HID	HID	Up to 3 A or Up to 4 N	A/N	<p>Hunt Group Identification -</p> <p>Identifies the existing hunt group.</p>	X	X		0, N
TKQ	TKQ	Up to 4	N	<p>Trunk Quantity -</p> <p>Indicates the quantity of DID trunks.</p>	X	X		0, N
DO	DO	Up to 2	N	<p>DID Digits Out -</p> <p>Identifies the number of digits outpulsed from the central office to the customer's premise.</p>	X	X		0, N
S&E Section: Working TN								

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
WTN	WTN	10	N	<p>Working Telephone Number(s) -</p> <p>Identifies the working telephone number at the end user's location.</p> <p>Note: WTN field will be populated with Zeros (0) when a USOC on the Customer Service Record (CSR) does not have an associated TN.</p>	X	X		0, N
FPI	FPI	1	A	<p>Freeze PIC Indicator -</p> <p>Indicates that the end user requested a freeze option for the PIC, LPIC or IPIC.</p>	X	X		0, N
PIC	PIC	4	N	<p>InterLATA Presubscription Indicator Code -</p> <p>Identifies the presubscription indicator code (PIC) for the carrier the customer has selected for interLATA traffic.</p> <p>Valid Entry Note: Stated Character type does not match character type of valid values. However, valid values are correct for BST</p>	X	X		0, N

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
LPIC	LPIC	4	N	<p>IntraLATA Presubscription Indicator Code -</p> <p>Identifies the presubscription indicator code (PIC) for the carrier the customer has selected for intraLATA traffic.</p> <p>Valid Entry Note: Stated Character type does not match character type of valid values. However, valid values are correct for BST</p>	X	X		0, N
ECCKT	ECCKT	Up to 41	A/N	<p>Exchange Company Circuit ID -</p> <p>Identifies a provider's circuit identification.</p>	X	X		0, N
HNTYP	HNTYP	1	N	<p>HUNT TYPE -</p> <p>Identifies the type of Hunting involved.</p> <p>Condition: Provided when HID is populated. Value will be blank if hunting on CSR does not match hunt types 1-6.</p> <p>Note: HNTYP may not be parsed consistently. The format of the Hunt Type on the CSR varies based on the central office and age of the account.</p>	X	X		0, N

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
HTSEQ	HTSEQ	4	N	HUNT SEQUENCE - Identifies the desired hunting sequence. Condition: Provided when HID is populated.	X	X		0, N
NOTYP	NOTYP	1	A	NUMBER TYPE - Identifies the type of number (TER or TN) entered in the HT field. Condition: Provided when HID is populated.	X	X		0, N
HTN	HTN	Up to 15	A/N	HUNT TELEPHONE NUMBER - Identifies the hunting telephone number for the hunt group sequence. Condition: Provided when HID is populated.	X	X		0, N
TERS	TERS	Up to 10	A/N	Terminal Numbers - Identifies the number for a non-lead line in a multi-line hunt group or consecutive range of terminal numbers associated with the TNS for this request. Condition: Provided when NOTYP is populated with an L.	X	X		0, N

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
TLI	TLI	10	N	Telephone Line Identifier - The pilot number for a multi-line hunt group. Condition: Provided when TER is populated.	X	X		0, N
PULSE	PULSE	2 or 4	A	Pulsing Type - Identifies the pulsing of the end user or DID working telephone number.	X	X		0, N
S&E Section: Working TN Blocking								
BLOCK	N/A	Up to 2	A	Blocking Exceptions - Identifies the blocking exceptions for the telephone number.	X	X		0, N
S&E Section: End Blocking								
SSIG	SSIG	2	A	Start Signaling - Identifies the type of start signaling requested.	X	X		0, N
TGN	TGN	3 - 4	N	Trunk Group Number - Identifies the DID trunk group number.	X	X		0, N
RIN	RIN	3 - 4	N	Route Index Number - Identifies the route index number assigned to the DID trunk group.	X	X		0, N



Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Character Type	Business Rules	Is S9	TAG	Valid Values	Occurrences
LTLI	LTLI	10	N	Lead Telephone Line Identifier - Identifies the lead telephone line identifier of the DID trunk group.	X	X		0, N
TKID	TKID	Up to 10	A/N	Trunk Identifier - Identifies the trunk ID of the existing DID service.	X	X		0, N
S&E Section: Working TN: Feature								
FEATURE	FEATURE	3, 5 or 6	A/N	Feature Codes - Identifies the type of feature associated with the line.	X	X		0, N
S&E Section: Working TN: Feature Feature Detail								
CSR-FEATURE-DETAIL	CSR-FEATURE-DETAIL	Up to 200	A/N	Feature Detail - Identifies additional information for the type of feature associated with the line.	X	X		0, N
S&E Section: Svc Equip Data								
SRVCEQUIPDAT A	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 S&E Section Data Block (unparsed data)
Ported Lines Information								
PORTED-OUT-LINE-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Ported Lines Data Block (unparsed data)
Related Account Information								
RELATED-ACCOUNT-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Related Account Data Block (unparsed data)
Billing Transfer Section								

Parsed Customer Record Response (PCSRR)								
Field Names		Usage						
BST	LSOG6	Field Length	Char Type	Business Rules	Is S 9	TAG	Valid Values	Occurrences
BILLING-TRANSFER-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Billing Transfer Data Block (unparsed data)
Remarks Section								
REMARKS-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Remarks Section Data Block (unparsed data)
Completed Activity Section								
COMPACT-DATA	N/A	Variable	A/N	Unparsed data that is returned in a block of information for CLEC use.	X	X		0, 1 Comp Act Data Block (unparsed data)

TAG/LENS**ELMS6*****Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts***

The following Parsed CSR data will be returned if available for the Wireless Type 1 Block account request only. If no Parsed CSR data is available a message will be returned in the Message ID and Message Text fields. This query will be returning limited data.

Note: Wireless Type 1 accounts will not receive the LSF information.

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Character Type	Business Rules	Valid Values
TXNUM	TXNUM	Up to 16	A/N	Transaction Number Identifies the customer provided tracking number to link the inquiry with the response	
CCNA	CCNA	3	A	Customer Carrier Name Abbreviation Identifies the Common Language IAC code for the customer submitting the LSR and receiving the confirmation.	
CC	CC	4	A/N	Company Code Identifies the exchange carrier generating the inquiry.	
BILLING-DATA	BILLING-DATA	Var. String Unparsed	A/N	Billing Data All Billing Data will be returned in an Unparsed format.	
IDENT-DATA	IDENT-DATA	Var. String Unparsed	A/N	Identification Section Data	

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Char Type	Business Rules	Valid Values
ATN	ATN	10	N	Account Telephone Number Identifies the account telephone number of the end user.	
AN	AN	10 or 13	A/N	Account Number Identifies the customer account number.	
CS	CS	3 or 5	A/N	Class of Service Identifies the basic class of service for the line ordered.	
TOS	TOS	4	A/N	Type of Service Identifies the type of service for the line offered. Note: The second and third characters will not be derived and returned. The TAG return format will be number, space, space, space	

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Char Type	Business Rules	Valid Values
PSO	PSO	Up to 10	A/N	<p>Pending Service Order</p> <p>Identifies pending service orders for this account.</p> <p>Note 1: This field is returned on a response when a pending service order condition exists on the CSR account being requested.</p> <p>The PSO Indicator will indicate if there is either a pending service order, multiple service orders or no service order as follows: A pending service order = The PSO Indicator will provide the SHAK number.</p> <p>Multiple service Orders= "MULTI" will be returned</p> <p>No pending service orders="NONE" will be returned</p>	
DT-SENT	DT-SENT	8	N	Date Sent transaction is sent.	Format CCYYMMDD
TM-SENT	TM-SENT	6	N	Time transaction is sent	Format: HHMMSS
LISTING SECTION-END USER LOCATION DATA					
SANO	SANO	Up to 8	A/N	<p>Service Address House Number</p> <p>Identifies the number of the service address.</p>	

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Character Type	Business Rules	Valid Values
SASF	SASF	Up to 4	A/N	Service Address House Number Suffix Identifies the suffix for the address number of the service address.	
SASD	SASD	Up to 2 A	A	Service Address Street Directional Prefix Identifies the street directional prefix for the service address.	
SATH	SATH	Up to 6	A/N	Service Address Street Type Identifies the thoroughfare portion of the street name of the service address.	
SASS	SASS	Up to 2	A	Service Address Street Directional Suffix Identifies the street directional suffix for the service address.	
CSR-AAI	CSR-AAI	Up to 60	A/N	Additional Address Information Identifies additional location information about the address.	

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Character Type	Business Rules	Valid Values
CSR-NAME	CSR-NAME	Up to 151	A/N	<p>End User Name</p> <p>Identifies the name of the end user. Can be identified from the left-handed data following the FID LN, NL, or NP in the LIST section of the CSR.</p> <p>Definition Note: The data in this field is created by concatenating the data in the LNLN field and the data in the LNFN fields. The data in the LNLN field will also appear in the LNLN field and the data in the LNFN field will also appear in the LNFN field.</p>	
LDI	LDI	Up to 4	A	<p>Location Designator 1</p> <p>Identifies additional specific information related to the address (e.g., building)</p>	
LV1	LV1	Up to 10	A/N	<p>Location Value 1</p> <p>Identifies the value associated with the first location designator (LD1) of the address.</p>	
LD2	LD2	Up to 4	A	<p>Location Designator 2</p> <p>Identifies additional specific information related to the address (e.g., floor).</p>	
LV2	LV2	Up to 10	A	<p>Location Value 2</p> <p>Identifies the value associated with the second location designator (LD2) of the address.</p>	

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Char Type	Business Rules	Valid Values
LD3	LD3	Up to 4	A	Location Designator 3 Identifies additional specific information related to the address (e.g., room)	
LV3	LV3	Up to 10	A/N	Location Value 3 Identifies the value associated with the third location designator (LD3) of the address.	
CITY	CITY	Up to 32	A/N	City Identifies the city, village or township, etc.	
STATE	STATE	2	A	State Identifies the abbreviation for the state or province	
ZIP	ZIP	5	N	Zip Identifies the abbreviation for the state or province.	
LISTED NAME DATA					
LNLN	LNLN	Up to 50	A/N	Listed Name Last Identifies the first word for business listings or the complete last name for residence listings.	
LNFN	LNFN	Up to 100	A/N	Listed Name First Identifies all except the first word for business listings or all of the first name or names and middle name/initials for residence listings.	

Parsed Customer Record Response (PCSR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Char Type	Business Rules	Valid Values
DLNM	DLNM	1	A	Dual Name Listing Indicates that this listing contains multiple first names, e.g., Smith, Betty & John and that both should appear in directory assistance.	
NICK	NICK	Up to 12	A/N	Nickname Indi Indicates the listed person's nickname. .	
TL	TL	Up to 12	A/N	Title of Lineage Indicates a phrase used to designate lineage of a listed person, (e.g., Jr., Sr., III, etc.).	
TITLE1	TITLE1	Up to 12	A/N	Title of Address 1 Identifies the title of address 1 of a directory listing user, (e.g., Mr., Fr., DDS, etc.).	
WORKING TELEPHONE INFORMATION					
WTN	WTN	10	N	Working Telephone Number Identifies the working telephone number at the end user's location. Note: WTN field will be populated with Zeros (0) when a USOC on the Customer Service Record (CSR) does not have an associated TN.	
CSR ERROR MESSAGE LIST					
ERROR-CODE	ERROR-CODE	5	A/N	Error Code	
ERROR-TEXT	ERROR-TEXT	Up to 264	A/N	Error Text	

EDI**ELMS6*****Parse Customer Record Response (PCSRR)***

This message is used to return customer record information in a parsed format. Since customer records can be very large, this message size will be limited to one (1) MG of data. The parsed CSR response contains the parsed sections and will also contain unparsed sections in a block of data. The following sections will return parsed and unparsed and the unparsed sections will be returned in a block of data (see table)

The Bellsouth Parsed CSR transaction is intended for noncomplex accounts, PBX and DID.

1. IDENT section
2. LISTING section
3. DIRECTORY section
4. TRAFFIC section
5. BILLING section
6. Note: Local Service Freeze (LSF) will be returned when indicated on the CSR in states where LSF is a valid offering.
7. S&E section
8. Ported out lines
9. Related account information
10. Billing transfer section
11. Completed activity section
12. Remarks section
13. Error message information

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
TXNUM (Replaces INQ-NUM)	Up to 16 A/N	Transaction Number - Identifies the customer provided tracking number to link the inquiry with the response. Occurs 0, 1
TXACT	1 A	Transaction Activity - Identifies the inquiry activity involved. Occurs 0, 1
TXTYP	1 A	Transaction Type - Identifies the type of transaction. Occurs 0, 1

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
ATN	10 N	Account Telephone Number - Identifies the account telephone number of the end user. Occurs 0, 1
AN	10 or 13 A/N	Account Number - Identifies the customer account number. Occurs 0, 1
DT-SENT	8 N	Date Sent - Date transaction is sent. Occurs 0, 1
TM-SENT	6 N	Time Sent - Time transaction is sent. Occurs 0, 1
CCNA	3 A	Carrier Name Abbreviation - Identifies the Common Language IAC Code for the customer submitting the inquiry and receiving the response. Occurs 0, 1
CC	4 A/N	Company Code Identifies the exchange carrier generating the inquiry. Occurs 0, 1
PSO	Up to 6 A/N	Pending Service Order - Identifies pending service orders for this account. Occurs 0, 1
Identification Section:		
ATN	10 N	Account Telephone Number - Identifies the account telephone number of the end user. Occurs 0, 1
AN	10 or 13 A/N	Account Number - Identifies the customer account number. Occurs 0, 1
TOS	4 A/N	Type of Service - Identifies the type of service for the line offered. Can be identified as residence, business, government or coin from the data following TYPE in the IDENT section of the CSR. The second and third characters will not be derived and returned. They will be blank. Occurs 0, 1

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
CS	3 or 5 A/N	Class of Service - Identifies the basic class of service for the line ordered. Can be identified from the un-fielded IDENT section in the first line of the CSR after EXCH. When found, return the data in the CS field of the BCS field. Occurs 0, 1
IDENT-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use Occurs 0, 1
Listing Section: End User Location		
SANO	Up to 8 A/N	Service Address House Number - Identifies the number of the service address. Occurs 0, 1
SASF	Up to 4 A/N	Service Address House Number Suffix - Identifies the suffix for the address number of the service address. Occurs 0, 1
SASD	Up to 2 A	Service Address Street Directional - Identifies the street directional prefix of the service address. Occurs 0, 1
SASN	Up to 44 A/N	Service Address Street Name - Identifies the street name of the service address. Occurs 0, 1
SATH	Up to 6 A/N	Service Address Street Thoroughfare - Identifies the thoroughfare portion of the street name of the service address. Occurs 0, 1
SASS	Up to 2 A	Service Address Street Suffix - Identifies the street directional suffix for the service address. Occurs 0, 1
CSR-AAI	Up to 60 A/N	Service Address Descriptive Location - Identifies additional location information about the address. Occurs 0, 1

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
CSR-NAME	Up to 151 A/N	<p>End User Name - Identifies the name of the end user. Can be identified from the left-handed data following the FID LN, NL, or NP in the LIST section of the CSR</p> <p>Definition Note: The data in this field is created by concatenating the data in the LNLN field and the data in the LNFN fields. The data in the LNLN field will also appear in the LNLN field and the data in the LNFN field will also appear in the LNFN field.</p> <p>Occurs 0, 1</p>
LD2 (FLOOR)	Up to 4 A	<p>LOCATION DESIGNATOR 2 - Identifies additional specific information related to the address. (e.g., floor).</p> <p>Occurs 0, 1</p>
LV2	Up to 10 A/N	<p>LOCATION VALUE 2 - Identifies the value associated with the second location designator (LD2) of the address.</p> <p>Occurs 0, 1</p>
LD3 (ROOM)	Up to 4 A	<p>LOCATION DESIGNATOR 3 -Identifies additional specific information related to the address (e.g., room).</p> <p>Occurs 0, 1</p>
LV3	Up to 10 A/N	<p>LOCATION VALUE 3 - Identifies the value associated with the third location designator (LD3) of the address.</p> <p>Occurs 0, 1</p>
LD1 (BLDG)	Up to 4 A	<p>LOCATION DESIGNATOR 1 - Identifies additional specific information related to the address (e.g., building).</p> <p>Occurs 0, 1</p>
LV1	Up to 10 A/N	<p>LOCATION VALUE 1 - Identifies the value associated with the first location designator (LD1) of the address.</p> <p>Occurs 0, 1</p>
CITY	Up to 32 A/N	<p>City - Identifies the city, village or township, etc.</p> <p>Occurs 0, 1</p>
STATE	2 A	<p>State - Identifies the abbreviation for the state or province.</p> <p>Occurs 0, 1</p>
ZIP	5 N	<p>Zip code - Identifies the zip code or postal code.</p> <p>Occurs 0, 1</p>

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
Listing Section: Listed Name		
RTY	3 A	Record Type - Identifies the type of listing that exists with respect to pricing and tariffs. Occurs 0, N
ALI	Up to 3 A	Alpha/Numeric Listing Identifier Code - Identifier assigned to each listing to uniquely identify a listing for a MTN from a customer. Occurs 0, N
DML	1 A	Direct Mail List - Identifies whether this listing is to be omitted from any direct mail lists. Occurs 0, N
LTY	1 N	Listing Type - Identifies the type of listing that exists with respect to publication and Directory Assistance (DA) appearance rules. Occurs 0, N
LNPL	1 A	Listed Name Placement - Identifies by placement of semi-colon (;) and the finding word is a single letter. Occurs 0, N
LNLN	Up to 50 A/N	Listed Name Last - Identifies the first word for business listings or the complete last name for residence listings. Occurs 0, N
STYC	2 A	Style Code - Identifies whether the listing is a straight line, caption, etc.. Occurs 0, N
TOA	Up to 2 A	Type of Account - Identifies the type of account for this listing. Occurs 0, N
BRO	1 A	Business/Residence Placement Override - Identifies an override of the normal placement of business listings. Occurs 0, N
LNFN	Up to 100 A/N	Listed Name First - Identifies all except the first word for business listings or all of the first name or names and middle name/initials for residence listings. Occurs 0, N

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
DLNM	1 A	Dual Name Listing - Indicates that this listing contains multiple first names, (e.g., Smith, Betty & John) and that both should appear in directory assistance. Occurs 0, N
NICK	Up to 12 A/N	Listing Nickname - Indicates the listed person's nickname Occurs 0, N
TL	Up to 12 A/N	Title of Lineage - Indicates a phrase used to designate lineage of a listed person, (e.g., Jr., Sr., III, etc.). Occurs 0, N
TITLE1	Up to 12 A/N	Title of Address 1 - Identifies the title of address 1 of a directory listing user, (e.g., Mr., Fr., DDS, etc.). Occurs 0, N
TITLE2	Up to 12 A/N	Title of Address 2 - Identifies the additional title of address of a directory listing user, (e.g., Mr., Fr., DDS, etc.). Occurs 0, N
CSR-PLA	Up to 150 A/N	Place Listing As - Identifies the special filing words that should be used instead of the listed name if the customer wishes to override the normal sequencing. Occurs 0, N
DES	Up to 25 A/N	Designation - Identifies the professional designation phrase of the business listing. Occurs 0, N
WPP	Up to 3 A	White Page Products - Identifies information about the White Page Products, Signature Listings, Personality Logo and Lines of Distinction. Occurs 0, N
DIRNAME	Up to 35 A/N	Directory Name - Identifies the name of a directory in which the listing exists. Occurs 0, N
DIRSUB	Up to 35 A/N	Directory Subsection - Identifies the subsection of a directory in which to place the listing. Occurs 0, N
Listing Section Listed Name: Listed Text		

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
LXTY	Up to 3 A	Listed Text Type - Identifies the type of the associated text that will appear in the directory to assist the end user. Occurs 0, N
LTEXT	Up to 250 A/N	Listing Text - Identifies the descriptive or informative text that will appear in the directory to assist the end user. Occurs 0, N
LPHRASE	Up to 3 A/N	Identifies a pre-defined phrase associated with a listing. Occurs 0, N
Listing Section: Listed Address		
LAPR	Up to 6 A/N	Listed Address House Prefix - Identifies the prefix for the house number of the listed address. Occurs 0, N
LANO	Up to 10 A/N	Listed Address House Number - Identifies the house number of the listed address. Occurs 0, N
LASF	Up to 4 A/N	Listed Address House Number Suffix - Identifies the suffix for the house number of the listed address. Occurs 0, N
LASD	Up to 2 A	Listed Address Street Directional - Identifies the street directional of the listed address. Occurs 0, N
LASN	Up to 60 A/N	Listed Address Street Name - Identifies the street name of the listed address. Occurs 0, N
LATH	Up to 10 A/N	Listed Address Thoroughfare - Identifies the thoroughfare portion of the street name of the listed address. Occurs 0, N
LASS	Up to 2 A	Listed Address Street Suffix - Identifies the street suffix to the street name of the listed address. Occurs 0, N
LALOC	Up to 35 A/N	Listed Address Locality - Identifies the locality or community to be listed. Occurs 0, N

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
LAST	2 A	Listed Address State - Identifies the state of the listed address. Occurs 0, N
Listing Section: Additional Listing Data		
YPH	6 N	Yellow Page Heading Code - Identifies the heading under which a business listing will appear in the yellow pages. Occurs 0, N
SIC	4 or 5 N	Standard Industrial Classification - Identifies the primary function of a customer's business. Occurs 0, N
LTN	10 N	Listing Telephone Number - indicates the telephone number to be placed in the directory and quoted in Directory Assistance (DA). Occurs 0, N
NSTN	3 N or 10 A/N	Non Standard Telephone Number - Identifies a telephone number which is not in the standard North American Numbering Plan format, (e.g., vanity numbers, Enterprise, 911). Occurs 0, N
ADI	1 A	Address Indicator - Identifies that listing address elements should be omitted from directory assistance and published directories. Occurs 0, N
Listing Data Block		
LISTING-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
Directory Section Information		
Directory Section: Delivery Address		
NAME-DEL	Up to 30 A/N	End User Name - Identifies the name of the end user to whom the directory is delivered. Occurs 0, 1

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
DDAPR	Up to 6 A/N	Delivery Address House Prefix - Identifies the prefix for the house number of the delivery address. Occurs 0, 1
DDANO	Up to 10 A/N	Delivery Address House Number - Identifies the house number of the delivery address. Occurs 0, 1
DDASF	Up to 5 A/N	Delivery Address House Number Suffix - Identifies the suffix for the house number of the delivery address. Occurs 0, 1
DDASD	Up to 2 A	Delivery Address Street Directional - Identifies the street directional of the delivery address. Occurs 0, 1
DDASN	Up to 60 A/N	Delivery Address Street Name - Identifies the street name of the delivery address. Occurs 0, 1
DDATH	Up to 7 A/N	Delivery Address Thoroughfare - Identifies the thoroughfare portion of the street name of the delivery address. Occurs 0, 1
DDASS	Up to 2 A/N	Delivery Address Street Suffix - Identifies the street suffix to the street name of the delivery address. Occurs 0, 1
LD1	Up to 4 A	LOCATION DESIGNATOR 1 - Identifies additional specific information related to the address (e.g., building). Occurs 0, 1
LV1	Up to 10 A/N	LOCATION VALUE 1 - Identifies the value associated with the first location designator (LD1) of the address. Occurs 0, 1
LD2	Up to 4 A	LOCATION DESIGNATOR 2 - Identifies additional specific information related to the address. (e.g., floor). Occurs 0, 1
LV2	Up to 10 A/N	LOCATION VALUE 2 - Identifies the value associated with the second location designator (LD2) of the address. Occurs 0, 1

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
LD3	Up to 4 A	LOCATION DESIGNATOR 3 -Identifies additional specific information related to the address (e.g., room). Occurs 0, 1
LV3	Up to 10 A/N	LOCATION VALUE 3 - Identifies the value associated with the third location designator (LD3) of the address. Occurs 0, 1
CITY	Up to 32 A/N	CITY- Identifies the city, village or township where the directory is to be delivered. Occurs 0, 1
STATE	2 A	State - Identifies the State/Province of the delivery address. Occurs 0, 1
ZIP	5 N	Zip Code - Identifies the postal code of the delivery address. Occurs 0, 1
Directory Section: Directory Type		
DIRTYP	1 A	Directory ID Type - Identifies the type of the directory (e.g., W, Y, B, O) to be delivered. Occurs 0, N
DIRQTYA	Up to 4 N	Number of Directories for Annual Delivery - Identifies the number of directories to be delivered on an annual basis. Occurs 0, N
Directory Section: Directory Data Block		
DIRECTORY-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
Traffic Section:		
TRAFFIC-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
Billing Section :		

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
BILLING-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
LSCP	1 A	Local Service Provider Change Prohibited Identifies that the end user has requested the option of prohibiting the change of their current service provider This field will be returned when the Transaction Type = E. When the FID LSF is not found in the Bill Section of the CSR, no data will be returned in this field. Data will only be returned in those states where LSF is valid Occurs 0, 1
Service & Equipment Section Information		
HID	Up to 3 A or Up to 4 N	Hunt Group Identification - Identifies the existing hunt group. Occurs 0, N
TKQ	Up to 4 N	Trunk Quantity - Indicates the quantity of DID trunks. Occurs 0, N
DO	Up to 2 N	Digits Out -Identifies the number of digits outpulsed from the central office to the customer's premise. Occurs 0, N
S&E Section: Working TN		
WTN	10 N	Working Telephone Number(s) - Identifies the working telephone number at the end user's location. Note: WTN field will be populated with Zeros (0) when USOC on Customer service Record (CSR) does not have an associated TN Occurs 0, N
FPI	1 A	Freeze PIC Indicator - Indicates that the end user requested a freeze option for the PIC, LPIC or IPIC. Occurs 0, N

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
PIC	4N	InterLATA Presubscription Indicator Code - Identifies the presubscription indicator code (PIC) for the carrier the customer has selected for interLATA traffic. Occurs 0, N
LPIC	4N	IntraLATA Presubscription Indicator Code - Identifies the presubscription indicator code (PIC) for the carrier the customer has selected for intraLATA traffic. Occurs 0, N
ECCKT	Up to 41 A/N	Exchange Company Circuit ID - Identifies a provider's circuit identification. Occurs 0, N
HNTYP	1 N	HUNT TYPE - Identifies the type of Hunting involved. Condition: Provided when HID is populated. Value will be blank if hunting on CSR does not match hunt types 1-6. Note: HNTYP may not be parsed consistently. The format of the Hunt Type on the CSR varies based on the central office and age of the account. Occurs 0, N
HTSEQ	4 N	HUNT SEQUENCE - Identifies the desired hunting sequence. Condition: Provided when HID is populated. Occurs 0, N
NOTYP	1 A	NUMBER TYPE - Identifies the type of number (TER or TN) entered in the HT field. Condition: Provided when HID is populated. Occurs 0, N
HTN	Up to 15 A/N	HUNT TELEPHONE NUMBER - Identifies the hunting telephone number for the hunt group sequence. Condition: Provided when HID is populated. Occurs 0, N
TERS	Up to 10 A/N	Terminal Numbers - Identifies the number for a non-lead line in a multi-line hunt group or consecutive range of terminal numbers associated with the TNS for this request. Condition: Provided when NOTYP is populated with an L. Occurs 0, N

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
TLI	10 N	Telephone Line Identifier - The pilot number for a multi-line hunt group. Condition: Provided when TER is populated. Occurs 0, N
PULSE	2 A or 4 A	Pulsing Type - Identifies the pulsing of the end user or DID working telephone number. Occurs 0, N
S&E Section: Working TN Blocking		
BLOCK	Up to 2 A	Blocking Exceptions - Identifies the blocking exceptions for the telephone number Occurs 0, N
S&E Section: End Blocking		
SSIG	2 A	Start Signaling - Identifies the type of start signaling requested. Occurs 0, N
TGN	3 or 4 N	Trunk Group Number - Identifies the DID trunk group number. Occurs 0, N
RIN	Min 3 Max 4 N	Route Index Number - Identifies the route index number assigned to the DID trunk group. Occurs 0, N
LTLI	10 N	Lead Telephone Line Identifier - Identifies the lead telephone line identifier of the DID trunk group. Occurs 0, N
TKID	Up to 10 A/N	Trunk Identifier - Identifies the trunk ID of the existing DID service. Occurs 0, N
S&E Section: Working TN: Feature		
FEATURE	3, 5 or 6 A/N	Feature Codes - Identifies the type of feature associated with the line. Occurs 0, N

Parsed Customer Record Response (PCSRR)		
BST FIELD	Data Characteristics	Field Description
S&E Section: Working TN: Feature Feature Detail		
CSR-FEATURE- DETAIL	Up to 200 A/N	Feature Detail - Identifies additional information for the type of feature associated with the line. Occurs 0, N
S&E Section: Srv Equip Data:		
SRVCEQUIPDATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
Ported Lines Information:		
PORTED-OUT- LINE-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
Related Account Information:		
RELATED- ACCOUNT-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
Billing Transfer Section:		
BILLING- TRANSFER-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
Remarks Section:		
REMARKS-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1
Completed Activity Section:		
COMPACT-DATA	Variable A/N	Unparsed data that is returned in a block of information for CLEC use. Occurs 0, 1



Attachment
SN91084236


EDI**ELMS6*****Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts***

The following Parsed CSR data will be returned if available for the Wireless Type 1 Block account request only. If no Parsed CSR data is available a message will be returned in the Message ID and Message Text fields. This query will be returning limited data.

Note: Wireless Type 1 accounts will not receive the LSF information.

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Character Type	Business Rules	Valid Values
TXNUM	TXNUM	Up to 16	A/N	Transaction Number Identifies the customer provided tracking number to link the inquiry with the response	
CCNA	CCNA	3	A	Customer Carrier Name Abbreviation Identifies the Common Language IAC code for the customer submitting the LSR and receiving the confirmation.	
CC	CC	4	A/N	Company Code Identifies the exchange carrier generating the inquiry.	

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Char Type	Business Rules	Valid Values
BILLING-DATA	BILLING-DATA	Var. String Unparsed	A/N	Billing Data All Billing Data will be returned in an Unparsed format.	
IDENT-DATA	IDENT-DATA	Var. String Unparsed	A/N	Identification Section Data	
ATN	ATN	10	N	Account Telephone Number Identifies the account telephone number of the end user.	
AN	AN	10 or 13	A/N	Account Number Identifies the customer account number.	
CS	CS	3 or 5	A/N	Class of Service Identifies the basic class of service for the line ordered.	
TOS	TOS	4	A/N	Type of Service Identifies the type of service for the line offered. Note: The second and third characters will not be derived and returned. The TAG return format will be number, space, space, space	



Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output						
Field Names			Usage			
BST		LSOG 6	Field Length	Char Type	Business Rules	Valid Values
PSO		PSO	Up to 10	A/N	<p>Pending Service Order</p> <p>Identifies pending service orders for this account.</p> <p>Note 1: This field is returned on a response when a pending service order condition exists on the CSR account being requested.</p> <p>The PSO Indicator will indicate if there is either a pending service order, multiple service orders or no service order as follows: A pending service order = The PSO Indicator will provide the SHAK number.</p> <p>Multiple service Orders= "MULTI" will be returned</p> <p>No pending service orders="NONE" will be returned</p>	
DT-SENT		DT-SENT	8	N	Date Sent transaction is sent.	Format CCYYMMDD
TM-SENT		TM-SENT	6	N	Time transaction is sent	Format: HHMMSS

LISTING SECTION-END USER LOCATION DATA

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Char Type	Business Rules	Valid Values
SANO	SANO	Up to 8	A/N	Service Address House Number Identifies the number of the service address.	
SASF	SASF	Up to 4	A/N	Service Address House Number Suffix Identifies the suffix for the address number of the service address.	
SASD	SASD	Up to 2 A	A	Service Address Street Directional Prefix Identifies the street directional prefix for the service address.	
SATH	SATH	Up to 6	A/N	Service Address Street Type Identifies the thoroughfare portion of the street name of the service address.	
SASS	SASS	Up to 2	A	Service Address Street Directional Suffix Identifies the street directional suffix for the service address.	
CSR-AAI	CSR-AAI	Up to 60	A/N	Additional Address Information Identifies additional location information about the address.	

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Char Type	Business Rules	Valid Values
CSR-NAME	CSR-NAME	Up to 151	A/N	<p>End User Name</p> <p>Identifies the name of the end user. Can be identified from the left-handed data following the FID LN, NL, or NP in the LIST section of the CSR.</p> <p>Definition Note: The data in this field is created by concatenating the data in the LNLN field and the data in the LNFN fields. The data in the LNLN field will also appear in the LNLN field and the data in the LNFN field will also appear in the LNFN field.</p>	
LDI	LDI	Up to 4	A	<p>Location Designator 1</p> <p>Identifies additional specific information related to the address (e.g., building)</p>	
LV1	LV1	Up to 10	A/N	<p>Location Value 1</p> <p>Identifies the value associated with the first location designator (LD1) of the address.</p>	
LD2	LD2	Up to 4	A	<p>Location Designator 2</p> <p>Identifies additional specific information related to the address (e.g., floor).</p>	

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Char Type	Business Rules	Valid Values
LV2	LV2	Up to 10	A	Location Value 2 Identifies the value associated with the second location designator (LD2) of the address.	
LD3	LD3	Up to 4	A	Location Designator 3 Identifies additional specific information related to the address (e.g., room)	
LV3	LV3	Up to 10	A/N	Location Value 3 Identifies the value associated with the third location designator (LD3) of the address.	
CITY	CITY	Up to 32	A/N	City Identifies the city, village or township, etc.	
STATE	STATE	2	A	State Identifies the abbreviation for the state or province	
ZIP	ZIP	5	N	Zip Identifies the abbreviation for the state or province.	
LISTED NAME DATA					
LNLN	LNLN	Up to 50	A/N	Listed Name Last Identifies the first word for business listings or the complete last name for residence listings.	

Parsed Customer Record Response (PCSR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Character Type	Business Rules	Valid Values
LNFN	LNFN	Up to 100	A/N	Listed Name First Identifies all except the first word for business listings or all of the first name or names and middle name/initials for residence listings.	
DLNM	DLNM	1	A	Dual Name Listing Indicates that this listing contains multiple first names, e.g., Smith, Betty & John and that both should appear in directory assistance.	
NICK	NICK	Up to 12	A/N	Nickname Indicates the listed person's nickname.	
TL	TL	Up to 12	A/N	Title of Lineage Indicates a phrase used to designate lineage of a listed person, (e.g., Jr., Sr., III, etc.).	
TITLE1	TITLE1	Up to 12	A/N	Title of Address 1 Identifies the title of address 1 of a directory listing user, (e.g., Mr., Fr., DDS, etc.).	
WORKING TELEPHONE INFORMATION					
WTN	WTN	10	N	Working Telephone Number Identifies the working telephone number at the end user's location. Note: WTN field will be populated with Zeros (0) when a USOC on the Customer Service Record (CSR) does not have an associated TN.	
CSR ERROR MESSAGE LIST					

Parsed Customer Record Response (PCSRR) for Wireless Type 1 Block Accounts CLEC output					
Field Names		Usage			
BST	LSOG 6	Field Length	Character Type	Business Rules	Valid Values
ERROR-CODE	ERROR-CODE	5	A/N	Error Code	
ERROR-TEXT	ERROR-TEXT	Up to 264	A/N	Error Text	

TAG/LENS**ELMS6****CSR-NAME**

Description name:	End User Name
Definition:	Identifies the name of the end user.
Definition Note:	The data in this field is created by concatenating the data in the LNLN field and the data in the LNFN fields. The data in the LNLN field will also appear in the LNLN field and the data in the LNFN field will also appear in the LNFN field.
Characteristics:	Up to 151 A/N

TAG/LENS**ELMS6****CSR-NAME**

Description name:	End User Name
Business Rule:	Identifies the name of the end user.
Definition Note:	The data in this field is created by concatenating the data in the LNLN field and the data in the LNFN fields. The data in the LNLN field will also appear in the LNLN field and the data in the LNFN field will also appear in the LNFN field.
Characteristics:	Up to 151 A/N

17.0 and 16.0

ELMS 6 AND TCIF 9 DOCS
TNAQ-MISC QUERY
(ADD NOTE to CITY Field)
TAG/LENS BUSINESS RULES

Telephone Number Availability Query For Miscellaneous Account Number (TNAQ-MISC)

This query requests miscellaneous NPANXXs & reserves up to 25 miscellaneous account numbers for 60 days per transaction.

This transaction is used twice:

First, to obtain a list of miscellaneous NPANXXs from which to make a selection.

Second, to request up to 25 miscellaneous account numbers.

Telephone Number Availability Query-Misc (TNAQ-MISC)										
Field Names			Usage							
BST	LSOG 4	LSOG 6	Field Length	Character Type	R/C/O	Business Rules				Valid Values
TNAQ-MISC Message										
TXNUM	INQNUM	TXNUM	Up to 16	A/N	R	Transaction Number Identifies the customer provided tracking number to link the inquiry with the response.				
CITY	SALOC	CITY	Up to 32	A/N	R	City Identifies the city, village or township, etc. TAG only: Field is Case Sensitive. Enter all letters in Upper Case.				

Telephone Number Availability Query-Misc (TNAQ-MISC)									
Field Names			Usage						
BST	LSOG 4	LSOG 6	Field Length	Character Type	R/C/O	Business Rules			Valid Values
STATE	STATE	STATE	2	A	R	State Code Identifies the abbreviation for the state or province-			AL = Alabama FL = Florida GA = Georgia KY = Kentucky LA = Louisiana MS = Mississippi NC = North Carolina SC = South Carolina TN = Tennessee

17.0 and 16.0
ELMS 6 and TCIF 9
PRE-ORDER LOH
EDI DATA DICTIONARY

CITY

Description name: City

Business Rule: Identifies the city, village or township, etc.

Characteristics: Up to 32 A/N

Corresponding Firm Order Field Name: CITY - City

Conditional Usage Notes:

Transaction	Condition
Address Validation Query by Address	Required if State/Zip code is not populated.
Miscellaneous TN Availability Query – MiSC – TNAQ-MISC	City field is case sensitive. Enter all letters in Upper Case.
Miscellaneous TN Availability Query – MiSC – TNAQ-MISC	City/State combination must be populated with when LSO is blank.
Miscellaneous TN Availability Query – MiSC – TNAQ-MISC	City/State is Prohibited when LSO is populated.
Estimated Service Date Query	Required if State/Zip code is not populated

CCP 2037 Attachment Listed Below**ELMS6****SPEC – Service and Product Enhancement Code****LSR Form/Screen**

(LSOG6 / ELMS6 map)

Definition:

Identifies a specific product or service offering.

Definition Notes:

NOTE 1: SPEC may be applicable for circuit level features and options other than those already identified by the Network Channel (NC) and Network Channel Interface (NCI) codes.

Valid Entries:

None

Valid Entry Notes:

Note 1: For REQTYPs A and B, positions 1 - 7 = any alpha character except " I " or any numeric

character except '0' (zero)

Note 2: For REQTYPE A the following SPEC codes for EELs and OCU's service types is valid:

SPEC Code	Service Type
UNCVX	Voice Grade
UNCNX	ISDN
UNCDX	56/64 kbps
UNC1X	DS1
UNC3X	DS3
UNCSX	STS-1

Note 3: When UNC3X or UNCSX is populated the LSR must be submitted manually.

Note 4: When the REQTYPE is B and the product is EELs, the only valid entry in the SPEC field is UNCVX (Voice Grade).

Manual:

Note 5: When ordering a REQTYPE A Unbundled Dark Fiber (UDF) as an Ordinarily Combined UNE Combination the only valid entry in the SPEC field is UDFCX.

Data Characteristics:

5 or 7 alpha/numeric characters



Attachment
SN91084236

Examples:

BD11T

BD1T5AD

Conditional Usage Notes:

Manual:

Note 1: Required when ordering REQ TYP A Unbundled Dark Fiber (UDF) as an Ordinarily Combined UNE Combination.

Business Rules

Rule 1: For REQ TYP B, when the SPEC field is populated with UNCVX, CFA is required.

Rule 2: For REQ TYP B, when SPEC field is populated and the product is EELS, the 1st 8 characters of the SWC CLLI of the EATN must equal the 1st 8 characters of the Non-ACTL CLLI (MUXLOC).

***** End of definition for SPEC / LSR form screen *****

CCP 2038 Attachment Listed Below

ELMS6

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= T: EU	REMARKS	change to	REMARKS (M)
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= T: LSR	REMARKS (M)	change to	REMARKS (M)
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= V: EU	FBI	change to	condition
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= V: EU	FBI*	change to	FBI
17.0	ELMS6	A	Analog Non-Designed Loop	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT= C: LSR	DRC	change to	DRC*
17.0	ELMS6	A	Analog Designed Loop	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT= N: LSR	REMARKS (M)	change to	REMARKS (M)
17.0	ELMS6	A	Analog Designed Loop	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT= V: EU	FBI	change to	condition
17.0	ELMS6	A	Analog Designed Loop	ACT= V: EU	FBI*	change to	FBI
17.0	ELMS6	A	Analog Designed Loop	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Analog Designed	LNA= C: LS	JR	change	JR*

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Loop			to	
17.0	ELMS6	A	Analog Designed Loop	LNA= N: LS	JR	change to	JR*
17.0	ELMS6	A	Analog Designed Loop	LNA= V: LS	JR	change to	JR*
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= C: LSR	DRC	change to	DRC*
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= C: LSR	IMPCON-TEL NO.	remove field from	condition
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= D: LSR	IMPCON-TEL NO.	add field as	required
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= T: EU	AN	change to	AN (M)
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= V: EU	FBI	change to	condition
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= V: EU	FBI*	change to	FBI
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= V: EU	FB-SBILLNM	add field as	condition
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= C: LSR	DRC	change to	DRC*
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= D: LSR	IMPCON-TEL NO.	change to	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= V: EU	FBI	change to	condition
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= V: EU	FBI*	change to	FBI
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= V: EU	FB-SBILLNM	add field as	condition
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	LNA= C: LS	NIDR	change to	NIDR*
17.0	ELMS6	A	CLEC to CLEC Conversion Non-Designed Loop	ACT= W: LSR	IMPCON-TEL NO. (M)	change to	required
17.0	ELMS6	A	CLEC to CLEC Conversion Designed Loop	ACT= W: LSR	IMPCON-TEL NO. (M)	change to	required
17.0	ELMS6	A	Channelized DS1, DS3, STS1 Local Channel	ACT= N: LSR	IMPCON-TEL NO. (M)	change to	required
17.0	ELMS6	A	Network Interface Devices (NIDs)	ACT= N: LSR	IMPCON-TEL NO. (M)	change to	required
17.0	ELMS6	A	Network Interface Devices (NIDs)	LNA= N: LS	NIDR (M)	change to	NIDR* (M)
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= D: EU	LCON-TEL NO.	change to	optional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled	ACT= N:	IMPCON-	change	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Copper Loop – Designed (UCL)	LSR	TEL NO.	to	
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= V: EU	FBI	change to	condition
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= V: EU	FBI*	change to	FBI
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: EU	FBI	change to	condition
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: EU	FBI*	change to	FBI
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT= C: LSR	DRC*	add field as	optional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT= C: LSR	IMPCON-TEL NO. (M)	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT= D: LSR	REMARKS (M)	change to	REMARKS
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT= W: LSR	IMPCON-TEL NO. (M)	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= V: EU	FBI	change to	condition
17.0	ELMS6	A	xDSL Loops	ACT= V: EU	FBI*	change to	FBI
17.0	ELMS6	A	xDSL Loops	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled CO-based Line Share (BST-Owned Splitter)	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled CO-based Line Share (BST-Owned Splitter)	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled CO-based Line Share (BST-Owned Splitter)	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	Unbundled CO-based Line Share (BST-Owned Splitter)	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	HFS Unbundled	ACT= C:	IMPCON-	change	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			CO-based Line Splitting (DLEC-Owned Splitter)	LSR	TEL NO.	to	
17.0	ELMS6	A	HFS Unbundled CO-based Line Splitting (DLEC-Owned Splitter)	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	HFS Unbundled CO-based Line Splitting (DLEC-Owned Splitter)	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	HFS Unbundled CO-based Line Splitting (DLEC-Owned Splitter)	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	Non-Channelized DS3 and STS1	ACT= N: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= C: LSR	DRC* (M)	add field as	optional
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= C: LSR	IMPCON-TEL NO.(M)	add field as	required
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= D: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= N: LSR	DRC* (M)	add field as	optional
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= N: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= V: LSR	DRC* (M)	add field as	optional
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	Unbundled Network Terminating Wire-UNTW	ACT= C: EU	VER	change to	VER (M)
17.0	ELMS6	A	Unbundled Network Terminating Wire-UNTW	ACT= C: LSR	ALT-IMPCON	change to	ALT-IMPCON*
17.0	ELMS6	A	Unbundled	ACT= C:	DRC*	add field	optional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Network Terminating Wire-UNTW	LSR		as	
17.0	ELMS6	A	Unbundled Network Terminating Wire-UNTW	ACT= C: LSR	DSGCON-FAX NO.	add field as	condition
17.0	ELMS6	A	Unbundled Network Terminating Wire-UNTW	ACT= C: LSR	DSGCON-FLOOR	add field as	condition
17.0	ELMS6	A	Unbundled Network Terminating Wire-UNTW	ACT= C: LSR	DSGCON-ROOM/MAIL STOP	add field as	condition
17.0	ELMS6	A	Unbundled CO-based Line Share (DLEC-Owned Splitter)	ACT= C: LSR	IMPCON*	change to	IMPCON
17.0	ELMS6	A	Unbundled CO-based Line Share (DLEC-Owned Splitter)	ACT= N: LSR	IMPCON-TEL NO.	add field as	required
17.0	ELMS6	A	Unbundled CO-based Line Share (DLEC-Owned Splitter)	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	HFS Unbundled CO-based Line Splitting (BST-Owned Splitter)	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	HFS Unbundled CO-based Line Splitting (BST-Owned Splitter)	ACT= D: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	HFS Unbundled CO-based Line Splitting (BST-Owned Splitter)	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	A	HFS Unbundled CO-based Line Splitting (BST-Owned Splitter)	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	HFS Unbundled	ACT= W:	IMPCON-	change	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			CO-based Line Splitting (BST-Owned Splitter)	LSR	TEL NO.(M)	to	
17.0	ELMS6	A	Unbundled Dark Fiber (UDF)	LNA= N: LS	JK NUM (M)	add field as	condition
17.0	ELMS6	A	Unbundled Dark Fiber (UDF)	LNA= N: LS	JK POS (M)	add field as	condition
17.0	ELMS6	A	OCU 2w ISDN-BRI	LNA= N: LS	IWJK (M)	add field as	condition
17.0	ELMS6	A	OCU 2w ISDN-BRI	LNA= N: LS	IWJQ (M)	add field as	condition
17.0	ELMS6	A	OCU 2w ISDN-BRI	LNA= N: LS	JK NUM (M)	add field as	condition
17.0	ELMS6	A	OCU 2w ISDN-BRI	LNA= N: LS	JK POS (M)	add field as	condition
17.0	ELMS6	A	OCU 56 / 64 kbps	LNA= N: LS	JK NUM (M)	add field as	condition
17.0	ELMS6	A	OCU 56 / 64 kbps	LNA= N: LS	JK POS (M)	add field as	condition
17.0	ELMS6	A	OCU DS-1	LNA= N: LS	IWJK (M)	add field as	condition
17.0	ELMS6	A	OCU DS-1	LNA= N: LS	IWJQ (M)	add field as	condition
17.0	ELMS6	A	OCU DS-1	LNA= N: LS	JK NUM (M)	add field as	condition
17.0	ELMS6	A	OCU DS-1	LNA= N: LS	JK POS (M)	add field as	condition
17.0	ELMS6	A	OCU DS-3/STS-1	LNA= N: LS	IWJK (M)	add field as	condition
17.0	ELMS6	A	OCU DS-3/STS-1	LNA= N: LS	IWJQ (M)	add field as	condition
17.0	ELMS6	A	OCU DS-3/STS-1	LNA= N: LS	JK NUM (M)	add field as	condition
17.0	ELMS6	A	OCU DS-3/STS-1	LNA= N: LS	JK POS (M)	add field as	condition
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: LSR	ALT-IMPCON	change to	ALT-IMPCON*
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: LSR	DRC*	add field as	optional
17.0	ELMS6	A	Digital Data Designed Loop	ACT= N: LSR	ALT-IMPCON	change to	ALT-IMPCON*

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			(DS1)		(M)		(M)
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= T: LSR	ALT- IMPCON	change to	ALT- IMPCON*
17.0	ELMS6	A	RS (Remote Site) HFS Line Splitting (DLEC- Owned Splitter)	ACT= C: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	A	RS (Remote Site) HFS Line Splitting (DLEC- Owned Splitter)	ACT= D: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	A	RS (Remote Site) HFS Line Splitting (DLEC- Owned Splitter)	ACT= N: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	A	RS (Remote Site) HFS Line Splitting (DLEC- Owned Splitter)	ACT= V: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	A	RS (Remote Site) HFS Line Splitting (DLEC- Owned Splitter)	ACT= W: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	A	Non-Channelized IOC	ACT = C: LSR	PG_OF_	change to	PG_OF_ (M)
17.0	ELMS6	A	Non-Channelized IOC	ACT = D: LSR	PG_OF_	change to	PG_OF_ (M)
17.0	ELMS6	A	Non-Channelized IOC	ACT = N: LSR	PG_OF_	change to	PG_OF_ (M)
17.0	ELMS6	A	Non-Channelized IOC	ACT= C: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	A	Non-Channelized IOC	ACT= N: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	A	Non-Channelized IOC	LNA = C: LS	REMARKS	change to	REMARKS (M)
17.0	ELMS6	A	Non-Channelized IOC	LNA = D: LS	REMARKS	change to	REMARKS (M)
17.0	ELMS6	A	Non-Channelized IOC	LNA = N: LS	REMARKS	change to	REMARKS (M)
17.0	ELMS6	A	Non-Channelized IOC	LNA= C: LS	JK NUM	add field as	condition
17.0	ELMS6	A	Non-Channelized IOC	LNA= C: LS	JK POS	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	A	Non-Channelized IOC	LNA= N: LS	JK NUM	add field as	condition
17.0	ELMS6	A	Non-Channelized IOC	LNA= N: LS	JK POS	add field as	condition
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	ACT= D: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	ACT= N: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	LNA= N: LS	JR (M)	change to	JR* (M)
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	LNA= V: LS	JR (M)	change to	JR* (M)
17.0	ELMS6	B	INP, Designed Analog Loop	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	B	INP, Non-Designed Analog Loop	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	B	INP, Unbundled Copper Loop – Designed (UCL-D)	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	B	INP, xDSL Loops	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	B	LNP, Designed Analog Loop	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	B	LNP, Non-Designed Analog Loop	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	B	LNP, Unbundled Copper Loop – Designed (UCL-D)	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	B	LNP, xDSL Loops	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	B	INP, Digital Designed Basic Rate ISDN	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	B	INP, Digital Data Designed Loop (DS0)	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	B	LNP, Digital Designed Basic Rate ISDN	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	B	LNP, Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: EU	AN	change to	AN (M)
17.0	ELMS6	B	LNP, Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: EU	ATN	change to	ATN (M)
17.0	ELMS6	B	LNP, Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: EU	VER	change to	VER (M)
17.0	ELMS6	B	LNP, Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	B	UNE to UNE Bulk Migrations	ACT= V: LSR	DRC (E)	change to	DRC* (E)
17.0	ELMS6	B	INP, Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: EU	FB-ZIP (M)	add field as	condition
17.0	ELMS6	B	INP, Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	B	LNP, EELs	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Resale, non-complex	ACT= C: EU	TC NAME	add field as	condition
17.0	ELMS6	E	Resale, non-complex	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Resale, non-complex	ACT= L: EU	TC NAME	add field as	condition
17.0	ELMS6	E	Resale, non-complex	ACT= L: EU	TC PER	add field as	condition
17.0	ELMS6	E	Resale, non-complex	ACT= L: EU	TCID	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	Resale, non-complex	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Resale, non-complex	ACT= T: EU	TC PER	add field as	condition
17.0	ELMS6	E	Resale, non-complex	ACT= T: EU	TCID	add field as	condition
17.0	ELMS6	E	Resale, non-complex	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Resale, non-complex	ACT= V: EU	TCID	add field as	condition
17.0	ELMS6	E	Resale, non-complex	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Resale, non-complex	ACT= W: EU	FBI	change to	FBI*
17.0	ELMS6	E	Resale, non-complex	ACT= W: EU	FBI*	change to	optional
17.0	ELMS6	E	Resale, non-complex	LNA= C: RS	TC NAME	add field as	condition
17.0	ELMS6	E	Resale, non-complex	LNA= G: RS	NIDR	change to	NIDR*
17.0	ELMS6	E	Resale, non-complex	LNA= T: RS	FA*	change to	FA
17.0	ELMS6	E	Resale, non-complex	LNA= T: RS	FA*	change to	condition
17.0	ELMS6	E	Hunting	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Hunting	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Hunting	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Hunting	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT = W: EU	VER	change to	VER (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= C: EU	AN	change to	AN (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= C: EU	ATN	change to	ATN (M)
17.0	ELMS6	E	Remote Call Forwarding	ACT= C: EU	VER	change to	VER (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			(RCF)				
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= N: EU	AN	change to	AN (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= N: EU	ATN	change to	ATN (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= N: EU	VER	change to	VER (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= T: EU	TC PER	add field as	condition
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= T: EU	TCID	add field as	condition
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= T: EU	VER	change to	VER (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= V: EU	AN	change to	AN (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= V: EU	ATN	change to	ATN (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= V: EU	TCID	add field as	condition
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= V: EU	VER	change to	VER (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= W: EU	FBI	change to	FBI*
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT= W: EU	FBI*	change to	optional
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA = D: RS	ATN	change to	ATN (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA = G: RS	VER	change to	VER (M)
17.0	ELMS6	E	Remote Call	LNA = N: RS	VER	change	VER (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Forwarding (RCF)			to	
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA = V: RS	ATN	change to	ATN (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA = V: RS	VER	change to	VER (M)
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA= C: RS	FA	change to	required
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA= G: RS	FA	change to	required
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA= N: RS	FA	change to	required
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA= T: RS	BLOCK	add field as	condition
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA= T: RS	FA	change to	required
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA= T: RS	FA*	change to	FA
17.0	ELMS6	E	Remote Call Forwarding (RCF)	LNA= V: RS	FA	change to	required
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT = D: EU	REMARKS	change to	REMARKS (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT = W: EU	REMARKS	change to	REMARKS (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= C: EU	AN	change to	AN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= C: EU	ATN	change to	ATN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= D: EU	TC NAME	add field as	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= N: LSR	IMPCON-TEL NO.(M)	change to	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= T: EU	TC PER	add field as	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= T: EU	TCID	add field as	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= T: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= V: EU	FBI	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= V: EU	FBI*	change to	FBI
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= V: EU	FB-SBILLNM	add field as	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= V: EU	REMARKS	change to	REMARKS (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= V: EU	TCID	add field as	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= W: EU	FBI	change to	FBI*
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT= W: EU	FBI*	change to	optional
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = C: RS	AN	change to	AN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = C: RS	ATN	change to	ATN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = C: RS	PON	change to	PON (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = P: RS	AN	change to	AN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = P: RS	ATN	change to	ATN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = P: RS	PON	change to	PON (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = V: RS	PON	change to	PON (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = W: RS	AN	change to	AN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = W: RS	ATN	change to	ATN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = W: RS	PON	change to	PON (M)
17.0	ELMS6	E	ISDN-BRI Resale	LNA = X: RS	AN	change	AN (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Service			to	
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA = X: RS	ATN	change to	ATN (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= C: RS	FA	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= C: RS	FA*	change to	FA
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= N: RS	FA (M)	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= N: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= P: RS	FA	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= P: RS	FA*	change to	FA
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= V: RS	FA (M)	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= V: RS	FEATURE (M)	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= V: RS	FEATURE DETAIL (M)	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= W: RS	FA	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= W: RS	FEATURE	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= W: RS	FEATURE DETAIL	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= X: RS	FA	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= X: RS	FEATURE	change to	condition
17.0	ELMS6	E	ISDN-BRI Resale Service	LNA= X: RS	FEATURE DETAIL	change to	condition
17.0	ELMS6	E	Coin	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Coin	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Coin	ACT= T: EU	TC PER	add field as	condition
17.0	ELMS6	E	Coin	ACT= T: EU	TCID	add field as	condition
17.0	ELMS6	E	Coin	ACT= T: LSR	IMPCON-TEL NO.	change to	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	Coin	ACT= V: EU	FB-BILLCON (E)	change to	FB-BILLCON
17.0	ELMS6	E	Coin	ACT= V: EU	TCID	add field as	condition
17.0	ELMS6	E	Coin	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	E	Coin	ACT= W: EU	FBI	change to	FBI*
17.0	ELMS6	E	Coin	ACT= W: EU	FBI*	change to	optional
17.0	ELMS6	E	Coin	LNA= C: RS	FA	change to	condition
17.0	ELMS6	E	Coin	LNA= C: RS	FA*	change to	FA
17.0	ELMS6	E	Coin	LNA= G: RS	FA	change to	condition
17.0	ELMS6	E	Coin	LNA= G: RS	FA*	change to	FA
17.0	ELMS6	E	Coin	LNA= G: RS	NIDR	change to	NIDR*
17.0	ELMS6	E	Coin	LNA= N: RS	FA	change to	condition
17.0	ELMS6	E	Coin	LNA= N: RS	FA*	change to	FA
17.0	ELMS6	E	Coin	LNA= V: RS	FA	change to	condition
17.0	ELMS6	E	Coin	LNA= V: RS	FA*	change to	FA
17.0	ELMS6	E	Coin	LNA= X: RS	FA	change to	condition
17.0	ELMS6	E	Coin	LNA= X: RS	FA*	change to	FA
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= N: LSR	DRC (M)	change to	DRC* (M)
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= N: LSR	DSGCON-CITY (M)	add field as	condition
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= N: LSR	DSGCON-FAX NO. (M)	add field as	condition
17.0	ELMS6	E	BellSouth®	ACT= N:	DSGCON-	add field	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Intergrated Solutions	LSR	FLOOR (M)	as	
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= N: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= N: LSR	DSGCON-STATE (M)	add field as	condition
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= N: LSR	DSGCON-STREET (M)	add field as	condition
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= N: LSR	DSGCON-ZIP CODE (M)	add field as	condition
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	E	AccuPulse®	ACT= N: LSR	DSGCON-CITY (M)	add field as	condition
17.0	ELMS6	E	AccuPulse®	ACT= N: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	AccuPulse®	ACT= N: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	AccuPulse®	ACT= N: LSR	DSGCON-STATE (M)	add field as	condition
17.0	ELMS6	E	AccuPulse®	ACT= N: LSR	DSGCON-STREET (M)	add field as	condition
17.0	ELMS6	E	AccuPulse®	ACT= N: LSR	DSGCON-ZIP CODE (M)	add field as	condition
17.0	ELMS6	E	AccuPulse®	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	AccuPulse®	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	ATM	ACT= C: LSR	REMARKS (M)	change to	REMARKS
17.0	ELMS6	E	ATM	ACT= D: LSR	IMP CON (M)	change to	IMP CON* (M)
17.0	ELMS6	E	ATM	ACT= D:	IMP CON-	change	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
				LSR	TEL NO.(M)	to	
17.0	ELMS6	E	ATM	ACT= D: LSR	REMARKS (M)	change to	REMARKS
17.0	ELMS6	E	ATM	ACT= N: LSR	REMARKS (M)	change to	REMARKS
17.0	ELMS6	E	ATM	ACT= T: EU	DSGCON (M)	remove field from	condition
17.0	ELMS6	E	ATM	ACT= T: EU	DSGCON- TEL NO. (M)	remove field from	condition
17.0	ELMS6	E	ATM	ACT= T: LSR	REMARKS (M)	change to	REMARKS
17.0	ELMS6	E	ATM	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	ATM	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	Frame Relay	ACT= T: EU	DSGCON (M)	remove field from	condition
17.0	ELMS6	E	Frame Relay	ACT= T: EU	DSGCON- TEL NO. (M)	remove field from	condition
17.0	ELMS6	E	Frame Relay	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	Frame Relay	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	MegaLink® Service	ACT= N: LSR	DRC (M)	change to	DRC* (M)
17.0	ELMS6	E	MegaLink® Service	ACT= N: LSR	DSGCON- CITY (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Service	ACT= N: LSR	DSGCON- FAX NO. (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Service	ACT= N: LSR	DSGCON- FLOOR (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Service	ACT= N: LSR	DSGCON- ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Service	ACT= N: LSR	DSGCON- STATE (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Service	ACT= N: LSR	DSGCON- STREET (M)	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	MegaLink® Service	ACT= N: LSR	DSGCON-ZIP CODE (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Service	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	MegaLink® Service	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	MegaLink® Channel Services	ACT= N: LSR	DRC (M)	change to	DRC* (M)
17.0	ELMS6	E	MegaLink® Channel Services	ACT= N: LSR	DSGCON-CITY (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Channel Services	ACT= N: LSR	DSGCON-FAX NO. (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Channel Services	ACT= N: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Channel Services	ACT= N: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Channel Services	ACT= N: LSR	DSGCON-STATE (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Channel Services	ACT= N: LSR	DSGCON-STREET (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Channel Services	ACT= N: LSR	DSGCON-ZIP CODE (M)	add field as	condition
17.0	ELMS6	E	MegaLink® Channel Services	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	MegaLink® Channel Services	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	NMLI	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	NMLI	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	NMLI	ACT= W: EU	FB-STREET (M)	add field as	condition
17.0	ELMS6	E	Primary Rate ISDN -PRI	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	Primary Rate ISDN -PRI	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	SMARTRing® Service	ACT= C: LSR	ALT-IMP CON (M)	change to	ALT-IMP CON* (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	SMARTRing® Service	ACT= C: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= C: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= N: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= N: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= N: LSR	DSGCON-STREET. (M)	add field as	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= T: EU	FBI* (M)	remove field from	optional
17.0	ELMS6	E	SMARTRing® Service	ACT= T: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= T: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= T: LSR	DSGCON-STREET. (M)	add field as	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	E	SMARTRing® Service	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	E	SMARTRing® Service	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	SMARTRing® Service	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	SMARTRing® Service	ACT= W: LSR	IMPCON (M)	change to	IMPCON* (M)
17.0	ELMS6	E	SMARTRing® Service	ACT= W: LSR	IMPCON-TEL NO.(M)	change to	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= C: LSR	DRC* (M)	add field as	optional
17.0	ELMS6	E	LIGHTGATE® Services	ACT= C: LSR	DSGCON-FAX NO. (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= C: LSR	DSGCON-FLOOR (M)	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	LIGHTGATE® Services	ACT= C: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= N: LSR	DRC (M)	change to	DRC* (M)
17.0	ELMS6	E	LIGHTGATE® Services	ACT= N: LSR	DSGCON-CITY (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= N: LSR	DSGCON-FAX NO. (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= N: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= N: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= N: LSR	DSGCON-STATE (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= N: LSR	DSGCON-STREET (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= N: LSR	DSGCON-ZIP CODE (M)	add field as	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= T: EU	FBI* (M)	remove field from	optional
17.0	ELMS6	E	LIGHTGATE® Services	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	E	LIGHTGATE® Services	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	E	LIGHTGATE® Services	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	LIGHTGATE® Services	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	LIGHTGATE® Services	ACT= W: EU	IMPCON (M)	remove field from	optional
17.0	ELMS6	E	LIGHTGATE® Services	ACT= W: EU	IMPCON-TEL NO.(M)	remove field from	optional
17.0	ELMS6	E	LIGHTGATE® Services	ACT= W: LSR	IMPCON (M)	change to	IMPCON* (M)
17.0	ELMS6	E	TFD	ACT= C: EU	TC NAME (M)	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	TFD	ACT= C: EU	TC PER (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= C: EU	TC TO PRI (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= C: EU	TC TO SEC (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= D: EU	TCID (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= N: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= N: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= N: LSR	DSGCON-STATE (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= V: EU	FB-FLOOR (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= V: EU	FB-ROOM (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= V: EU	FB-SBILLNM (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= V: EU	TC OPT* (M)	add field as	optional
17.0	ELMS6	E	TFD	ACT= V: EU	TCID (M)	add field as	condition
17.0	ELMS6	E	TFD	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	TFD	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	TFD	LNA= C: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	TFD	LNA= C: RS	BLOCK (M)	add field as	condition
17.0	ELMS6	E	TFD	LNA= C: RS	FA (M)	change to	condition
17.0	ELMS6	E	TFD	LNA= C: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	TFD	LNA= D: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	TFD	LNA= D: RS	BLOCK (M)	add field as	condition
17.0	ELMS6	E	TFD	LNA= D: RS	FA (M)	change	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
						to	
17.0	ELMS6	E	TFD	LNA= D: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	TFD	LNA= N: RS	FA (M)	change to	condition
17.0	ELMS6	E	TFD	LNA= N: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	TFD	LNA= N: RS	FEATURE DEATAIL (M)	change to	condition
17.0	ELMS6	E	TFD	LNA= N: RS	NIDR (M)	change to	NIDR* (M)
17.0	ELMS6	E	TFD	LNA= P: RS	FA (M)	change to	condition
17.0	ELMS6	E	TFD	LNA= P: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	TFD	LNA= V: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	TFD	LNA= V: RS	BLOCK (M)	add field as	condition
17.0	ELMS6	E	TFD	LNA= V: RS	FA (M)	change to	condition
17.0	ELMS6	E	TFD	LNA= V: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	TFD	LNA= W: RS	FA (M)	change to	condition
17.0	ELMS6	E	TFD	LNA= W: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	TFD	LNA= X: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	TFD	LNA= X: RS	BLOCK (M)	add field as	condition
17.0	ELMS6	E	TFD	LNA= X: RS	FA (M)	change to	condition
17.0	ELMS6	E	TFD	LNA= X: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	TIE Lines	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	TIE Lines	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	On/Off Premises Extensions	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	On/Off Premises	ACT= W: EU	FBI* (M)	change	optional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Extensions			to	
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= N: LSR	DRC (M)	change to	DRC* (M)
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= N: LSR	DSGCON-CITY (M)	add field as	condition
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= N: LSR	DSGCON-FAX NO. (M)	add field as	condition
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= N: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= N: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= N: LSR	DSGCON-STATE (M)	add field as	condition
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= N: LSR	DSGCON-STREET (M)	add field as	condition
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= N: LSR	DSGCON-ZIP CODE (M)	add field as	condition
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	BellSouth® 256 DSL Service	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	WATS	ACT= D: EU	TCID (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= D: LSR	IMPCON-TEL NO. (M)	remove field from	condition
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON-CITY (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON-FAX NO. (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON-STATE (M)	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON-STREET (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON-TEL NO. (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= N: LSR	DSGCON-ZIP CODE (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= V: EU	FB-FLOOR (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= V: EU	FB-ROOM (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= V: EU	FB-SBILLNM (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= V: EU	TCID (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= W: EU	FB-BILLCON (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= W: EU	FB-BILLCON-TEL NO. (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= W: EU	FB-FLOOR (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	WATS	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	WATS	ACT= W: EU	FB-ROOM (M)	add field as	condition
17.0	ELMS6	E	WATS	ACT= W: EU	FB-SBILLNM (M)	add field as	condition
17.0	ELMS6	E	WATS	LNA= C: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	WATS	LNA= C: RS	BLOCK (M)	add field as	condition
17.0	ELMS6	E	WATS	LNA= C: RS	FA (M)	change to	condition
17.0	ELMS6	E	WATS	LNA= C: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	WATS	LNA= C: RS	NIDR* (M)	add field as	optional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	WATS	LNA= D: RS	FA (M)	change to	condition
17.0	ELMS6	E	WATS	LNA= D: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	WATS	LNA= N: RS	FA (M)	change to	condition
17.0	ELMS6	E	WATS	LNA= N: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	WATS	LNA= N: RS	FEATURE DEATAIL (M)	add field as	condition
17.0	ELMS6	E	WATS	LNA= N: RS	NIDR* (M)	add field as	optional
17.0	ELMS6	E	WATS	LNA= P: RS	FA (M)	change to	condition
17.0	ELMS6	E	WATS	LNA= P: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	WATS	LNA= V: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	WATS	LNA= V: RS	FA (M)	change to	condition
17.0	ELMS6	E	WATS	LNA= V: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	WATS	LNA= W: RS	FA (M)	change to	condition
17.0	ELMS6	E	WATS	LNA= W: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	WATS	LNA= X: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	WATS	LNA= X: RS	FA (M)	change to	condition
17.0	ELMS6	E	WATS	LNA= X: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= C: EU	LCON-TEL NO. (M)	change to	optional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= C: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	FB-FLOOR (M)	remove field from	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	FB-ROOM (M)	remove field from	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	FB-SBILLNM (M)	remove field from	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	TCID (M)	add field as	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= N: EU	LCON-TEL NO. (M)	change to	optional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= N: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	LCON-TEL NO. (M)	change to	optional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	TC NAME (M)	add field as	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	TC PER (M)	add field as	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	TCID (M)	add field as	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= V: EU	LCON-TEL NO. (M)	change to	optional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= V: EU	TCID (M)	add field as	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= V: EU	TCMI (M)	remove field from	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= V: LSR	IMPCON-TEL NO.(M)	change to	required
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= C: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= C: RS	FA (M)	change to	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= C: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= N: RS	FA (M)	change to	condition
17.0	ELMS6	E	Uniserv UAN /	LNA= N: RS	FA* (M)	change	FA (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			CSA / ANI			to	
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= V: RS	BA (M)	change to	BA* (M)
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= V: RS	BLOCK (M)	add field as	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= V: RS	FA (M)	change to	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= V: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= W: RS	FA (M)	change to	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= W: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= X: RS	FA (M)	change to	condition
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	LNA= X: RS	FA* (M)	change to	FA (M)
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	BellSouth® Metro Ethernet	ACT= W: EU	FB- BILLNM (M)	add field as	condition
17.0	ELMS6	E	BellSouth® Metro Ethernet	ACT= W: EU	FBI (M)	change to	FBI* (M)
17.0	ELMS6	E	BellSouth® Metro Ethernet	ACT= W: EU	FBI* (M)	change to	optional
17.0	ELMS6	E	BellSouth® Metro Ethernet	ACT= W: EU	FB-STREET (M)	add field as	condition
17.0	ELMS6	F	Port Service	ACT= L: EU	TC PER	add field as	condition
17.0	ELMS6	F	Port Service	ACT= L: EU	TCID	add field as	condition
17.0	ELMS6	F	Port Service	ACT= N: LSR	APOT	change to	APOT (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	F	Port Service	ACT= N: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	F	Port Service	ACT= V: EU	TCID	add field as	condition
17.0	ELMS6	F	Port Service	ACT= V: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	F	Port Service	LNA= G: PS	BA*	add field as	optional
17.0	ELMS6	K	Private Line	ACT= C: LSR	ALT- IMPCON (M)	change to	ALT- IMPCON* (M)
17.0	ELMS6	K	Private Line	ACT= C: LSR	ALT- IMPCON- TEL NO. (M)	change to	condition
17.0	ELMS6	K	Private Line	ACT= C: LSR	DSGCON- FAX NO. (M)	change to	condition
17.0	ELMS6	K	Private Line	ACT= C: LSR	DSGCON- FLOOR (M)	add field as	condition
17.0	ELMS6	K	Private Line	ACT= C: LSR	DSGCON- ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	K	Private Line	ACT= N: LSR	ALT- IMPCON (M)	change to	ALT- IMPCON* (M)
17.0	ELMS6	K	Private Line	ACT= N: LSR	DSGCON- FAX NO. (M)	change to	condition
17.0	ELMS6	K	Private Line	ACT= N: LSR	DSGCON- FLOOR (M)	add field as	condition
17.0	ELMS6	K	Private Line	ACT= N: LSR	DSGCON- ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	K	Private Line	ACT= T: EU	FBI* (M)	remove field from	optional
17.0	ELMS6	K	Private Line	ACT= T: LSR	DSGCON- FAX NO. (M)	change to	condition
17.0	ELMS6	K	Private Line	ACT= T: LSR	DSGCON- FLOOR (M)	add field as	condition
17.0	ELMS6	K	Private Line	ACT= T: LSR	DSGCON- ROOM/MAIL STOP (M)	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	K	Private Line	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	K	Private Line	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	K	Private Line	ACT= V: EU	FB-SBILLNM (M)	add field as	condition
17.0	ELMS6	K	Private Line	ACT= V: LSR	ALT-IMPCON (M)	change to	ALT-IMPCON* (M)
17.0	ELMS6	K	Private Line	ACT= W: EU	FB-BILLCON-TEL NO. (M)	add field as	condition
17.0	ELMS6	K	Private Line	ACT= W: EU	FB-SBILLNM (M)	add field as	condition
17.0	ELMS6	K	Private Line	ACT= W: LSR	IMPCON (M)	change to	IMPCON* (M)
17.0	ELMS6	K	Private Line	ACT= W: LSR	IMPCON-TEL NO.(M)	change to	condition
17.0	ELMS6	K	Private Line	LNA= C: RPL	NIDR* (PD/SD) (M)	add field as	optional
17.0	ELMS6	K	Private Line	LNA= N: RPL	NIDR* (PD/SD) (M)	add field as	optional
17.0	ELMS6	K	Private Line	LNA= V: RPL	NIDR* (PD/SD) (M)	add field as	optional
17.0	ELMS6	K	Synchronet	ACT= C: LSR	ALT-IMPCON (M)	change to	ALT-IMPCON* (M)
17.0	ELMS6	K	Synchronet	ACT= C: LSR	ALT-IMPCON-TEL NO. (M)	change to	condition
17.0	ELMS6	K	Synchronet	ACT= C: LSR	DSGCON-FAX NO. (M)	change to	condition
17.0	ELMS6	K	Synchronet	ACT= C: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	K	Synchronet	ACT= C: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	K	Synchronet	ACT= N: LSR	ALT-IMPCON (M)	change to	ALT-IMPCON* (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	K	Synchronet	ACT= N: LSR	ALT- IMPCON- TEL NO. (M)	change to	condition
17.0	ELMS6	K	Synchronet	ACT= N: LSR	DSGCON- FAX NO. (M)	change to	condition
17.0	ELMS6	K	Synchronet	ACT= N: LSR	DSGCON- FLOOR (M)	add field as	condition
17.0	ELMS6	K	Synchronet	ACT= N: LSR	DSGCON- ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	K	Synchronet	ACT= T: EU	FBI* (M)	remove field from	optional
17.0	ELMS6	K	Synchronet	ACT= T: LSR	ALT- IMPCON (M)	change to	ALT- IMPCON* (M)
17.0	ELMS6	K	Synchronet	ACT= T: LSR	ALT- IMPCON- TEL NO. (M)	change to	condition
17.0	ELMS6	K	Synchronet	ACT= T: LSR	DSGCON- FAX NO. (M)	change to	condition
17.0	ELMS6	K	Synchronet	ACT= T: LSR	DSGCON- FLOOR (M)	add field as	condition
17.0	ELMS6	K	Synchronet	ACT= T: LSR	DSGCON- ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	K	Synchronet	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	K	Synchronet	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	K	Synchronet	ACT= V: LSR	ALT- IMPCON (M)	change to	ALT- IMPCON* (M)
17.0	ELMS6	K	Synchronet	ACT= V: LSR	ALT- IMPCON- TEL NO. (M)	change to	condition
17.0	ELMS6	K	Synchronet	ACT= W: LSR	IMPCON (M)	change to	IMPCON* (M)
17.0	ELMS6	K	Synchronet	ACT= W: LSR	IMPCON- TEL NO.(M)	change to	condition
17.0	ELMS6	K	Synchronet	LNA= C: RPL	NIDR* (PD/SD) (M)	add field as	optional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	K	Synchronet	LNA= N: RPL	NIDR* (PD/SD) (M)	add field as	optional
17.0	ELMS6	K	Synchronet	LNA= V: RPL	NIDR* (PD/SD) (M)	add field as	optional
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= C: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= L: EU	TC PER	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= L: EU	TCID	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= N: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= T: EU	TC PER	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= T: EU	TCID	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= T: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= V: EU	TCID	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= V: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= W: EU	FBI	change to	FBI*

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= W: EU	FBI*	change to	optional
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	LNA= C: PS	TC NAME	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	LNA= T: PS	FA	change to	condition
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	LNA= T: PS	FA*	change to	FA
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= C: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= N: EU	AN	change to	AN (M)
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= N: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= N: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= T: EU	AN	change to	AN (M)
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= T: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= T: EU	TC PER	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= T: EU	TCID	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= T: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= V: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= V: EU	TCID	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= V: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= W: EU	FBI	change to	FBI*
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= W: EU	FBI*	change to	optional
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= C: PS	FA	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= G: PS	FA	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= G: PS	FEATURE DETAIL	add field as	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= N: PS	FA	change to	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= T: PS	FA	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= T: PS	FA*	change to	FA
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= T: PS	FEATURE	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= T: PS	FEATURE DETAIL	change to	required
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	LNA= V: PS	FA	change to	required
17.0	ELMS6	M	UNE-P/WLP Coin	ACT = D: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	ACT = W: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= C: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= N: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= T: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= T: EU	TC PER	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= T: EU	TCID	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= T: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= V: EU	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= V: EU	TCID	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= W: EU	FBI	change to	FBI*
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= W: EU	FBI*	change to	optional
17.0	ELMS6	M	UNE-P/WLP Coin	LNA = C: PS	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	LNA = D: PS	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	LNA = N: PS	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	LNA = P: PS	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	LNA = T: PS	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	LNA = V: PS	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	LNA = W: PS	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	LNA = X: PS	ATN	change to	ATN (M)
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= C: PS	FA	change to	condition
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= C: PS	FA*	change to	FA
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= G: PS	FA	change to	condition
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= G: PS	FA*	change to	FA
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= N: PS	FA	change to	condition
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= N: PS	FA*	change to	FA
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= T: PS	FA	change to	condition
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= T: PS	FA*	change to	FA
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= V: PS	FA	change to	condition
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= V: PS	FA*	change to	FA
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= X: PS	FA	change	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
						to	
17.0	ELMS6	M	UNE-P/WLP Coin	LNA= X: PS	FA*	change to	FA
17.0	ELMS6	M	UNE-P/WLP 4-wire ISDN PRI Combination	ACT= C: LSR	ALT-IMPCON (M)	change to	ALT-IMPCON* (M)
17.0	ELMS6	M	UNE-P/WLP 4-wire ISDN PRI Combination	ACT= V: EU	TCID	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire ISDN PRI Combination	ACT= V: LSR	ALT-IMPCON (M)	change to	ALT-IMPCON* (M)
17.0	ELMS6	M	UNE-P/WLP 4-wire ISDN PRI Combination	ACT= V: LSR	ALT-IMPCON-TEL NO. (M)	change to	condition
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= C: LSR	ALT-IMPCON (M)	change to	ALT-IMPCON* (M)
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= C: LSR	IMPCON (M)	change to	IMPCON* (M)
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= D: LSR	ALT-IMPCON (M)	change to	ALT-IMPCON* (M)
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= V: EU	FBI* (M)	remove field from	optional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= V: EU	FB-ROOM (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= V: EU	TCID (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	LNA= P: PS	FA* (M)	remove field from	optional
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= N: LSR	DRC (M)	change to	DRC* (M)
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= N: LSR	DSGCON-CITY (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= N: LSR	DSGCON-FAX NO. (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP	ACT= N:	DSGCON-	add field	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			DDITS - DS1	LSR	FLOOR (M)	as	
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= N: LSR	DSGCON- ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= N: LSR	DSGCON- STATE (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= N: LSR	DSGCON- STREET (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= N: LSR	DSGCON- ZIP CODE (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP DDITS - Trunk Service	ACT= V: EU	FB- BILLCON (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP DDITS - Trunk Service	ACT= V: EU	TCID (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4- wire DS1 Loop with Channelization with Port (DS1 Service)	ACT= N: LSR	DRC (M)	change to	DRC* (M)
17.0	ELMS6	M	UNE-P/WLP 4- wire DS1 Loop with Channelization with Port (DS1 Service)	ACT= N: LSR	DSGCON- CITY (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4- wire DS1 Loop with Channelization with Port (DS1 Service)	ACT= N: LSR	DSGCON- FAX NO. (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4- wire DS1 Loop with Channelization with Port (DS1 Service)	ACT= N: LSR	DSGCON- FLOOR (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4- wire DS1 Loop with	ACT= N: LSR	DSGCON- ROOM/MAIL STOP (M)	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Channelization with Port (DS1 Service)				
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (DS1 Service)	ACT= N: LSR	DSGCON-STATE (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (DS1 Service)	ACT= N: LSR	DSGCON-STREET (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (DS1 Service)	ACT= N: LSR	DSGCON-ZIP CODE (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= D: EU	FBI* (M)	remove field from	optional
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= V: EU	FB-BILLCON (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= V: EU	TCID (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= V: LSR	DSGCON (M)	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Service)				
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= V: LSR	DSGCON-CITY (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= V: LSR	DSGCON-FAX NO. (M)	change to	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= V: LSR	DSGCON-FLOOR (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= V: LSR	DSGCON-ROOM/MAIL STOP (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= V: LSR	DSGCON-TEL NO. (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= C: EU	TCID (M)	add field as	condition
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: LSR	ALT-IMP CON (M)	change to	ALT-IMP CON* (M)
17.0	ELMS6	M	UNE-P/WLP Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	FBI	change to	FBI*

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	M	UNE-P/WLP Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	FBI*	change to	optional
17.0	ELMS6	N	DID Resale Service	ACT= C: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	N	DID Resale Service	ACT= C: LSR	LSP AUTH	change to	LSP AUTH*
17.0	ELMS6	N	DID Resale Service	ACT= D: LSR	LSP AUTH* (M)	add field as	optional
17.0	ELMS6	N	DID Resale Service	ACT= N: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	N	DID Resale Service	ACT= N: LSR	LSP AUTH*	add field as	optional
17.0	ELMS6	N	DID Resale Service	ACT= T: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	N	DID Resale Service	ACT= T: LSR	LSP AUTH*	add field as	optional
17.0	ELMS6	N	DID Resale Service	ACT= V: LSR	IMPCON- TEL NO.	change to	required
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= C: DIDPBXDOD	BA	change to	BA* DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= C: DIDPBXDOD	BLOCK	change to	BLOCK DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= C: DIDPBXDOD	RIN	change to	RIN DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= C: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= C: DIDPBXDOD	TNS	change to	TNS DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= D: DIDPBXDOD	FEATURE DETAIL	add to	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= D: DIDPBXDOD	RIN	change to	RIN DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= D: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= D: DIDPBXDOD	TNS	change to	TNS DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= N: DIDPBXDOD	BA	change to	BA* DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= N: DIDPBXDOD	BLOCK	change to	BLOCK DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= N: DIDPBXDOD	FEATURE DETAIL	add to	condition
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= N: DIDPBXDOD	RIN	change to	RIN DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= N: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= N: DIDPBXDOD	TNS	change to	TNS DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= V: DIDPBXDOD	BA	change to	BA* DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= V: DIDPBXDOD	BLOCK	change to	BLOCK DID Telephone Number

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= V: DIDPBXDOD	RIN	change to	RIN DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= V: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= V: DIDPBXDOD	TNS	change to	TNS DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= W: DIDPBXDOD	BA	change to	BA* DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= W: DIDPBXDOD	BLOCK	change to	BLOCK DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= W: DIDPBXDOD	RIN	change to	RIN DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= W: DIDPBXDOD	TNS	change to	TNS DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= X: DIDPBXDOD	BA	change to	BA* DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= X: DIDPBXDOD	BLOCK	change to	BLOCK DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= X: DIDPBXDOD	RIN	change to	RIN DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= X: DIDPBXDOD	TC PER	change to	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	DID Resale Service - Telephone Number Section	TNA= X: DIDPBXDOD	TNS	change to	TNS DID Telephone Number
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= C: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= C: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= C: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= C: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= D: DIDPBXDOD	FEATURE DETAIL	add to	condition
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= D: DIDPBXDOD	TC NAME	add field as	condition
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= D: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= D: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= N: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= N: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= N: DIDPBXDOD	FEATURE DETAIL	add to	condition
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= N: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= N: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= V: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= V: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= V: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= V: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= W: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= W: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= W: DIDPBXDOD	TGN	change to	TGN Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= W: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= X: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= X: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= X: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	DID Resale Service - Trunk Service Detail Section	TACT= X: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID	ACT= C: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	N	UNE-P/WLP 2-wire DID	ACT= N: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	N	UNE-P/WLP 2-wire DID	ACT= V: LSR	IMPCON-TEL NO.	change to	required
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= C: DIDPBXDOD	BA (M)	change to	BA* (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= C: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= C: DIDPBXDOD	ECCKT (M)	change to	ECCKT (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= C: DIDPBXDOD	RIN (M)	change to	RIN DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= C: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID -	TNA= C: DIDPBXDOD	TNS (M)	change to	TNS DID Telephone

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Telephone Number Section				Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= D: DIDPBXDOD	FEATURE DETAIL	add to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= D: DIDPBXDOD	RIN (M)	change to	RIN DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= D: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= D: DIDPBXDOD	TNS (M)	change to	TNS DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= N: DIDPBXDOD	BA (M)	change to	BA* (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= N: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= N: DIDPBXDOD	ECCKT (M)	change to	ECCKT (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= N: DIDPBXDOD	FEATURE DETAIL	add to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= N: DIDPBXDOD	RIN (M)	change to	RIN (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= N: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID -	TNA= N: DIDPBXDOD	TNS (M)	change to	TNS (M) DID

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Telephone Number Section				Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= V: DIDPBXDOD	BA (M)	change to	BA* (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= V: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= V: DIDPBXDOD	RIN (M)	change to	RIN (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= V: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= V: DIDPBXDOD	TNS (M)	change to	TNS (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= W: DIDPBXDOD	BA (M)	change to	BA* (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= W: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= W: DIDPBXDOD	RIN (M)	change to	RIN (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= W: DIDPBXDOD	TNS (M)	change to	TNS (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID - Telephone Number Section	TNA= X: DIDPBXDOD	BA (M)	change to	BA* (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2- wire DID -	TNA= X: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) DID

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Telephone Number Section				Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= X: DIDPBXDOD	RIN (M)	change to	RIN (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= X: DIDPBXDOD	TC PER (M)	change to	condition TNS (M) DID Telephone Number
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Telephone Number Section	TNA= X: DIDPBXDOD	TNS (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= C: DIDPBXDOD	BA (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= C: DIDPBXDOD	BLOCK (M)	change to	condition TNS (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= C: DIDPBXDOD	TC PER (M)	change to	condition TNS (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= C: DIDPBXDOD	TNS (M)	change to	condition TNS (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= D: DIDPBXDOD	FEATURE DETAIL	add to	condition TNS (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= D: DIDPBXDOD	TC NAME (M)	add field as	condition TNS (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= D: DIDPBXDOD	TC PER (M)	change to	condition TNS (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk	TACT= D: DIDPBXDOD	TNS (M)	change to	condition TNS (M) Trunk Service Detail

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Service Detail Section				Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= N: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= N: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= N: DIDPBXDOD	FEATURE DETAIL	add to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= N: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= N: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= V: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= V: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= V: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= V: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= W: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk	TACT= W: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Service Detail Section				Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= W: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= X: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= X: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= X: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP 2-wire DID - Trunk Service Detail Section	TACT= X: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	ACT= C: LSR	IMP CON-TEL NO.	change to	required
17.0	ELMS6	N	PBX Resale Service	ACT= C: LSR	LSP AUTH	change to	LSP AUTH*
17.0	ELMS6	N	PBX Resale Service	ACT= D: LSR	LSP AUTH	change to	LSP AUTH*
17.0	ELMS6	N	PBX Resale Service	ACT= N: LSR	IMP CON-TEL NO.	change to	required
17.0	ELMS6	N	PBX Resale Service	ACT= N: LSR	LSP AUTH	change to	LSP AUTH*
17.0	ELMS6	N	PBX Resale Service	ACT= T: LSR	IMP CON-TEL NO.	change to	required
17.0	ELMS6	N	PBX Resale Service	ACT= T: LSR	LSP AUTH	change to	LSP AUTH*
17.0	ELMS6	N	PBX Resale Service	ACT= T: LSR	REMARKS (M)	change to	REMARKS
17.0	ELMS6	N	PBX Resale Service	ACT= V: LSR	IMP CON-TEL NO.	change to	required
17.0	ELMS6	N	PBX Resale Service	ACT= V: LSR	LSP AUTH	change to	LSP AUTH*
17.0	ELMS6	N	PBX Resale Service	ACT= W: LSR	LSP AUTH	change to	LSP AUTH*

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	PBX Resale Service	TACT= C: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= C: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= C: DIDPBXDOD	TC PER	change to	condition TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= C: DIDPBXDOD	TNS	change to	condition TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= D: DIDPBXDOD	BA* Trunk Service Detail	add field as	optional BLOCK Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= D: DIDPBXDOD	BLOCK	change to	condition BLOCK Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= D: DIDPBXDOD	TC PER	change to	condition TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= D: DIDPBXDOD	TNS	change to	condition TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= G: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= G: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= G: DIDPBXDOD	TC PER	change to	condition TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= G: DIDPBXDOD	TC TO SEC	add field as	condition TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= N: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= N: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= N: DIDPBXDOD	TC PER	change to	condition TNS Trunk Service Detail

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	PBX Resale Service	TACT= N: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= V: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= V: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= V: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	PBX Resale Service	TACT= V: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= W: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= W: DIDPBXDOD	BLOCK Trunk Service Detail	add field as	optional
17.0	ELMS6	N	PBX Resale Service	TACT= W: DIDPBXDOD	TGN	change to	TGN Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= W: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= X: DIDPBXDOD	BA	change to	BA* Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= X: DIDPBXDOD	BLOCK	change to	BLOCK Trunk Service Detail
17.0	ELMS6	N	PBX Resale Service	TACT= X: DIDPBXDOD	JR	change to	JR*
17.0	ELMS6	N	PBX Resale Service	TACT= X: DIDPBXDOD	NIDR	change to	NIDR*
17.0	ELMS6	N	PBX Resale Service	TACT= X: DIDPBXDOD	TC PER	change to	condition
17.0	ELMS6	N	PBX Resale Service	TACT= X: DIDPBXDOD	TNS	change to	TNS Trunk Service Detail

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT= C: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT= C: LSR	LSP AUTH (M)	change to	LSP AUTH* (M)
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT= D: LSR	IMPCON- TEL NO.(M)	add field as	condition
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT= D: LSR	LSP AUTH (M)	change to	LSP AUTH* (M)
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT= N: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT= N: LSR	LSP AUTH (M)	change to	LSP AUTH* (M)
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= C: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= C: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= C: DIDPBXDOD	JR (M)	change to	JR* (M)
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= C: DIDPBXDOD	NIDR (M)	change to	NIDR* (M)
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= C: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= C: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= D: DIDPBXDOD	BA* (M) Trunk Service Detail	add field as	optional
17.0	ELMS6	N	UNE Port Service	TACT= D:	BLOCK (M)	change	BLOCK (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			(PBX Stand Alone Port)	DIDPBXDOD		to	Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= D: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= D: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= N: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= N: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= N: DIDPBXDOD	JR (M)	change to	JR* (M)
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= N: DIDPBXDOD	NIDR (M)	change to	NIDR* (M)
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= N: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= N: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= X: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= X: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= X: DIDPBXDOD	JR (M)	change to	JR* (M)
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= X: DIDPBXDOD	NIDR (M)	change to	NIDR* (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Alone Port)				
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= X: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	TACT= X: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	ACT= C: EU	IMPCON- TEL NO.(M)	remove field from	condition
17.0	ELMS6	N	UNE-P/WLP PBX	ACT= C: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	N	UNE-P/WLP PBX	ACT= C: LSR	LSP AUTH (M)	change to	LSP AUTH* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	ACT= D: LSR	LSP AUTH (M)	change to	LSP AUTH* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	ACT= N: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	N	UNE-P/WLP PBX	ACT= N: LSR	LSP AUTH (M)	change to	LSP AUTH* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	ACT= V: LSR	IMPCON- TEL NO.(M)	change to	required
17.0	ELMS6	N	UNE-P/WLP PBX	ACT= V: LSR	LSP AUTH (M)	change to	LSP AUTH* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= C: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= C: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= C: DIDPBXDOD	JR (M)	change to	JR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= C: DIDPBXDOD	NIDR (M)	change to	NIDR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= C: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= C: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= D: DIDPBXDOD	BA* (M) Trunk Service Detail	add field as	optional
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= D: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= D: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= D: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= G: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= G: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= G: DIDPBXDOD	JR (M)	change to	JR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= G: DIDPBXDOD	NIDR (M)	change to	NIDR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= G: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= N: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= N: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= N: DIDPBXDOD	JR (M)	change to	JR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= N: DIDPBXDOD	NIDR (M)	change to	NIDR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= N: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= N: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
							Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= V: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= V: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= V: DIDPBXDOD	JR (M)	change to	JR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= V: DIDPBXDOD	NIDR (M)	change to	NIDR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= V: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= V: DIDPBXDOD	TNS (M)	change to	TNS (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= W: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= W: DIDPBXDOD	BLOCK (M) Trunk Service Detail	add field as	optional
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= W: DIDPBXDOD	TNS (M)	change to	TNS (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= X: DIDPBXDOD	BA (M)	change to	BA* (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= X: DIDPBXDOD	BLOCK (M)	change to	BLOCK (M) Trunk Service Detail
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= X: DIDPBXDOD	JR (M)	change to	JR* (M)
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= X: DIDPBXDOD	NIDR (M)	change to	NIDR* (M)

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= X: DIDPBXDOD	TC PER (M)	change to	condition
17.0	ELMS6	N	UNE-P/WLP PBX	TACT= X: DIDPBXDOD	TNS (M)	change to	TNS (M)Trunk Service Detail
17.0	ELMS6	P	BellSouth® Centrex®	ACT= C: EU	TCID (M)	add field as	condition
17.0	ELMS6	P	BellSouth® Centrex®	ACT= L: EU	TC NAME (M)	add field as	condition
17.0	ELMS6	P	BellSouth® Centrex®	ACT= L: EU	TCID (M)	add field as	condition
17.0	ELMS6	P	BellSouth® Centrex®	ACT= T: EU	TC PER (M)	add field as	condition
17.0	ELMS6	P	BellSouth® Centrex®	ACT= T: EU	TCID (M)	add field as	condition
17.0	ELMS6	P	BellSouth® Centrex®	ACT= V: EU	FB- BILLCON (M)	add field as	condition
17.0	ELMS6	P	BellSouth® Centrex®	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	P	BellSouth® Centrex®	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	P	BellSouth® Centrex®	ACT= V: EU	FB- SBILLNM	add field as	condition
17.0	ELMS6	P	BellSouth® Centrex®	ACT= W: EU	FB- BILLCON (M)	add field as	condition
17.0	ELMS6	P	ESSX®	ACT= C: EU	TCID (M)	add field as	condition
17.0	ELMS6	P	ESSX®	ACT= C: LSR	IMPCON- TEL NO.(M)	remove field from	condition
17.0	ELMS6	P	ESSX®	ACT= L: EU	TC NAME (M)	add field as	condition
17.0	ELMS6	P	ESSX®	ACT= L: EU	TC TO PRI (M)	add field as	condition
17.0	ELMS6	P	ESSX®	ACT= L: EU	TCID (M)	add field as	condition
17.0	ELMS6	P	ESSX®	ACT= T: EU	TC PER (M)	add field as	condition
17.0	ELMS6	P	ESSX®	ACT= T: EU	TCID (M)	add field as	condition

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	P	ESSX®	ACT= V: EU	FB-BILLCON (M)	add field as	condition
17.0	ELMS6	P	ESSX®	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	P	ESSX®	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	P	ESSX®	ACT= V: EU	FB-SBILLNM (M)	add field as	condition
17.0	ELMS6	P	ESSX®	ACT= W: EU	FB-BILLCON (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= C: EU	TCID (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= D: LSR	ALT-IMP CON-TEL NO. (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= L: EU	TC NAME (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= L: EU	TC TO PRI (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= L: EU	TCID (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= T: EU	TC PER (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= T: EU	TCID (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= V: EU	FB-BILLCON (M)	add field as	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= V: EU	FBI (M)	change to	condition
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= V: EU	FBI* (M)	change to	FBI (M)
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= W: EU	FB-BILLCON (M)	add field as	condition

ELMS6

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
17.0	ELMS6	A	Analog Non-Designed Loop	ACT=D: EU	SASN	change to	SASN*
17.0	ELMS6	A	Analog Non-Designed Loop	ACT=N: EU	STATE	change to	required
17.0	ELMS6	A	Analog Non-Designed Loop	ACT=N: EU	ZIP	change to	required
17.0	ELMS6	A	Analog Non-Designed Loop	ACT=T: EU	STATE	change to	required
17.0	ELMS6	A	Analog Non-Designed Loop	ACT=T: EU	ZIP	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT=D: EU	SASN	change to	SASN*
17.0	ELMS6	A	Analog Designed Loop	ACT=N: EU	STATE	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT=N: EU	ZIP	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT=T: EU	STATE	change to	required
17.0	ELMS6	A	Analog Designed Loop	ACT=T: EU	ZIP	change to	required
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT=C: EU	LD1	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT=C: EU	LD2	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT=C: EU	LD3	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT=C: EU	LV1	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT=C: EU	LV2	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT=C: EU	LV3	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS0)	ACT=C: EU	SASN	change to	SASN*
17.0	ELMS6	A	Digital Data Designed Loop	ACT=D: EU	SASN	change to	SASN*

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			(DS0)				
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT=D: EU	SASN	change to	SASN*
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT=V: EU	LD1	change to	conditional
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT=V: EU	LV1	change to	conditional
17.0	ELMS6	A	Digital Designed Loop (Basic Rate ISDN)	ACT=V: EU	SASN	change to	SASN*
17.0	ELMS6	A	EELs	ACT=C: EU	SASS	add field as	conditional
17.0	ELMS6	A	EELs	ACT=T: EU	LD2	change to	conditional
17.0	ELMS6	A	EELs	ACT=T: EU	LV2	change to	conditional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT=D: EU	CITY	add field as	conditional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT=D: EU	LD1	add field as	conditional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT=D: EU	LD2	add field as	conditional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT=D: EU	LD3	add field as	conditional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT=D: EU	LV1	add field as	conditional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT=D: EU	LV2	add field as	conditional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT=D: EU	LV3	add field as	conditional
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT=D: EU	SASN	change to	SASN*

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= N: EU	STATE	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= N: EU	ZIP	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= T: EU	STATE	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= T: EU	ZIP	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= V: EU	STATE	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Designed (UCL)	ACT= V: EU	ZIP	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= D: EU	SASN	change to	SASN*
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= N: EU	STATE	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= N: EU	ZIP	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= T: EU	STATE	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= T: EU	ZIP	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT= V: EU	STATE	change to	required
17.0	ELMS6	A	Unbundled Copper	ACT=	ZIP	change to	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Loop – Non-Designed (UCL-ND)	V: EU			
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT=W: EU	STATE (M)	change to	required
17.0	ELMS6	A	Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT=W: EU	ZIP (M)	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT=D: EU	SASN	change to	SASN*
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT=N: EU	STATE	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT=N: EU	ZIP	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT=T: EU	STATE	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT=T: EU	ZIP	change to	required
17.0	ELMS6	A	Universal Digital Channel (UDC)	ACT=W: EU	CITY (M)	change to	conditional
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	CITY	change to	required
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	LD1	add field as	conditional
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	LD2	add field as	conditional
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	LD3	add field as	conditional
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	LV1	add field as	conditional
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	LV2	add field as	conditional
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	LV3	add field as	conditional
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	STATE	change to	required
17.0	ELMS6	A	xDSL Loops	ACT=D: EU	ZIP	change to	required
17.0	ELMS6	A	xDSL Loops	ACT=N: EU	STATE	change to	required

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
17.0	ELMS6	A	xDSL Loops	ACT= N: EU	ZIP	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= T: EU	STATE	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= T: EU	ZIP	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= V: EU	STATE	change to	required
17.0	ELMS6	A	xDSL Loops	ACT= V: EU	ZIP	change to	required
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= D: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= N: EU	STATE (M)	change to	required
17.0	ELMS6	A	Unbundled Sub-Loops	ACT= N: EU	ZIP (M)	change to	required
17.0	ELMS6	A	Ordinarily Combined UNEs (OCU)	ACT= C: EU	SASS (M)	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: EU	LD1	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: EU	LD2	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: EU	LD3	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: EU	LV1	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: EU	LV2	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: EU	LV3	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= C: EU	SASN	change to	SASN*
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT= D: EU	LD1	add field as	conditional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT=D: EU	LD2	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT=D: EU	LD3	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT=D: EU	LV1	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT=D: EU	LV2	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT=D: EU	LV3	add field as	conditional
17.0	ELMS6	A	Digital Data Designed Loop (DS1)	ACT=D: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	ACT=D: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	ACT=N: EU	STATE (M)	change to	required
17.0	ELMS6	A	Unbundled Sub-Loop Feeder	ACT=N: EU	ZIP (M)	change to	required
17.0	ELMS6	B	INP, Designed Analog Loop	ACT=V: EU	STATE (M)	change to	required
17.0	ELMS6	B	INP, Designed Analog Loop	ACT=V: EU	ZIP (M)	change to	required
17.0	ELMS6	B	INP, xDSL Loops	ACT=V: EU	STATE (M)	change to	required
17.0	ELMS6	B	INP, xDSL Loops	ACT=V: EU	ZIP (M)	change to	required
17.0	ELMS6	B	INP, Digital Designed Basic Rate ISDN	ACT=V: EU	STATE (M)	change to	required
17.0	ELMS6	B	INP, Digital Designed Basic Rate ISDN	ACT=V: EU	ZIP (M)	change to	required
17.0	ELMS6	B	INP, Digital Data Designed Loop (DS0)	ACT=V: EU	STATE (M)	change to	required
17.0	ELMS6	B	INP, Digital Data Designed Loop	ACT=V: EU	ZIP (M)	change to	required

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
			(DS0)				
17.0	ELMS6	B	INP, Unbundled Copper Loop – Non-Designed (UCL-ND)	ACT = V: EU	ZIP (M)	remove field from	conditional
17.0	ELMS6	E	Resale, non-complex	ACT = B: EU	LD1	add field as	conditional
17.0	ELMS6	E	Resale, non-complex	ACT = B: EU	LD2	add field as	conditional
17.0	ELMS6	E	Resale, non-complex	ACT = B: EU	LD3	add field as	conditional
17.0	ELMS6	E	Resale, non-complex	ACT = B: EU	LV1	add field as	conditional
17.0	ELMS6	E	Resale, non-complex	ACT = B: EU	LV2	add field as	conditional
17.0	ELMS6	E	Resale, non-complex	ACT = B: EU	LV3	add field as	conditional
17.0	ELMS6	E	Resale, non-complex	ACT = B: EU	SASN	change to	SASN*
17.0	ELMS6	E	Resale, non-complex	ACT = D: EU	SASN	change to	SASN*
17.0	ELMS6	E	Resale, non-complex	ACT = L: EU	SASN	change to	SASN*
17.0	ELMS6	E	Resale, non-complex	ACT = S: EU	SASN (E)	change to	SASN*
17.0	ELMS6	E	Resale, non-complex	ACT = W: EU	SASN	change to	SASN*
17.0	ELMS6	E	Resale, non-complex	ACT = Y: EU	SASN	change to	SASN*
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT = C: EU	STATE	remove field from	conditional
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT = D: EU	ZIP	remove field from	conditional
17.0	ELMS6	E	Remote Call Forwarding (RCF)	ACT = V: EU	ZIP	remove field from	conditional
17.0	ELMS6	E	ISDN-BRI Resale Service	ACT = D: EU	SASN	change to	SASN*
17.0	ELMS6	E	Coin	ACT = D: EU	SASN	change to	SASN*
17.0	ELMS6	E	Coin	ACT = W: EU	SASN	change to	SASN*
17.0	ELMS6	E	BellSouth® Intergrated	ACT = C: EU	CITY (M)	add field as	conditional

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
			Solutions				
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= C: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	E	BellSouth® Intergrated Solutions	ACT= C: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	E	AccuPulse®	ACT= C: EU	LD1 (M)	add field as	conditional
17.0	ELMS6	E	AccuPulse®	ACT= C: EU	LD2 (M)	add field as	conditional
17.0	ELMS6	E	AccuPulse®	ACT= C: EU	LD3 (M)	add field as	conditional
17.0	ELMS6	E	AccuPulse®	ACT= C: EU	LV1 (M)	add field as	conditional
17.0	ELMS6	E	AccuPulse®	ACT= C: EU	LV2 (M)	add field as	conditional
17.0	ELMS6	E	AccuPulse®	ACT= C: EU	LV3 (M)	add field as	conditional
17.0	ELMS6	E	ATM	ACT= D: EU	CITY (M)	add field as	required
17.0	ELMS6	E	ATM	ACT= D: EU	STATE (M)	add field as	required
17.0	ELMS6	E	ATM	ACT= D: EU	ZIP (M)	add field as	required
17.0	ELMS6	E	ATM	ACT= T: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	Frame Relay	ACT= T: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	MegaLink® Service	ACT = W: EU	SASF (M)	remove field from	optional
17.0	ELMS6	E	MegaLink® Service	ACT= N: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	MegaLink® Service	ACT= T: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	MegaLink® Service	ACT= V: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	MegaLink® Channel Services	ACT= T: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	MegaLink®	ACT=	SANO	change to	conditional

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
			Channel Services	V: EU	(M)		
17.0	ELMS6	E	MegaLink® Channel Services	ACT= W: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	Primary Rate ISDN -PRI	ACT= N: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	Primary Rate ISDN -PRI	ACT= T: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	Primary Rate ISDN -PRI	ACT= V: EU	SANO (M)	change to	conditional
17.0	ELMS6	E	TFD	ACT = N: EU	AAI (M)	remove field from	optional
17.0	ELMS6	E	TFD	ACT = V: EU	AAI (M)	remove field from	optional
17.0	ELMS6	E	TFD	ACT = W: EU	AAI (M)	remove field from	optional
17.0	ELMS6	E	TFD	ACT= C: EU	AAI (M)	remove field from	optional
17.0	ELMS6	E	TIE Lines	ACT= C: EU	SASS (M)	add field as	conditional
17.0	ELMS6	E	On/Off Premises Extensions	ACT= C: EU	SASS (M)	add field as	conditional
17.0	ELMS6	E	WATS	ACT = N: EU	AAI (M)	remove field from	optional
17.0	ELMS6	E	WATS	ACT = V: EU	AAI (M)	remove field from	optional
17.0	ELMS6	E	WATS	ACT = W: EU	AAI (M)	remove field from	optional
17.0	ELMS6	E	WATS	ACT= C: EU	AAI (M)	remove field from	optional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = N: EU	LD1 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = N: EU	LD2 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = N: EU	LD3 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = N: EU	LV1 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = N: EU	LV2 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = N: EU	LV3 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = W: EU	LD1 (M)	change to	conditional

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = W: EU	LD2 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = W: EU	LD3 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = W: EU	LV1 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = W: EU	LV2 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT = W: EU	LV3 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= C: EU	SASD (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= C: EU	SASN (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	LD1 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	LD2 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	LD3 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	LV1 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	LV2 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	LV3 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= D: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	LD1 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	LD2 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	LD3 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	LV1 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	LV2 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= T: EU	LV3 (M)	add field as	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= V: EU	LD1 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN /	ACT=	LD2 (M)	change to	conditional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			CSA / ANI	V: EU			
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= V: EU	LD3 (M)	change to	conditional
17.0	ELMS6	E	Uniserv UAN / CSA / ANI	ACT= W: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= C: EU	CITY (M)	add field as	conditional
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= C: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= C: EU	SASS (M)	add field as	conditional
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= C: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= N: EU	CITY (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= N: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= N: EU	STATE (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= N: EU	ZIP (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= T: EU	CITY (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= T: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= T: EU	STATE (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises	ACT= T: EU	ZIP (M)	add field as	required

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
			Extensions/DPA				
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= V: EU	CITY (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= V: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= V: EU	STATE (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= V: EU	ZIP (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= W: EU	CITY (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= W: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= W: EU	STATE (M)	add field as	required
17.0	ELMS6	E	Complex PBX On/Off Premises Extensions/DPA	ACT= W: EU	ZIP (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= C: EU	CITY (M)	add field as	conditional
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= C: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= C: EU	SASS (M)	add field as	conditional
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= C: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= N: EU	CITY (M)	add field as	required

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= N: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= N: EU	STATE (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= N: EU	ZIP (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= T: EU	CITY (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= T: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= T: EU	STATE (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= T: EU	ZIP (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= V: EU	CITY (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= V: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= V: EU	STATE (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= V: EU	ZIP (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	CITY (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	NAME (M)	add field as	required
17.0	ELMS6	E	Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	STATE (M)	add field as	required
17.0	ELMS6	E	Non-Complex	ACT=	ZIP (M)	add field	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			On/Off Premises Extensions/DPA	W: EU		as	
17.0	ELMS6	F	Port Service	ACT = S: EU	LV1	add field as	conditional
17.0	ELMS6	F	Port Service	ACT = S: EU	LV2	add field as	conditional
17.0	ELMS6	F	Port Service	ACT = S: EU	LV3	add field as	conditional
17.0	ELMS6	J	Directory Listing	ACT = N: EU	LV1	add field as	conditional
17.0	ELMS6	J	Directory Listing	ACT = N: EU	LV2	add field as	conditional
17.0	ELMS6	J	Directory Listing	ACT = N: EU	LV3	add field as	conditional
17.0	ELMS6	J	Directory Listing	ACT = R: EU	LV1	add field as	conditional
17.0	ELMS6	J	Directory Listing	ACT = R: EU	LV2	add field as	conditional
17.0	ELMS6	J	Directory Listing	ACT = R: EU	LV3	add field as	conditional
17.0	ELMS6	J	Directory Listing	ACT= N: EU	LD1	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= N: EU	LD2	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= N: EU	LD3	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= N: EU	SASD	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= N: EU	SASF	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= N: EU	SASS	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= N: EU	SATH	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= R: EU	SASS	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= R: EU	LD1	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= R: EU	LD2	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= R: EU	LD3	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT=	SASD	change to	conditional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
				R: EU			
17.0	ELMS6	J	Directory Listing	ACT= R: EU	SASF	change to	conditional
17.0	ELMS6	J	Directory Listing	ACT= R: EU	SATH	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= B: EU	SASN	change to	SASN*
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= D: EU	SANO	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= D: EU	SANO*	change to	SANO
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= D: EU	SASN	change to	SASN*
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= L: EU	SASN	change to	SASN*
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= S: EU	SASN	change to	SASN*
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= W: EU	SASN	change to	SASN*
17.0	ELMS6	M	UNE-P/WLP Bus/Res (Switched Combo Bus/Res)	ACT= Y: EU	SASN	change to	SASN*
17.0	ELMS6	M	UNE-P/WLP Remote Call Forwarding (RCF Switched Combo)	ACT= V: EU	SASN	remove field from	optional
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= D: EU	SASN	change to	SASN*
17.0	ELMS6	M	UNE-P/WLP Coin	ACT= W: EU	SASN	change to	SASN*
17.0	ELMS6	M	UNE-P/WLP 4-wire ISDN PRI Combination	ACT= N: EU	SANO (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP 4-wire ISDN PRI Combination	ACT= V: EU	SANO (M)	change to	conditional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= C: EU	CITY (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= C: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= C: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= D: EU	CITY (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= D: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= D: EU	STATE (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= D: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= V: EU	CITY (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= V: EU	STATE (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP 2-wire ISDN-BRI UNE Combo	ACT= V: EU	ZIP (M)	remove field from	required
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= N: EU	SANO (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP DDITS - DS1	ACT= V: EU	SANO (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP DDITS - Trunk Service	ACT= C: EU	SASS (M)	remove field from	conditional
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization	ACT= N: EU	SANO (M)	change to	conditional

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
			with Port (DS1 Service)				
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (DS1 Service)	ACT= V: EU	SANO (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= C: EU	CITY (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= C: EU	SASN (M)	change to	SASN* (M)
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP 4-wire DS1 Loop with Channelization with Port (Trunk Service)	ACT= C: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	LD1 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	LD2 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	LD3 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	LV1 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	LV2 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	LV3 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	SASD (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	SASF (M)	change to	conditional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	SASS (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= N: EU	SATH (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: EU	LD1 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: EU	LD2 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: EU	LD3 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: EU	LV1 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: EU	LV2 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Centrex	ACT= V: EU	LV3 (M)	change to	conditional
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises Extensions/DPA	ACT= C: EU	CITY (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises Extensions/DPA	ACT= C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises Extensions/DPA	ACT= C: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises Extensions/DPA	ACT= N: EU	CITY (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises Extensions/DPA	ACT= N: EU	STATE (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises Extensions/DPA	ACT= N: EU	ZIP (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises	ACT= V: EU	CITY (M)	add field as	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			Extensions/DPA				
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises Extensions/DPA	ACT= V: EU	STATE (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Complex PBX On/Off Premises Extensions/DPA	ACT= V: EU	ZIP (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off Premises Extensions/DPA	ACT= C: EU	CITY (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off Premises Extensions/DPA	ACT= C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off Premises Extensions/DPA	ACT= C: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off Premises Extensions/DPA	ACT= N: EU	CITY (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off Premises Extensions/DPA	ACT= N: EU	STATE (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off Premises Extensions/DPA	ACT= N: EU	ZIP (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off Premises Extensions/DPA	ACT= T: EU	CITY (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off Premises Extensions/DPA	ACT= T: EU	STATE (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non- Complex On/Off	ACT= T: EU	ZIP (M)	add field as	required

Rel	Map	Reqty	Product	Type	Field from	Action	Field to
			Premises Extensions/DPA				
17.0	ELMS6	M	UNE-P/WLP Non-Complex On/Off Premises Extensions/DPA	ACT= V: EU	CITY (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non-Complex On/Off Premises Extensions/DPA	ACT= V: EU	STATE (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non-Complex On/Off Premises Extensions/DPA	ACT= V: EU	ZIP (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	CITY (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	STATE (M)	add field as	required
17.0	ELMS6	M	UNE-P/WLP Non-Complex On/Off Premises Extensions/DPA	ACT= W: EU	ZIP (M)	add field as	required
17.0	ELMS6	N	DID Resale Service	ACT= D: EU	CITY (M)	add field as	conditional
17.0	ELMS6	N	DID Resale Service	ACT= D: EU	STATE (M)	add field as	conditional
17.0	ELMS6	N	DID Resale Service	ACT= D: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	N	DID Resale Service	ACT= V: EU	CITY	change to	required
17.0	ELMS6	N	DID Resale Service	ACT= W: EU	CITY	change to	required
17.0	ELMS6	N	UNE-P/WLP 2-wire DID	ACT= D: EU	CITY (M)	add field as	conditional
17.0	ELMS6	N	UNE-P/WLP 2-wire DID	ACT= D: EU	STATE (M)	add field as	conditional
17.0	ELMS6	N	UNE-P/WLP 2-wire DID	ACT= D: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	N	UNE-P/WLP 2-wire	ACT=	CITY	change to	required

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			DID	V: EU			
17.0	ELMS6	N	PBX Resale Service	ACT=D: EU	CITY (M)	add field as	conditional
17.0	ELMS6	N	PBX Resale Service	ACT=D: EU	STATE (M)	add field as	conditional
17.0	ELMS6	N	PBX Resale Service	ACT=D: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	N	PBX Resale Service	ACT=V: EU	CITY	change to	required
17.0	ELMS6	N	PBX Resale Service	ACT=W: EU	CITY	change to	required
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT=D: EU	CITY (M)	add field as	conditional
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT=D: EU	STATE (M)	add field as	conditional
17.0	ELMS6	N	UNE Port Service (PBX Stand Alone Port)	ACT=D: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	N	UNE-P/WLP PBX	ACT=D: EU	CITY (M)	add field as	conditional
17.0	ELMS6	N	UNE-P/WLP PBX	ACT=D: EU	STATE (M)	add field as	conditional
17.0	ELMS6	N	UNE-P/WLP PBX	ACT=D: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	N	UNE-P/WLP PBX	ACT=V: EU	CITY (M)	change to	required
17.0	ELMS6	P	ESSX®	ACT=C: EU	AAI (M)	add field as	conditional
17.0	ELMS6	P	ESSX®	ACT=C: EU	CITY (M)	add field as	conditional
17.0	ELMS6	P	ESSX®	ACT=C: EU	SATH (M)	add field as	conditional
17.0	ELMS6	P	ESSX®	ACT=C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	P	ESSX®	ACT=C: EU	ZIP (M)	add field as	conditional
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT=C: EU	AAI (M)	add field as	conditional
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT=C: EU	CITY (M)	add field as	conditional
17.0	ELMS6	P	MultiServ® /	ACT=	SASD	add field	conditional

Rel	Map	Reqtyp	Product	Type	Field from	Action	Field to
			MultiServ PLUS®	C: EU	(M)	as	
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= C: EU	SASD (M)	add field as	conditional
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= C: EU	SASS (M)	add field as	conditional
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= C: EU	SATH (M)	add field as	conditional
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= C: EU	STATE (M)	add field as	conditional
17.0	ELMS6	P	MultiServ® / MultiServ PLUS®	ACT= C: EU	ZIP (M)	add field as	conditional

ELMS6

FB-FLOOR – Final Bill Floor

EU Form/Screen

(LSOG6 / ELMS6 map)

Definition:

Identifies the floor of the billing address associated with the billing name.

Definition Notes:

None

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 10 alpha/numeric characters

Examples:

32

Conditional Usage Notes:

Electronic:

Note 1: Prohibited when the MI field is A or B.

Note 2: Optional when the FBI field is Y, otherwise prohibited.

Manual:

Note 3: Optional when the FBI field is D, otherwise prohibited

Business Rules

None

***** End of definition for FB-FLOOR / EU form screen *****

FB-ROOM – Final Bill Room**EU Form/Screen**

(LSOG6 / ELMS6 map)

Definition:

Identifies the room for the billing address associated with the billing name.

Definition Notes:

None

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 10 alpha/numeric characters

Examples:

1K151A

Conditional Usage Notes:

Electronic:

Note 1: Prohibited when the MI field is A or B.

Note 2: Optional when the FBI field is Y, otherwise prohibited.**Manual:****Note 3: Optional when the FBI field is D, otherwise prohibited****Business Rules**

None

***** End of definition for FB-ROOM / EU form screen *****

FB-SBILLNM – Final Billing Secondary Name**EU Form/Screen**

(LSOG6 / ELMS6 map)

Definition:

Identifies the name of a department or group within the designated BILLNM entry.

Definition Notes:

None

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 25 alpha/numeric characters

Examples:

ACCOUNTS RECEIVABLE

Conditional Usage Notes:

Note 1: Prohibited when the MI field is A or B.

Note 2: Optional when the FBI field is Y, otherwise prohibited.**Manual:****Note 3: Optional when the FBI field is D, otherwise prohibited****Business Rules**

None

****** End of definition for FB-SBILLNM / EU form screen ******

CCP 2039 Attachment Listed Below

ELMS6

Unbundled Copper Loop - Non-Designed (UCL-ND)

Product Listing

Unbundled Copper Loop - Non-Designed (UCL-ND)

Tables to request Unbundled Copper Loop - Non-Designed (UCL-ND) service are located in this section.

Ordering Forms/Screens

The following chart illustrates the required, conditional and optional forms/screens for ordering this service. Detailed information will follow to assist you in filling out each of these forms/screens.

Forms/Screens Unbundled Copper Loop - Non-Designed (UCL-ND)												
SI	LSR	Hunting	EU	DL	RS	DRS	PS	NP	LS	LSNP	RPL	Proprietary
O	R		R						R			
R = Required C = Conditional O = Optional												

Completing the DL Form/Screen

If directory listings are required, refer to **REQTYP J** for more information on completing the DL form/screen.

Completing the LSR and EU Forms/Screens

Account level activities (ACT) apply to the entire account. A complete list of ACTs and their definition can be found in the Data Dictionary entry for ACT.

The following chart shows all of the valid account level activities for this service.

Valid Account Level Activities Unbundled Copper Loop - Non-Designed (UCL-ND)										
N	C	D	T	R	V	S	B	W	L	Y
X	X	X	X	-	X	-	-	X	-	-

“X” denotes valid account level activities. A dash (-) indicates a non-valid account level activity.

The Required, Conditional and Optional (R/C/O) fields on the LSR and EU forms/screens will be given for every valid ACT code in the **ACT Tables** section.

Completing the LS Form/Screen

The Loop Service (LS) form/screen may be required or invalid depending on the account level activity. Each account level activity has valid Line Level Activities (LNAs). These LNAs determine how, or if, the LS form/screen should be populated. A complete list of LNAs and their definition can be found in the Data Dictionary entry for LNA.

The following chart gives the valid LNAs for each account level activity (ACT) and the associated LS form/screen usage for this service.

If ACT is:	Then LNA is:	And LS form is:
N	N	Required
C	N, C or D	Required
D	D N/A	Required Prohibited
T	N or T	Required
V	N, D, or V	Required
W	W	Required

The Required, Conditional and Optional (R/C/O) fields for the Loop Service (LS) form/screen are listed according to the Line Level Activity (LNA) in the **LNA Tables** Section.

CCP 2040 Attachment Listed Below

16.0 and 17.0
ELMS6 only

TAG AND EDI Data Dictionaries Additions

Add these 2 new fields to the Data Dictionary

EATN

Description name:	Existing Account Telephone Number
Definition:	Identifies the existing account telephone number.
Characteristics:	10 N
Condition:	Required for REQTYP MB, ACT T.

AND

LEATN

Description name:	Line Existing Account Telephone Number
Definition:	Identifies the existing account telephone number for the line.
Characteristics:	10 N

ELMS6***Estimated Service Date Query***

This query will provide information to the Estimated Service Date Response in order to return the best available service date possible.

Estimated Service Date Query					
BST FIELD		FIELD DESCRIPTIO N	Business Rule	R/C /O	Length
LSOG 4	LSOG 6				

Estimated Service Date Query					
BST FIELD		FIELD DESCRIPTIO N	Business Rule	R/C /O	Length
LSOG 4	LSOG 6				
TXNUM	TXNUM	Transaction Number	Identifies the customer provided tracking number to link the inquiry with the response.	R	Up to 16 A/N
REQTYP	REQTYP	Type of Request	Identifies the type of service being requested and the status of the request.	R	2 A
ACT	ACT	Type of Activity	Identifies the activity involved in this service request. Conditional rule: Required when REQ TYP is not JB	C	1 A
RSQTY	RSQTY	Resale Quantity	Identifies the quantity of Resale Services (e.g., lines circuits, trunks, etc.) involved in this service request.	O	3 N Range: 000 - 999
CHC	CHC	Coordinated Hot Cut	Indicates the customer is requesting new seamless cutover activity.	O	1 A Y = Yes N = No
EATN	EATN	Existing Account Telephone Number	Indicates the existing account telephone number. Required when REQ TYP MB, ACT T.	C	10 N
LNECLSSVC	LNECLSSVC	Line Level Class of Service	Identifies the type of service requested for this service location.	O	3 or 5 A/N
LEATN	LEATN	Line Existing Account Telephone Number	Indicates the existing account telephone number for the line.	O	10 N
		End Line Information			

Estimated Service Date Query					
BST FIELD		FIELD DESCRIPTIO N	Business Rule	R/C /O	Length
LSOG 4	LSOG 6				
		Order Code Occurs (0,N)			
FA	FA	Feature Activity	Identifies the activity type for the feature	O	1 A

ELMS6

Estimated Service Date Query

This query will provide information to the Estimated Service Date Response in order to return the best available service date possible.

Estimated Service Date Query				
BST FIELD		Field Description	R/C/O	Data Characteristics
LSOG 4	LSOG 6			
INQ-NUM	TXNUM	Transaction Number	R	Up to 16 A/N
INQACT	TXACT	Transaction Activity	R	1 A
TXTYP	TXTYP	Transaction Type	R	1 A
TXCLS	TXCLS	Transaction Classification	C	1 A/N
DDD	DDD	Desired Due Date	O	8 N
ATN	ATN	Account Telephone Number	O	10 N
LQTY	LQTY	Loop Quantity	C	5 N
NPQTY	NPQTY	Number Portability Quantity	C	5 N
RSQTY	RSQTY	Resale Quantity	O	3 N
CHC	CHC	Coordinated Hot Cut	O	1 A

Estimated Service Date Query				
BST FIELD		Field Description	R/C/O	Data Characteristics
LSOG 4	LSOG 6			
LEATN	LEATN	Line Existing Account Telephone Number	O	10 N
HOUSE-NUM	SANO	Service Address Street Number	R	Up to 8 A/N
HOUSE-NUM-SUFFIX	SASF	Service Address Number Suffix	O	Up to 4 A/N

LNECLSSVC	LNECLSSV	Line Level Class of Service	O	3 or 5 A/N
EATN	EATN	Existing Account Telephone Number Required when REQ TYP is MB, ACT T.	C	10 N

CCP 2043 Attachment Listed Below**TCIF 9 and ELMS 6**

Removing this section and creating a new section in the General Local Service Ordering chapter.

~~# Local Resale Assumption Agreements~~

~~For 'Switch As Is' and 'Switch With Change' requests, if the End User has an existing contract arrangement with BellSouth®, then the CLEC must decide whether to assume or decline that existing contract.~~

~~To make this decision:~~

- ~~1. The CLEC will review the Customer Service Record (CSR) and determine if any of the Universal Service Order Codes (USOCs) indicate that the services are provided under a contractual arrangement. The CSR will indicate the date that the contract was signed and the total number of months in the contract period.~~
- ~~2. If the CLEC does not plan to assume the contract, a Remarks entry should be included on the LSR stating: "CLEC not assuming contract; bill termination charges to end user." The LSR should be issued to the LCSC as Switch With Change, due to changes that must be made on the customer's record to remove the contract information. The Firm Order Confirmation (FOC) will contain the amount due as termination charges. To determine the amount of the termination charges due prior to receiving the FOC, the CLECs may calculate the total termination charge as specified in the tariff for that particular service based on the months remaining multiplied by the total monthly charges of the USOCs under contract. If the CLEC disagrees with the amount shown on the FOC, normal escalation procedures will be followed.~~
- ~~3. If the CLEC does want to assume the contract, a copy of the Assumption Agreement template should be downloaded from the BellSouth® Web site, completed and signed by the CLEC. Attachment A should include a list of all of the USOCs included in the original agreement, as indicated on the CSR. The CLEC must send the signed Assumption Agreement, along with the Switch As Is LSR, to the CRSG. The CRSG will verify the USOCs, sign the agreement, return a copy to the CLEC, and forward the order to the LCSC.~~

TCIF9 & ELMS6

New section in the General Local Service Ordering chapter

TITLE: Resale Contract Assumption Agreements

DESCRIPTION:



Attachment
SN91084236

Contract Service Arrangements (CSA), Term Agreements (TA) and Special Assemblies are special arrangements used to offer special pricing or discounts on BellSouth® products and services.

CSAs and TAs are used to provide special pricing or discounts for tariffed service; while Special Assemblies (SA) are used for non-tariffed offerings.

When migrating from BST to Resale, or when migrating from Resale to Resale the new LSP may exercise the option to assume the CSA, TA and SA when one is present on the end users account at the time of migration.

When the Customer Service Record (CSR) has a contractual agreement indicator on the account, the CLEC must decide at the time of migration whether to assume the existing contractual arrangement, or decline. If the CLEC opts not to assume the contractual agreement, termination charges if applicable will be billed to the billing party of record if applicable.

A contract service arrangement/Special Assembly when present is formatted in the Bill section of the CSR as well as in the S&E section, below is an example of how the information is formatted on the CSR:

Example:

---**Bill**

CN 950234, MM-DD-YY

---**S&E**

USOC/CN 950234

Where 95=Year (2 numerics)

Where 0234=Contract Number (4 numerics)

Where MM-DD-YY=Expiration date

Note: Only the USOCS listed in the contract service arrangement will have the CN indicator floated next to them. Special Assembly USOCS typically begin with a W (example: WV5U)

Term agreements like CSA and Special Assembly agreements are also indicated in the billing and S&E sections of the CSR.

---**BILL**

TA 36, MM-DD-YY

Where 36=The number of months included in the term agreement payment plan

Where MM-DD-YY=The **beginning** or start date of the contract

---**S&E**

USOC/SPP VT1/TA 36

Where SPP=Special Pricing Plan
Where VT1=Variable term entry
Where TA 36=Number of months in payment plan

To determine if a contractual agreement exist the CLEC should obtain copies of the existing CSR and check for the following information:

IF	Then
The FID CN appears in the Bill section of the CSR EXAMPLE: ---BILL CN XXXXXX, MM-DD-YY	The customer should verify the expiration date to determine if the contract arrangement is still in effect.
The expiration date is still in effect	Contact the CRSG (Complex Resale Service Group) to determine what options are available.
The FID TA appears in the Bill section of the CSR EXAMPLE: ---BILL TA, XX, MM-DD-YY	The customer should verify the expiration date to determine if the contract arrangement is still in effect.
The expiration date is still in effect	Contact the CRSG (Complex Resale Service Group) to determine what options are available.
If the CN or TA is expired.	The LSR request may be submitted to the appropriate BellSouth order processing group based on product ordering specifications (ex:CSRG/LCSC).

SERVICE RESTRICTIONS:

Contract Service arrangements do not apply to UNE/UNE-P or WLP services.

LSR RESTRICTIONS:

- If the migrating account has a contractual agreement that is still in effect and the CLEC does not wish to assume responsibility for the contract the LSR must be submitted as ACT=V
- All assumptions/terminations of contractual agreements must be processed by the CRSG (Note: once the account has been transferred to or orders issued to transfer to the new LSP, the new LSP may process subsequent order activities via the normal process).
- When termination charges are applicable, the termination charges will be returned on the FOC.

TARIFF REFERENCE:

N/A

USOC & FID REFERENCES:

N/A



Attachment
SN91084236

SITUATIONS/EXHIBITS:

N/A

RELEATED TOPICS/INFORMATION:

None

CCP 2045 Attachment Listed Below

TCIF9 & ELMS6

Product	ACT	LSRPage	Field	Status	Change Status To
ISDN-BRI Resale Service	D	LSR	DDDO	C	O
ISDN-BRI Resale Service	T	LSR	DDDO	C	R
Coin	V	LSR	DDDO	C	O
SMARTRing® Service	D	LSR	DDDO	C	O
LIGHTGATE® Services	D	LSR	DDDO	C	O
Private Line	D	LSR	DDDO	C	O
Synchronet	D	LSR	DDDO	C	O
UNE-P/WLP 2-wire ISDN-BRI UNE Combo	D	LSR	DDDO	C	O
DID Resale Service	T	LSR	DDDO	R	Delete
DID Resale Service	V	EU	DDDO	C	Delete
DID Resale Service	V	LSR	DDDO	O	Delete
UNE-P/WLP 2-wire DID	V	LSR	DDDO	O	Delete
PBX Resale Service	T	LSR	DDDO	R	O
PBX Resale Service	V	LSR	DDDO	O	Delete
UNE-P/WLP PBX	V	LSR	DDDO	O	Delete

TCIF9 & ELMS6

Product	ACT	LSR Page	Field	Status	New Status
ISDN-BRI Resale Service	T	LSR	DDDO	C	R
Coin	V	LSR	DDDO	C	O
Private Lines	D	LSR	DDDO	C	O
UNE-P/WLP 2-wire ISDN-BRI UNE Combo	D	LSR	DDDO	C	O
DID Resale Service	T	LSR	DDDO	R	Delete

ELMS6**DDDO – Desired Due Date Out****LSR Form/Screen**

(LSOG6 / ELMS6 map)

Definition:

Identifies the customer's desired due date for the suspension or disconnection of service.

Definition Notes:

NOTE 1: This field is used to identify the date the service is to be disconnected at the old location when the end user's service is moving to a new location.

Valid Entries:

Manual:

Entry	Description
1 and 2	Two Digit Month (01-12)
3	Always a Hyphen
4 and 5	Two Digit Day (01-31)
6	Always a Hyphen
7 and 8	Two Digit Century (20-99)
9 and 10	Two Digit Year (00-99)

Electronic:

Entry	Description
Two Digit Century (CC)	20-99
Two Digit Year (YY)	00-99
Two Digit Month (MM)	01-12
Two Digit Day (DD)	01-31

Valid Entry Notes:

None

Data Characteristics:

Manual: 10 alpha/numeric characters

Electronic: 8 alpha/numeric characters

Examples:

Manual: 03-22-2001

Electronic: 20010322

Conditional Usage Notes:~~Manual:~~~~Note 1: This field is required when the ACT field is T, and the 2nd character of the TOS field is H.~~**Business Rules**

Rule 1: Interval between the DDD and DDDO fields must be 30 calendar days or less (Excluding REQTYP A).

~~Rule 2: The DDDO is populated on requests to move service. Therefore, population of both the DDD and DDDO field is required.~~



Attachment
SN91084236

- | Rule 3 2: Must be a valid date.
- | Rule 43: When the TOS field is populated with 4CF (Coin), or 4CM (Coin) and the ACT is T for REQTYPs E and M (Non-Complex), the DDD and DDDO fields must match.
- | Rule 54: When the REQTYP is A and the ACT is T, **when populated** the DDDO and DDD must match.

***** End of definition for DDDO / LSR form screen *****

CCP 2046 Attachment Listed Below

ELMS6

Reqtyp	Product	Code Type	Code	LSR Page	Field	Status	Manual	Note	Change Status to
A	Digital Designed Loop (Basic Rate ISDN)	ACT	V	EU	LD1	O			C
A	Digital Designed Loop (Basic Rate ISDN)	ACT	V	EU	LV1	O			C
A	EELs	ACT	T	EU	LD2	O			C
A	EELs	ACT	T	EU	LV2	O			C
E	Uniserv UAN / CSA / ANI	ACT	N	EU	LD1	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	N	EU	LD2	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	N	EU	LD3	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	T	EU	LD1	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	T	EU	LD2	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	T	EU	LD3	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	V	EU	LD1	O	M		C (M)

Reqtyp	Product	Code Type	Code	LSR Page	Field	Status	Manual	Note	Change Status to
E	Uniserv UAN / CSA / ANI	ACT	V	EU	LD2	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	V	EU	LD3	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	W	EU	LD1	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	W	EU	LD2	O	M		C (M)
E	Uniserv UAN / CSA / ANI	ACT	W	EU	LD3	O	M		C (M)
F	Port Service	ACT	S	EU	LD1	O			C
F	Port Service	ACT	S	EU	LD2	O			C
F	Port Service	ACT	S	EU	LD3	O			C
J	Directory Listing	ACT	N	EU	LD1	O			C
J	Directory Listing	ACT	N	EU	LD2	O			C
J	Directory Listing	ACT	N	EU	LD3	O			C
J	Directory Listing	ACT	R	EU	LD1	O			C
J	Directory Listing	ACT	R	EU	LD2	O			C
J	Directory Listing	ACT	R	EU	LD3	O			C
K	Private Line	LNA	C	RPL	LD1	O	M	* (P/S)	C (M)
K	Private Line	LNA	C	RPL	LD2	O	M	* (P/S)	C (M)
K	Private Line	LNA	C	RPL	LD3	O	M	* (P/S)	C (M)
K	Private Line	LNA	N	RPL	LD1	O	M	* (P/S)	C (M)
K	Private	LNA	N	RPL	LD2	O	M	*	C (M)

Reqtyp	Product	Code Type	Code	LSR Page	Field	Status	Manual	Note	Change Status to
	Line							(P/S)	
K	Private Line	LNA	N	RPL	LD3	O	M	* (P/S)	C (M)
K	Private Line	LNA	V	RPL	LD1	O	M	* (P/S)	C (M)
K	Private Line	LNA	V	RPL	LD2	O	M	* (P/S)	C (M)
K	Private Line	LNA	V	RPL	LD3	O	M	* (P/S)	C (M)
K	Private Line	LNA	W	RPL	LD1	O	M	* (P/S)	C (M)
K	Private Line	LNA	W	RPL	LD2	O	M	* (P/S)	C (M)
K	Private Line	LNA	W	RPL	LD3	O	M	* (P/S)	C (M)
K	Synchronet	LNA	C	RPL	LD1	O	M	* (P/S)	C (M)
K	Synchronet	LNA	C	RPL	LD2	O	M	* (P/S)	C (M)
K	Synchronet	LNA	C	RPL	LD3	O	M	* (P/S)	C (M)
K	Synchronet	LNA	N	RPL	LD1	O	M	* (P/S)	C (M)
K	Synchronet	LNA	N	RPL	LD2	O	M	* (P/S)	C (M)
K	Synchronet	LNA	N	RPL	LD3	O	M	* (P/S)	C (M)
K	Synchronet	LNA	V	RPL	LD1	O	M	* (P/S)	C (M)
K	Synchronet	LNA	V	RPL	LD2	O	M	* (P/S)	C (M)
K	Synchronet	LNA	V	RPL	LD3	O	M	* (P/S)	C (M)
K	Synchronet	LNA	W	RPL	LD1	O	M	* (P/S)	C (M)
K	Synchronet	LNA	W	RPL	LD2	O	M	* (P/S)	C (M)
K	Synchronet	LNA	W	RPL	LD3	O	M	* (P/S)	C (M)
M	UNE-P/WLP Centrex	ACT	N	EU	LD1	O	M		C (M)

Reqtyp	Product	Code Type	Code	LSR Page	Field	Status	Manual	Note	Change Status to
M	UNE-P/WLP Centrex	ACT	N	EU	LD2	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	N	EU	LD3	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	N	EU	LV1	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	N	EU	LV2	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	N	EU	LV3	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	V	EU	LD1	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	V	EU	LD2	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	V	EU	LD3	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	V	EU	LV1	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	V	EU	LV2	O	M		C (M)
M	UNE-P/WLP Centrex	ACT	V	EU	LV3	O	M		C (M)

ELMS6**LD1 – Location Designator 1 (PRILOC)****RPL Form/Screen, PRILOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies additional specific information related to the address (e.g. bldg).

Definition Notes:

None

Valid Entries:

Entry	Description
-------	-------------

BLDG	Building
------	----------

WNG	Wing
-----	------

PIER	Pier
------	------

Valid Entry Notes:

None

Data Characteristics:

Up to 4 alpha characters

Examples:

BLDG

Conditional Usage Notes:| Note 1: Required when LV1 (**PRILOC**) field is populated otherwise prohibited.**Business Rules**

Rule 1: Must be RSAG valid.

***** End of definition for LD1 / RPL form screen *****

LD1 – Location Designator 1 (SECLOC)**RPL Form/Screen, SECLOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies additional specific information related to the address (e.g. bldg).

Definition Notes:

None

Valid Entries:

Entry Description

BLDG Building

WNG Wing

PIER Pier

Valid Entry Notes:

None

Data Characteristics:

Up to 4 alpha characters

Examples:

BLDG

Conditional Usage Notes:~~None~~**Note 1: Required when the LV1 (SECLOC) Field is populated, otherwise prohibited.****Business Rules**

Rule 1: Address must be RSAG valid.

***** End of definition for LD1 / RPL form screen *****

LD2 – Location Designator 2 (PRILOC)**RPL Form/Screen, PRILOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies additional specific information related to the address (e.g., floor).

Definition Notes:

None

Valid Entries:

FLR = Floor

Valid Entry Notes:

NOTE 1 BellSouth allows only one valid value for this field.

Data Characteristics:

Up to 4 alpha characters

Examples:

FLR

Conditional Usage Notes:| Note 1: Required when LV2 (**PRILOC**) field is populated otherwise prohibited.**Business Rules**

Rule 1: Must be RSAG valid.

***** End of definition for LD2 / RPL form screen *****

LD2 – Location Designator 2 (SECLOC)**RPL Form/Screen, SECLOC Section**

17.0 (LSOG6 / ELMS6 map)

*Updated: 07/28/04, CRB Issues included: None***Definition:**

Identifies additional specific information related to the address (e.g., floor).

Definition Notes:

None

Valid Entries:

FLR = Floor

Valid Entry Notes:

None

Data Characteristics:

Up to 4 alpha characters

Examples:

FLR

Conditional Usage Notes:~~None~~**Note 1: Required when the LV2 (SECLOC) field is populated otherwise prohibited.****Business Rules**

Rule 1: Address must be RSAG valid.

***** End of definition for LD2 / RPL form screen *****

LD3 – Location Designator 3 (PRILOC)**RPL Form/Screen, PRILOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies additional specific information related to the address (e.g., room).

Definition Notes:

None

Valid Entries:

Entry	Description
APT	Apartment
RM	Room
LOT	Lot
SLIP	Slip
SUIT	Suit
UNIT	Unit

Valid Entry Notes:

None

Data Characteristics:

Up to 4 alpha characters

Examples:APT
SUIT
RM**Conditional Usage Notes:**| Note 1: Required when LV3 (**PRILOC**) field is populated, otherwise prohibited.**Business Rules**

Rule 1: Must be RSAG valid.

***** End of definition for LD3 / RPL form screen *****

LD3 – Location Designator 3 (SECLOC)**RPL Form/Screen, SECLOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies additional specific information related to the address (e.g., room).

Definition Notes:

None

Valid Entries:

Entry	Description
APT	Apartment
RM	Room
LOT	Lot
SLIP	Slip
SUIT	Suite
UNIT	Unit

Valid Entry Notes:

None

Data Characteristics:

Up to 4 alpha characters

Examples:

SUIT

Conditional Usage Notes:~~None~~**Note 1: Required when the LV3 (SECLOC) field is populated, otherwise prohibited.****Business Rules**

Rule 1: Address must be RSAG valid.

LV1 – Location Value 1 (PRILOC)

RPL Form/Screen, PRILOC Section

(LSOG6 / ELMS6 map)

Definition:

Identifies the value associated with the first location designator (LD1) of the address.

Definition Notes:

None

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 10 alpha/numeric characters

Examples:

12W

Conditional Usage Notes:

Note 1: Required when the LD1 (PRILOC) field is populated, otherwise prohibited.

Business Rules

Rule 1: Must be RSAG valid.

***** End of definition for LV1 / RPL form screen *****

LV1 – Location Value 1 (SECLOC)**RPL Form/Screen, SECLOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies the value associated with the first location designator (LD1) of the address.

Definition Notes:

None

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 10 alpha/numeric characters

Examples:

12W

Conditional Usage Notes:

Note 1: Required when the LD1 (SECLOC) field is populated, otherwise prohibited.

Business Rules

Rule 1: Address must be RSAG valid.

***** End of definition for LV1 / RPL form screen *****

LV2 – Location Value 2 (PRILOC)**RPL Form/Screen, PRILOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies the value associated with the second location designator (LD2) of the address.

Definition Notes:

None

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 10 alpha/numeric characters

Examples:

2

Conditional Usage Notes:

Note 1: Required when the LD2 (PRILOC) field is populated, otherwise prohibited.

Business Rules

Rule 1: Must be RSAG valid.

***** End of definition for LV2 / RPL form screen *****

LV2 – Location Value 2 (SECLOC)**RPL Form/Screen, SECLOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies the value associated with the second location designator (LD2) of the address.

Definition Notes:

None

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 10 alpha/numeric characters

Examples:

2

Conditional Usage Notes:

Note 1: Required when the LD2 (SECLOC) field is populated, otherwise prohibited.

Business Rules

Rule 1: Address must be RSAG valid.

***** End of definition for LV2 / RPL form screen *****

LV3 – Location Value 3 (PRILOC)**RPL Form/Screen, PRILOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies the value associated with the third location designator (LD3) of the address.

Definition Notes:

NOTE 1: This instance of the LV3 field is used for the service address.

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 10 alpha/numeric characters

[Note 1: BellSouth allows a maximum of 4 alphanumeric characters.]

Examples:

23A

Conditional Usage Notes:

Note 1: Required when the LD3 (PRILOC) field is populated, otherwise prohibited.

Business Rules

Rule 1: Must be RSAG valid.

***** End of definition for LV3 / RPL form screen *****

LV3 – Location Value 3 (SECLOC)**RPL Form/Screen, SECLOC Section**

(LSOG6 / ELMS6 map)

Definition:

Identifies the value associated with the third location designator (LD3) of the address.

Definition Notes:

NOTE 1: This instance of the LV3 field is used for the service address.

Valid Entries:

None

Valid Entry Notes:

None

Data Characteristics:

Up to 10 alpha/numeric characters

Examples:

23A

Conditional Usage Notes:

Required when the LD3 (SECLOC) field is populated, otherwise prohibited.

Business Rules

Rule 1: Address must be RSAG valid.

***** End of definition for LV3 / RPL f

CCP 2047 Attachment Listed Below**TCIF9 & ELMS6****Reqtyp E, Non-complex
Non-Complex Resale Service****Product Listing****Non-Complex Resale Service**

Resale Services are those bundled services where the service provider is different from the network provider. Competitive Local Exchange Carriers (CLECs) can purchase telecommunications products, features and services from Local Exchange Carriers such as BellSouth®, for resale to their customers.

Ordering Forms/Screens

The following chart illustrates the required, conditional and optional forms/screens for ordering this service. Detailed information will follow to assist you in filling out each of these forms/screens.

Forms/Screens Non-Complex Resale Service										
LSR	Hunting	EU	DL	RS	DRS	PS	NP	LS	LSNP	RPL
R	O [1]	R	C [2]	C [3]						
R = Required C = Conditional O = Optional										

[1] = Hunting is optional only when ACT is N, C, T or V, otherwise Hunting is prohibited.

[2] = DL form/screen is required when the ACT is N or T.

[3] = RS form/screen is required only when the ACT is N, C, T, V or S.
Otherwise, the RS form/screen is not required.

Note: Changes to the RESCN (Resellers contact name) are not allowed with Non-Complex REQTYP E ACTs of B, L, S and Y.

Completing the DL Form/Screen

If directory listings are required, refer to **REQTYP J** for more information on completing the DL form/screen.

Completing the HUNTING Section on the LSR-HGI Form/Screen

Hunting is an optional feature only when the ACT is N, C, T or V. For more information on Hunting, refer to the Hunting Section.

Note 1: ELECTRONIC ORDERS - When ACT is V, if Hunting exists on the account being converted and the CLEC wishes to *keep the EXISTING hunting*, the HA field should be populated with "E" and all other required fields populated, **or** the HA field should **not be populated** (NO Hunting Page submitted Electronically).

Note 2: When ordering Hunting Service in conjunction with other service(s) refer to the Hunting section of the LOH-Local Ordering Handbook for processing the hunting portion of the LSR request.

Completing the LSR and EU Forms/Screens

Account level activities (ACT) apply to the entire account. A complete list of ACTs and their definition can be found in the Data Dictionary entry for ACT.

The following chart shows all of the valid account level activities for this service.

Valid Account Level Activities Non-Complex Resale Service										
N	C	D	T	R	V	S	B	W	L	Y
X	X	X	X	-	X	X	X	X	X	X
Note: "X" denotes valid account level activities. A dash (-) indicates a non-valid account level activity.										

The Required, Conditional and Optional (R/C/O) fields on the LSR and EU forms/screens will be given for every valid ACT code in the **ACT Tables** section.

Completing the RS Form/Screen

The Resale Service (RS) form/screen may be required or invalid depending on the account level activity. Each account level activity has valid Line Level Activities (LNAs). These LNAs determine how, or if, the RS form/screen should be populated. A

complete list of LNAs and their definition can be found in the Data Dictionary entry for LNA.

The following chart gives the valid LNAs for each account level activity (ACT) and the associated RS form/screen usage for this service.

If ACT is:	Then LNA is:	And RS form/screen is:
N	N	Required
C	N, C, D, X or P	Required
D	Prohibited	Not Required
T	N, T	Required
V	N, D, G, X, V, W or P	Required
V (UNE-P/WLP to Resale)	N, D, G, X, V or P	Required
S	L or B	Required
B	Prohibited	Not Required
W	Prohibited	Not Required
L	Prohibited	Not Required
Y	Prohibited	Not Required

The Required, Conditional and Optional (R/C/O) fields for the RS form/screen are listed according to the Line Level Activity (LNA) in the **LNA Tables** Section.

UNE-P/WLP (Switched Combination) to Resale

Product Listing

UNE-P/WLP (Switched Combination) to Resale

This section will provide information on ordering when converting/migrating Unbundled Network Elements-Platform (UNE-P/WLP) (Switched Combination) to Resale. This Process allows a CLEC End-User to migrate/convert a telephone number(s) from a UNE-P/WLP (Switched Combination) to Resale.

Restrictions

- ~~Electronic Ordering for~~ **Limited to ACT of V-~~or W~~.**

Ordering Guidelines

- REQ TYP: E
- ACT TYP: V-~~or W~~
- LNA: V, G, X, D, ~~W~~-or N
- ~~R/C/O and LNA Tables: Follow and~~ **For LSR processing**, use the **appropriate Reqtyp E, Non-complex ACT of V RCO tables**~~Resale REQ TYP E Guidelines~~
- Due Date: Follow BellSouth® Products and Services Interval Guide.

Ordering Forms/Screens

~~The following chart illustrates the required, conditional and optional forms for ordering this service~~

Forms/Screens UNE-P/WLP (Switched Combination) to Resale										
LSR	Hunting	EU	DL	RS	DRS	PS	NP	LS	LSNP	RPL
R	O [1]	R	C [2]	C [3]						
R=Required C=Conditional O=Optional										

~~[1]=Hunting is optional only when ACT is N, C, T or V. Otherwise, Hunting is prohibited.~~

~~[2]=DL form/screen is required when the ACT is N or T.~~

~~[3]=RS form/screen is required only when the ACT is N, C, T, V or S. Otherwise, the RS form/screen is not required.~~

Completing the Local Service Request Form(s)

When converting/migrating UNE-P/WLP (Switched Combination) to Resale, the R/C/O tables must be used. If also ordering line feature(s)/services, the RS-Resale Service form



Attachment
SN91084236

is *also* required. Not populating these fields and/or forms will result in a clarification of the LSR.

Follow the **REQTYP E Resale Service (Non-Complex) specific ordering guidelines** for the Required, Conditional and Optional (R/C/O) fields on the appropriate form(s).

CCP 2048 Attachment Listed Below**ELMS6**

BellSouth® MegaLink® Channel Trunk Service
Product Listing

BellSouth® MegaLink® Channel Services

MegaLink® Channel Service provides a "channelization" capability for subscribers between the subscriber's premises and the Company's central office, or between central offices.

Ordering Forms/Screens

The following chart illustrates the required, conditional and optional forms/screens for ordering this service. Detailed information will follow to assist you in filling out each of these forms/screens.

Forms/Screens												
BellSouth® MegaLink® Channel Services (Channelized T1)												
SI	LSR	Hunt- ing	EU	DL	RS	DRS	PS	NP	LS	LSNP	RPL	Complex Work Aid*
	R		R									R (only applicable for DID Trunks)
R = Required C = Conditional O = optional												

- = Complex Work Aid for DID Trunks
- = Complex Work Aid is not needed when ordering PBX Trunks

CLEC Forms On-Line

Refer to the ICS Web Portal page (www.interconnection.bellsouth.com), select 'Tools, Forms & Reports' on toolbar, select 'Forms and Templates', then select "CLEC Forms Online" or just go to CLEC Forms On-Line web page located at:

http://www.interconnection.bellsouth.com/forms/html/lec_form.html

Then below the 'WebForms' table-header, select "Click here to go to the WebForms Main Page" (<http://interconnection.bellsouth.com/forms/html/webforms/stdsrch.html>).

Completing the DL Form/Screen

If directory listings are required, refer to **REQTYP J** for more information on completing the DL form/screen.

Completing the LSR and EU Forms/Screens

Account level activities (ACT) apply to the entire account. A complete list of ACTs and their definition can be found in the Data Dictionary entry for ACT.

The following chart shows all of the valid account level activities for this service.

Valid Account Level Activities BellSouth® MegaLink® Channel Services (Channelized T1)										
N	C	D	T	R	V	S	B	W	L	Y
X	X	X	X	-	X	-	-	X	-	-
Note: "X" denotes valid account level activities. A dash (-) indicates a non-valid account level activity.										

The Required, Conditional and Optional (R/C/O) fields on the LSR and EU forms/screens will be given for every valid ACT code in the **ACT Tables** section.

RCO Tables

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored. Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the Data Dictionary for clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqttyp E, BellSouth® MegaLink® Channel Trunk Service**ACT= C: LSR****Required**

ACT (M)	ATN (M)	BAN1 (M)
BCS (M)	CC (M)	CCNA (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
INIT (M)	INIT-FAX NO. (M)	INIT-TEL NO. (M)
LSO (M)	P (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	CUST (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	LSP AUTH DATE (M)
LSP AUTH NAME (M)	MEU (M)	PROJECT (M)
RPON (M)	SUP (M)	VER (M)

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
DFDT (M)	EXP (M)	HTQTY (M)
LSCP (M)	LSP AUTH (M)	LST (M)
REMARKS (M)	RORD (M)	SCA (M)
VT A (M)		

ACT Tables: Reqttyp E, BellSouth® MegaLink® Channel Trunk Service**ACT= C: EU**Required

ATN (M)	LOCNUM (M)	LOCNUM DETAIL (M)
NAME (M)	PG_OF_ (M)	PON (M)

Conditional

AAI (M)	ACC (M)	CITY (M)
EUA (M)	IWBAN (M)	IWCON (M)
IWCON-TEL NO. (M)	IWO (M)	LD1 (M)
LD2 (M)	LD3 (M)	LV1 (M)
LV2 (M)	LV3 (M)	SANO (M)
SASD (M)	SASF (M)	SASN (M)
SASS (M)	SATH (M)	STATE (M)
VER (M)	ZIP (M)	

Optional

DQTY (M)	LCON-NAME (M)	LCON-TEL NO. (M)
LOCNUM HEADER (M)	REMARKS (M)	

ACT= D: LSRRequired

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	P (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	CUST (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	LSO (M)
LSP AUTH DATE (M)	LSP AUTH NAME (M)	MEU (M)
NOR (M)	PROJECT (M)	RPON (M)
SUP (M)	VER (M)	

ACT Tables: Reqtyp E, BellSouth® MegaLink® Channel Trunk Service**Optional**

ALT-IMPCON* (M)	APPTIME-DDD (M)	DFDT (M)
EXP (M)	IMPCON* (M)	LSP AUTH (M)
LST (M)	REMARKS (M)	RORD (M)
VTA (M)		

ACT= D: EU**Required**

ATN (M)	LOCNUM (M)	NAME (M)
PG_OF_ (M)	PON (M)	

Conditional

AAI (M)	EUA (M)	LD1 (M)
LD2 (M)	LD3 (M)	LV1 (M)
LV2 (M)	LV3 (M)	SANO (M)
SASD (M)	SASF (M)	SASN (M)
SASS (M)	SATH (M)	VER (M)

Optional

DQTY (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)		

ACT= N: LSR**Required**

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	IMPCON (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	P (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	CUST (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	LSP AUTH DATE (M)
LSP AUTH NAME (M)	MEU (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

ACT Tables: Reqtyp E, BellSouth® MegaLink® Channel Trunk Service**Optional**

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
DFDT (M)	EXP (M)	HTQTY (M)
LSCP (M)	LSP AUTH (M)	LST (M)
REMARKS (M)	RORD (M)	RPON (M)
SCA (M)	VTA (M)	

ACT= N: EU**Required**

ATN (M)	CITY (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	ACC (M)	EUA (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
IWO (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	NCON (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	REMARKS (M)
---------------	------------------	-------------

ACT= T: LSR**Required**

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	DDDO (M)	IMPCON (M)
INIT (M)	INIT-FAX NO. (M)	INIT-TEL NO. (M)
LSO (M)	P (M)	PG_OF_ (M)
PON (M)	REQTYP (M)	SC (M)
TOS (M)		

ACT Tables: Reqtyp E, BellSouth® MegaLink® Channel Trunk Service**Conditional**

ALT-IMPCON-TEL NO. (M)	BI1 (M)	CUST (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	LSP AUTH DATE (M)
LSP AUTH NAME (M)	MEU (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
DFDT (M)	EXP (M)	HTQTY (M)
LSCP (M)	LSP AUTH (M)	LST (M)
REMARKS (M)	RORD (M)	RPON (M)
SCA (M)	VTA (M)	

ACT= T: EU**Required**

ATN (M)	CITY (M)	LOCNUM (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	ACC (M)	EUA (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
IWO (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	NCON (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	REMARKS (M)
---------------	------------------	-------------

ACT Tables: Reqtyp E, BellSouth® MegaLink® Channel Trunk Service**ACT= V: LSR****Required**

ACT (M)	ATN (M)	BAN1 (M)
BCS (M)	CC (M)	CCNA (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
INIT (M)	INIT-FAX NO. (M)	INIT-TEL NO. (M)
LSO (M)	MI (M)	P (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	CUST (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	LSP AUTH DATE (M)
LSP AUTH NAME (M)	MEU (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

Optional

ALBR (M)	ALT-IMPCON* (M)	APPTIME-DDD (M)
DDDO (M)	DFDT (M)	EXP (M)
HTQTY (M)	LSCP (M)	LSP AUTH (M)
LST (M)	REMARKS (M)	RORD (M)
VTA (M)		

ACT= V: EU**Required**

ATN (M)	ELT (M)	LOCNUM (M)
LOCNUM DETAIL (M)	NAME (M)	PG_OF_ (M)
PON (M)	SASN (M)	STATE (M)
ZIP (M)		

ACT Tables: Reqtyp E, BellSouth® MegaLink® Channel Trunk Service**Conditional**

AAI (M)	ACC (M)	CITY (M)
EAN (M)	EATN (M)	EUA (M)
EUMI (M)	FB-BILLCON (M)	FB-BILLCON TEL NO. (M)
FB-BILLNM (M)	FB-CITY (M)	FB-FLOOR (M)
FBI (M)	FB-ROOM (M)	FB-SBILLNM (M)
FB-STATE (M)	FB-STREET (M)	FB-ZIP (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
IWO (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	NCON (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

DQTY (M)	LCON-NAME (M)	LCON-TEL NO. (M)
LOCNUM HEADER (M)	REMARKS (M)	

ACT= W: LSR**Required**

ACT (M)	ATN (M)	BAN1 (M)
CC (M)	CCNA (M)	D/TSENT (M)
DDD (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	P (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

ALT-IMPCON-TEL NO. (M)	BI1 (M)	CUST (M)
IMPCON-TEL NO. (M)	LOCQTY (M)	LSP AUTH DATE (M)
LSP AUTH NAME (M)	NOR (M)	PROJECT (M)
RPON (M)	SUP (M)	VER (M)

Optional

ALT-IMPCON* (M)	APPTIME-DDD (M)	EXP (M)
IMPCON* (M)	LSP AUTH (M)	LST (M)
REMARKS (M)	RORD (M)	VTA (M)



Attachment
SN91084236

ACT Tables: Reqttyp E, BellSouth® MegaLink® Channel Trunk Service

ACT= W: EU

Required

ATN (M)	LOCNUM (M)	LOCNUM DETAIL (M)
NAME (M)	PG_OF_ (M)	PON (M)
SASN (M)	STATE (M)	ZIP (M)

Conditional

AAI (M)	CITY (M)	EAN (M)
EATN (M)	LD1 (M)	LD2 (M)
LD3 (M)	LV1 (M)	LV2 (M)
LV3 (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		

Optional

DQTY (M)	LCON-NAME (M)	LCON-TEL NO. (M)
LOCNUM HEADER (M)	REMARKS (M)	