

## **Table of Contents – Revision History**

### **9-State LSOR Version 10.23 Revision Updates (03/19/16)**

#### **3a. Form Description**

#### **3.2 Request Type & Activity (Codes)**

#### **3b. REQTyp/ACT Form Requirements**

#### **5c. AT&T Error Codes & Messages**

**ADDED ERROR CODES & MESSAGES**

**REVISED ERROR CODES & MESSAGES**

**REMOVED ERROR CODES & MESSAGES**

#### **FORM: LOCAL SERVICE REQUEST**

**19\_DDD**

**06\_NPQTY**

**43\_PORTED\_NBR**

**46\_NPT**

**60\_LEAN**

**61\_LEATN**

### **9-State LSOR Version 10.24 Revision Updates (11/12/16)**

#### **AT&T Error Codes & Messages**

**ADDED ERROR CODES & MESSAGES**

**REVISED ERROR CODES & MESSAGES**

## **REMOVED ERROR CODES & MESSAGES**

### **FORM: LOOP SERVICE**

**11\_LMT**

**12\_BTRL**

**13\_CKR**

**14\_TSP**

**15\_TNT**

**19\_ECCKT**

**23\_CFA**

**32\_CABLE\_ID**

**34\_CHAN/PAIR**

**43\_JR**

**44\_IWT**

**45\_NIDR**

**48\_DISC\_NBR**

**50\_TC\_OPT**

**51\_TC\_TO\_PRI**

**52\_TC\_TO\_SEC**

**53\_TCID**

**54\_TC\_NAME**

**55\_TC\_PER**

56\_LEAN

57\_LEATN

58c\_CABLE\_ID2

58d\_CHAN/PAIR2

58g\_SCFA

58h\_TC\_FR

## FORM: DIGITAL TRUNKING UNE SERVICE

13\_CFA\_(DS1)

42\_TGN

46\_DGOUT

47\_TGRTI

48\_TGTN

51\_GLARE

54\_TGTLI

56\_TGSGNL

57\_DID\_IND

64\_TGTLI

65\_TG\_TC\_OPT

66\_TG\_TC\_TO\_PRI

76\_DBA

78\_LNUM

82\_TKIND

83\_LTGN

84\_ECCKT

86\_TC\_OPT

87\_TC\_TO\_PRI

101b\_CABLE\_ID

101c\_DIN

101i\_IWT

101s\_TTP

## **FORM: DIGITAL TRUNKING RESALE SERVICE**

46\_DGOUT

48\_TGTN

51\_GLARE

52\_PIC\_(TRKS)

53\_LPIC\_(TRKS)

55\_TGPULSE

56\_TGSGNL

57\_DID\_IND

62\_DTNR

65\_CFA\_(TRKS)

77\_DBA

79\_LNUM

82\_TNS

84\_TKIND

85\_LTGN

86\_ECCKT

87\_TC\_OPT

96\_TERS

98\_PIC

99\_LPIC

101\_BLOCK

101a\_CABLE\_ID

101b\_DIN

101c\_FPI

101e\_IWJK

101f\_IWJQ

101g\_IWT

101i\_JK\_CODE

101j\_JK\_NUM

101k\_JK\_POS

101l\_JR

**9-State LSOR Version 10.25 Revision Updates (03/18/17)**

## **5c. AT&T Error Codes & Messages**

**ADDED ERROR CODES & MESSAGES**

**REVISED ERROR CODES & MESSAGES**

**REMOVED ERROR CODES & MESSAGES**

### **FORM: LOCAL SERVICE REQUEST**

**26\_PROJECT**

**37\_SUP**

### **FORM: PORT SERVICE**

**05\_PQTY**

**09\_LNUM**

**16\_TNS**

**30\_ECCKT**

**74d\_MATN**

### **FORM: RESALE SERVICE**

**28\_LPIC**

**30\_TC\_OPT**

**63f\_TC\_FR**

### **FORM: RESALE COMPLEX SERVICE**

**50\_BA**

**63d\_MATN**

**63e\_SDI**

## **FORM: CENTREX RESALE SERVICE**

**07\_CB**

**07a\_SNA**

**39\_TERS**

**61\_FPI**

**75ff\_CPG**

**75jj\_ST**

## **9-State LSOR Version 10.26 Revision Updates (11/11/17)**

### **AT&T Error Codes & Messages**

#### **5c. AT&T Error Codes & Messages**

**ADDED ERROR CODES & MESSAGES**

**REVISED ERROR CODES & MESSAGES**

**REMOVED ERROR CODES & MESSAGES**

## **FORM: LOOP SERVICE**

**10\_SLTN**

**12\_BTRL**

**13\_CKR**

**14\_TSP**

**15\_TNT**

**18\_SAN**

**19\_ECCKT**

**23\_CFA**

**30\_SYSTEM\_ID**

**31\_CTI**

**32\_CABLE\_ID**

**34\_CHAN/PAIR**

**35\_RELAY\_RACK**

**36\_SHELF**

**37\_SLOT**

**40\_JK\_CODE**

**41\_JK\_NUM**

**42\_JK\_POS**

**43\_JR**

**44\_IWT**

**45\_NIDR**

**46\_IWJK**

**47\_IWJQ**

**48\_DISC\_NBR**

**50\_TC\_OPT**

**51\_TC\_TO\_PRI**

**52\_TC\_TO\_SEC**

**53\_TCID**



54\_TC\_NAME

55\_TC\_PER

58d\_CHAN/PAIR2

58e\_CMA

58f\_IWTQ

58g\_SCFA

58h\_TC\_FR

58i\_TER

**FORM: RESALE PRIVATE LINE**

15\_SANO

16\_SASF

17\_SASD

18\_SASN

19\_SATH

20\_SASS

41\_ACC

50\_SANO

51\_SASF

52\_SASD

53\_SASN

54\_SATH

55\_SASS

69\_ACTEL\_NO

71\_AACTEL

72\_IWO

76\_ACC

79\_FBI

092\_DNUM

93\_DISC\_ECCKT

94\_REMARKS

96a\_CKTA

96b\_SVC\_CD

96c\_MTP

96e\_CKTTYP

103\_JR

117\_FA

118\_FEATURE

119\_FEATURE\_DETAIL

126\_JR

140\_FA

141\_FEATURE

142\_FEATURE\_DETAIL

**142g\_FRF**

**142t\_LC**

**142u\_LCON\_TEL\_NO**

**142v\_LCON\_TEL\_NO**

## **9-State LSOR Version 10.27 Revision Updates (03/18/17)**

### **AT&T Error Codes & Messages**

#### **5c. AT&T Error Codes & Messages**

**ADDED ERROR CODES & MESSAGES**

**REVISED ERROR CODES & MESSAGES**

**REMOVED ERROR CODES & MESSAGES**

## 9-State LSOR Version 10.23 Revision Updates (03/19/16)

### 3a. Form Description

REMOVED:

**Matrix Table Example** (partial example taken from an LSR Form field matrix)

	ACTIVITIES										
REQTYP - Product	N	C	D	T	R	V	W	S	B	Y	L
REQTYP A-Address Correction-Designed Products	P	P	P	P	C	P	P				
REQTYP A-Address Correction-Non Designed Products	P	P	P	P	C	P	P				
REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)/EELs connected to Wholesale	C	P	C	P	P	P	P				

ADDED:

**Matrix Table Example** (partial example taken from an LSR Form field matrix)

	ACTIVITIES										
REQTYP - Product	N	C	D	T	R	V	W	S	B	Y	L
REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)	C	P	C	P	P	P	P				

### 3.2 Request Type & Activity (Codes)

REMOVED:

REQTYP Code	Request Type Description	Abbreviation
U	DID/PBX Port	DPU

### 3b. REQ TYP/ACT Form Requirements

REMOVED:

#### REQ TYP U

FORM/ACT	LSR	HGI	EU	LS (A)	LSNP (B)	NP (C)	RS (E)	RS Complex (E)	PS (F&M)	RPL (K)	CRS (P)	DTR (R)	DTU (S)	DPR (T)	DPU (U&W)	CUS (X)	IUS (Y&2)	IRS (Z)	DL
<b>N</b> = New Install	R	O	R	P	P	P	P	P	P	P	P	P	P	P	R	P	P	P	R
<b>C</b> = Change	R	O	R	P	P	P	P	P	P	P	P	P	P	P	R	P	P	P	O
<b>D</b> = Disconnect	R	P	R	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P
<b>T</b> = Move	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P
<b>R</b> = Record	R	P	R	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	O
<b>V</b> = Conv with Change	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P
<b>W</b> = Conv As Is	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P
<b>S</b> = Suspend/Restore Partial	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P
<b>B</b> = Restore Full	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P
<b>Y</b> = Deny	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P
<b>L</b> = Suspend Full	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P	P

#### REQ TYP U Conditions:

1. HGI form is optional for UNE Port Service (PBX Stand Alone Port), otherwise prohibited.

## 5c. AT&T Error Codes & Messages

### ADDED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
None at this time	

### REVISED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
None at this time	

### REMOVED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
R8002	LSR-TOS INVALID FOR REQ TYP U

## FORM: LOCAL SERVICE REQUEST

Legend: Modified New Delete

### 19\_DDD

**Notes**

REMOVED:

When the requested DDD is not available, the LSR will be returned to the originator to request a new DDD, later than the previously requested DDD.

**Notes**

REMOVED:

When the 2nd character of the TOS is P or R and the RORD field is populated with LSTNPSO, the system will return the following message: CANNOT CALCULATE DUE DATE, DUE DATE WILL BE RETURNED ON THE FOC.

ADDED:

When the 2nd character of the TOS is P or R and the RORD field is populated with LSTNPSO, the system will return the following message: DUE DATE WILL BE RETURNED ON THE FOC. LSR SUBMITTED SUCCESSFULLY..

## 06\_NPQTY

Conditions

ADDED:

Required when LNA is V.

Conditions

ADDED:

Prohibited when LNA is N.

Usage Matrix

This field is required.

	ACTIVITIES
<b>REQTYP - Product</b>	V
<b>REQTYP B-LNP BSLA-Designed Analog Loop</b>	RC
<b>REQTYP B-LNP BSLA-EELS</b>	RC
<b>REQTYP B-LNP BSLA-ISDN</b>	RC
<b>REQTYP B-LNP BSLA-Non-Designed Analog Loop</b>	RC
<b>REQTYP B-LNP BSLA-UCL-D</b>	RC
<b>REQTYP B-LNP BSLA-UCL-ND</b>	RC
<b>REQTYP B-LNP BSLA-XDSL</b>	RC
<b>REQTYP B-LNP, Designed Analog Loop</b>	RC
<b>REQTYP B-LNP, Digital Designed Basic Rate ISDN</b>	RC
<b>REQTYP B-LNP, EELs</b>	RC
<b>REQTYP B-LNP, Non-Designed Analog Loop</b>	RC
<b>REQTYP B-LNP, Sub-Loops</b>	RC
<b>REQTYP B-LNP, Unbundled Copper Loop-Designed (UCL-D)</b>	RC
<b>REQTYP B-LNP, Unbundled Copper Loop-Non-Designed (UCL- ND)</b>	RC
<b>REQTYP B-LNP, xDSL Loops</b>	RC

## 43\_PORTED\_NBR

Usage Matrix

This field is conditional.

	ACTIVITIES
<b>REQTYP - Product</b>	V

<i>REQTYP B-LNP BSLA-Designed Analog Loop</i>	RC
<i>REQTYP B-LNP BSLA-EELS</i>	RC
<i>REQTYP B-LNP BSLA-ISDN</i>	RC
<i>REQTYP B-LNP BSLA-Non-Designed Analog Loop</i>	RC
<i>REQTYP B-LNP BSLA-UCL-D</i>	RC
<i>REQTYP B-LNP BSLA-UCL-ND</i>	RC
<i>REQTYP B-LNP BSLA-XDSL</i>	RC
<i>REQTYP B-LNP, Designed Analog Loop</i>	C
<i>REQTYP B-LNP, Digital Designed Basic Rate ISDN</i>	C
<i>REQTYP B-LNP, EELs</i>	C
<i>REQTYP B-LNP, Non-Designed Analog Loop</i>	C
<i>REQTYP B-LNP, Sub-Loops</i>	C
<i>REQTYP B-LNP, Unbundled Copper Loop-Designed (UCL-D)</i>	C
<i>REQTYP B-LNP, Unbundled Copper Loop-Non-Designed (UCL- ND)</i>	C
<i>REQTYP B-LNP, xDSL Loops</i>	C

## 46\_NPT

### Conditions

ADDED:

Required when LNA is V.

### Conditions

ADDED:

Prohibited when LNA is N.

### Usage Matrix

This field is conditional.

	ACTIVITIES
<i>REQTYP - Product</i>	V
<i>REQTYP B-LNP BSLA-Designed Analog Loop</i>	RC
<i>REQTYP B-LNP BSLA-EELS</i>	RC
<i>REQTYP B-LNP BSLA-ISDN</i>	RC
<i>REQTYP B-LNP BSLA-Non-Designed Analog Loop</i>	RC
<i>REQTYP B-LNP BSLA-UCL-D</i>	RC



REQTYP B-LNP BSLA-UCL-ND	RC
REQTYP B-LNP BSLA-XDSL	RC
REQTYP B-LNP, Designed Analog Loop	RC
REQTYP B-LNP, Digital Designed Basic Rate ISDN	RC
REQTYP B-LNP, EELs	RC
REQTYP B-LNP, Non-Designed Analog Loop	RC
REQTYP B-LNP, Sub-Loops	RC
REQTYP B-LNP, Unbundled Copper Loop-Designed (UCL-D)	RC
REQTYP B-LNP, Unbundled Copper Loop-Non-Designed (UCL-ND)	RC
REQTYP B-LNP, xDSL Loops	RC

**60\_LEAN**

Conditions

ADDED:

Prohibited when LNA is N.

**61\_LEATN**

Conditions

ADDED:

Prohibited when LNA is N.

**9-State LSOR Version 10.24 Revision Updates (11/12/16)**

**AT&T Error Codes & Messages**

**ADDED ERROR CODES & MESSAGES**

ERROR CODE	ERROR MESSAGE
None at this time	

**REVISED ERROR CODES & MESSAGES**

ERROR CODE	ERROR MESSAGE

None at this time	
-------------------	--

## REMOVED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
------------	---------------

None at this time

## FORM: LOOP SERVICE

Legend: Modified New Deleted

### 11\_LMT

#### Conditions

ADDED:

For Unbundled Copper Loop - Non-Designed (UCL-ND) and Unbundled Copper Loop - Designed (UCL), xDSL Loops, HFS Unbundled CO-based Line Splitting, and Unbundled CO-based Line Share, prohibited when LNA is D.

#### Conditions

ADDED:

For Unbundled CO-based Line Share and HFS Unbundled CO-based Line Splitting, prohibited when LNA is V or W.

### 12\_BTRL

#### Conditions

ADDED:

For Unbundled Copper Loop - Non-Designed (UCL-ND) and Unbundled Copper Loop - Designed (UCL), prohibited when LNA is D.

### 13\_CKR

#### Conditions

REMOVED:

For Analog Designed Loop, Analog Non-Designed Loop and Digital Data Designed Loop (DS0), prohibited when the LNA is D, otherwise optional.

ADDED:

For Analog Designed Loop, Analog Non-Designed Loop and Digital Data Designed Loop (DS0), xDSL Loops and Universal Digital Channel (UDC), prohibited when the LNA is D, otherwise optional.

### 14\_TSP

#### Conditions

REMOVED:

For Analog Designed Loop, Analog Non-Designed Loop, Digital Data Designed Loop (DS0), Digital Designed Loop (Basic Rate ISDN), Unbundled Copper Loop-Designed (UCL), Unbundled Copper Loop-Non-Designed (UCL-ND) and xDSL Loops, prohibited when the LNA is D, otherwise optional.

ADDED:

For Analog Designed Loop, Analog Non-Designed Loop, Digital Data Designed Loop (DS0), Digital Designed Loop (Basic Rate ISDN), Unbundled Copper Loop-Designed (UCL), Unbundled Copper Loop-Non-Designed (UCL-ND), Universal Digital Channel (UDC) and xDSL Loops, prohibited when the LNA is D, otherwise optional.

#### Conditions

ADDED:

For Digital Data Designed Loop (DS1) and (Non-Channelized) DS1, prohibited when LNA is C, D or T, otherwise optional.

## 15\_TNT

#### Conditions

REMOVED:

Prohibited when the LNA is D and the request is for UCL-ND.

ADDED:

For Unbundled Copper Loop-Non-Designed (UCL-ND), prohibited when the LNA is D.

## 19\_ECCKT

#### Conditions

REMOVED:

Prohibited when LNA is N on the following products: Analog Designed Loop; Analog Non-Designed Loop; Digital Data Designed Loop (DS0); Digital Designed Basic Rate ISDN.

ADDED:

Prohibited when LNA is N on the following products: Analog Designed Loop; Analog Non-Designed Loop; Digital Data Designed Loop (DS0); Digital Designed Loop (Basic Rate ISDN); Digital Data Designed Loop (DS1) and (Non-Channelized) DS1.

#### Conditions

REMOVED:

For Analog Designed Loop, Analog Non-Designed Loop and Digital Data Designed Loop (DS0), required when the LNA is C, D or T.

ADDED:

For Analog Designed Loop, Analog Non-Designed Loop and Digital Data Designed Loop (DS0), Digital Designed Loop (Basic Rate ISDN), Digital Data Designed Loop (DS1) and (Non-Channelized) DS1, Unbundled Copper Loop - Designed (UCL) and Unbundled Copper Loop - Non-Designed (UCL-ND), required when the LNA is C, D or T.

#### Conditions

REMOVED:

For Analog Designed Loop and Digital Data Designed Loop (DS0), prohibited when the LNA is N or V.

ADDED:

For Analog Designed Loop and Digital Data Designed Loop (DS0), Digital Designed Loop (Basic Rate ISDN), Digital Data Designed Loop (DS1) and (Non-Channelized) DS1, Unbundled Copper Loop - Designed (UCL) and Unbundled Copper Loop - Non-Designed (UCL-ND), prohibited when the LNA is N or V.

#### Conditions

REMOVED:

When the request is for EELS and the LNA = N, the ECCKT field is required when the ACT = T and prohibited when the ACT = N.

#### Conditions

ADDED:

Required when ACT is T and LNA is N for EELs.

#### Conditions

ADDED:

Prohibited when ACT is N for EELs.

## 23\_CFA

### Conditions

REMOVED:

For Analog Designed Loop and Digital Data Designed Loop (DS0), prohibited when the LNA is D.

ADDED:

For Analog Designed Loop and Digital Data Designed Loop (DS0), Digital designed Loop (Basic Rate ISDN), Digital Data Designed Loop (DS1) and (Non-Channelized) DS1 and Universal Digital Channel (UDC), prohibited when the LNA is D.

## 32\_CABLE\_ID

### Conditions

REMOVED:

For the following products, CABLE ID must be populated when CHAN/PAIR is populated and CFA is not populated, however, CABLE ID must not be populated if CFA is populated: Analog Designed Loop; Digital Data Designed Loop (DS0); Digital Designed Loop Basic Rate ISDN; Unbundled Sub-Loop Feeder; Universal Digital Channel (UDC); EELs 4W VG; EELs 2W VG; EELs 56/64 kbps.

ADDED:

For the following products, CABLE ID must be populated when CHAN/PAIR is populated and CFA is not populated, however, CABLE ID must not be populated if CFA is populated: Analog Designed Loop; Digital Data Designed Loop (DS0); Digital Designed Loop (Basic Rate ISDN); Unbundled Sub-Loop Feeder; Universal Digital Channel (UDC); EELs 4W VG; EELs 2W VG; EELs 56/64 kbps.

### Conditions

REMOVED:

For Analog Designed Loop and Digital Data Designed Loop (DS0), prohibited when the LNA is D.

ADDED:

For Analog Designed Loop, Analog Non-Designed Loop, Digital Data Designed Loop (DS0), Digital Designed Loop (Basic Rate ISDN), Digital Data Designed Loop (DS1) and (Non-Channelized) DS1, Unbundled Copper Loop - Designed (UCL) , Unbundled Copper Loop - Non-Designed (UCL-ND), Unbundled CO-based Line Share (DLEC or ATT-owned splitter) and HFS Unbundled CO-based Line Splitting (DLEC or ATT-owned splitter), prohibited when the LNA is D.

### Conditions

REMOVED:

For Analog Non-Designed Loop, prohibited when the LNA is D.

## 34\_CHAN/PAIR

### Conditions

REMOVED:

For the following products, CHAN/PAIR must be populated when CABLE ID is populated and CFA is not populated, however, CHAN/PAIR must not be populated if CFA is populated: Analog Designed Loop; Digital Data Designed Loop (DS0); Digital Designed Loop Basic Rate ISDN; Universal Digital Channel (UDC); EELs 4W VG; EELs 56/64 kbps.

ADDED:

For the following products, CHAN/PAIR must be populated when CABLE ID is populated and CFA is not populated, however, CHAN/PAIR must not be populated if CFA is populated: Analog Designed Loop; Digital Data Designed Loop (DS0); Digital Designed Loop (Basic Rate ISDN); Universal Digital Channel (UDC); EELs 4W VG; EELs 56/64 kbps.

### Conditions

REMOVED:

For Analog Designed Loop and Digital Data Designed Loop (DS0), prohibited when the LNA is D.

ADDED:

For Analog Designed Loop, Digital Data Designed Loop (DS0), Digital Designed Loop (Basic Rate ISDN), Digital Data Designed Loop (DS1) and (Non-Channelized) DS1, Unbundled Copper Loop -

Designed (UCL) and Unbundled Copper Loop - Non-Designed (UCL-ND), xDSL Loops and Universal Digital Channel (UDC), prohibited when the LNA is D.

## 43\_JR

### Conditions

REMOVED:

For Analog Designed Loop, Analog Non-Designed Loop and Digital Data Designed Loop (DS0), prohibited when the LNA is D, otherwise optional.

ADDED:

For Analog Designed Loop, Analog Non-Designed Loop, Digital Data Designed Loop (DS0), Digital Designed Loop (Basic Rate ISDN), Digital Data Designed Loop (DS1) and (Non Channelized) DS1, Unbundled Copper Loop - Designed (UCL), Unbundled Copper Loop - Non-Designed (UCL-ND), xDSL Loops and Universal Digital Channel (UDC), prohibited when the LNA is D, otherwise optional.

## 44\_IWT

### Conditions

REMOVED:

Required when IWO is populated for the following products: Analog Designed and Non-Designed Loop; Digital Data Designed Loop (DS0 and DS1); Digital Data Basic Rate ISDN; ADSL (2W) designed; HDSL (2W) designed and (4W) designed; UCL-Short (2W) designed and (4W) designed; UCL-Long (2W) designed and (4W) designed; Enhanced Extended Links (EELS); UCL-ND; Universal Digital Channel (UDC).

ADDED:

Required when IWO is populated for the following products: Analog Designed and Non-Designed Loop; Digital Data Designed Loop (DS0 and DS1); Digital Data Loop (Basic Rate ISDN); ADSL (2W) designed; HDSL (2W) designed and (4W) designed; UCL-Short (2W) designed and (4W) designed; UCL-Long (2W) designed and (4W) designed; Enhanced Extended Links (EELS); UCL-ND.

### Conditions

REMOVED:

For Digital Data Designed Loop (DS0), prohibited when the LNA is D.

ADDED:

For Digital Data Designed Loop (DS0), Digital Designed Loop (Basic Rate ISDN), Digital Data Designed Loop (ISDN) and Non-Channelized) DS1, Unbundled Copper Loop - Designed (UCL) and Unbundled Copper Loop - Non-Designed (UCL-ND), xDSL Loops, prohibited when the LNA is D.

## 45\_NIDR

### Conditions

REMOVED:

For Analog Designed Loop, Analog Non-Designed Loop and Digital Data Designed Loop (DS0), prohibited when the LNA is D, otherwise optional.

ADDED:

For Analog Designed Loop, Analog Non-Designed Loop and Digital Data Designed Loop (DS0), Digital Designed Loop (ISDN), Digital Data Designed Loop (DS1) and (Non-Channelized) DS1, Unbundled Copper Loop - Designed (UCL), Unbundled Copper Loop - Non-Designed (UCL-ND), xDSL Loops and Universal Digital Channel (UDC), prohibited when the LNA is D, otherwise optional.

## 48\_DISC\_NBR

### Conditions

REMOVED:

For Digital Designed Loop (Basic Rate ISDN), Digital Data Designed Loop (DS1) and (Non-Channelized) DS1 and Unbundled Copper Loop-Non-Designed (UCL-ND), prohibited when the LNA is N or C.

### Conditions

ADDED:

For xDSL Loops and Universal Digital Channel (UDC), prohibited when LNA is N, C or T.

## 50\_TC\_OPT

### Conditions

REMOVED:

Prohibited when LNA is D and the product is: XDSL; Unbundled Copper Loop Designed (2W/4W) (UCL-D); Unbundled Copper Loop Non-Designed (UCL-ND); EELS.

ADDED:

Prohibited when LNA is D and the product is: xDSL; EELS.

### Conditions

ADDED:

For Digital Designed Loop (Basic Rate ISDN), prohibited when the LNA is N, C or V.

## 51\_TC\_TO\_PRI

### Conditions

ADDED:

For Digital Designed Loop (Basic Rate ISDN), prohibited when the LNA is N, C or V.

## 52\_TC\_TO\_SEC

### Conditions

ADDED:

For Digital Designed Loop (Basic Rate ISDN), prohibited when the LNA is N, C or V.

## 53\_TCID

### Conditions

REMOVED:

Prohibited when the REQ TYP is A and the LNA is D and the request is for the following products: ADSL (2 W); HDSL (2W/4W); UCL-D (2W/4W); UCL-ND; EELS.

ADDED:

Prohibited when the LNA is D and the request is for the following products: ADSL (2 W); HDSL (2W/4W); EELS.

### Conditions

ADDED:

For Digital Designed Loop (Basic Rate ISDN), prohibited when the LNA is N, C or V.

## 54\_TC\_NAME

### Conditions

REMOVED:

Prohibited on the following products when the LNA is D: Unbundled CO-based Line Share; Unbundled CO-based Line Splitting; Designed ADSL (2 W); Designed HDSL (2 W/4 W); Designed UCL (2 W/4 W); Non-Designed Unbundled Copper Loop-Non-Designed (UCL-ND); EELS.

ADDED:

Prohibited on the following products when the LNA is D: Unbundled CO-based Line Share; Unbundled CO-based Line Splitting; Designed ADSL (2 W); Designed HDSL (2 W/4 W); Designed UCL (2 W/4 W); EELS.

### Conditions

ADDED:

For Digital Designed Loop (Basic Rate ISDN), prohibited when the LNA is N, C or V.

## 55\_TC\_PER

### Conditions

REMOVED:

Prohibited when the LNA is D and the product type is: Line Share; Line Splitting; XDSL; Unbundled Copper Loop Designed (UCL-D); Unbundled Copper Loop Non-Designed (UCL-ND); EELS.

ADDED:

Conditions

Prohibited when the LNA is D and the product type is: Line Share; Line Splitting; XDSL; EELs.

ADDED:

For Digital Designed Loop (Basic Rate ISDN), prohibited when the LNA is N, C or V.

## 56\_LEAN

Conditions

REMOVED:

For Analog Non-Designed Loop, prohibited when the LNA is N or D.

ADDED:

For Analog Non-Designed Loop, Unbundled Copper Loop - Non-Designed (UCL-ND), Unbundled Copper Loop - Designed (UCL) and xDSL Loops, prohibited when the LNA is N or D.

## 57\_LEATN

Conditions

REMOVED:

For Analog Non-Designed Loop, prohibited when the LNA is N or D.

ADDED:

For Analog Non-Designed Loop, Unbundled Copper Loop - Non-Designed (UCL-ND), Unbundled Copper Loop - Designed (UCL), and xDSL Loops, prohibited when the LNA is N or D.

## 58c\_CABLE\_ID2

Conditions

ADDED:

Prohibited when LNA is D, V or W for HFS Unbundled CO-based Line Splitting (DLEC-owned Splitter).

## 58d\_CHAN/PAIR2

Conditions

REMOVED:

Prohibited when the product is UCL-ND and the LNA is N, C, V or G.

## 58g\_SCFA

Conditions

ADDED:

Required when the ACT is N, C or D and the request is for stand alone Inter Office Channel (IOC), otherwise prohibited.

REMOVED:

Required when the LNA is N, C or D and the request is for stand alone Inter Office Channel (IOC), otherwise prohibited.

## 58h\_TC\_FR

Conditions

REMOVED:

Prohibited when LNA is N, C or D.

ADDED:

Prohibited when LNA is N.

Conditions

REMOVED:

Prohibited when ACT is L or W and the 2nd character of TOS is 9.

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A-Analog Non-Designed Loop	P	CP	P	P	P	P	P

## FORM: DIGITAL TRUNKING UNE SERVICE

Legend: Modified New Deleted

### 13\_CFA\_(DS1)

Conditions

ADDED:

Prohibited when TGLNA is P or W.

### 42\_TGN

Conditions

ADDED:

Prohibited when TGLNA is P or W.

### 46\_DGOUT

Conditions

ADDED:

Prohibited when TGLNA is P or W.

### 47\_TGRTI

Conditions

REMOVED:

Required when the TGLNA field is populated with N, V, or T.

ADDED:

Required when the TGLNA field is populated with N or V.

### 48\_TGTN

Conditions

REMOVED:

Required when the TGLNA field is N, V, or T.

ADDED:

Required when the TGLNA field is N or V.

### 51\_GLARE



Conditions

ADDED;  
Prohibited when TGLNA is P or W.

**54\_TGTLI**

Conditions

REMOVED:  
Prohibited when the TGLNA is P.  
ADDED:  
Prohibited when the TGLNA is P or W.

**56\_TGSGNL**

Conditions

REMOVED:  
Prohibited when the TGLNA is P.  
ADDED;  
Prohibited when the TGLNA is P or W.

**57\_DID\_IND**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**64\_TGTLI**

Conditions

REMOVED:  
Prohibited when the TGLNA is P.  
ADDED:  
Prohibited when the TGLNA is P or W.

**65\_TG\_TC\_OPT**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**66\_TG\_TC\_TO\_PRI**

Conditions

REMOVED:  
Prohibited when the TGLNA field is P.  
ADDED;  
Prohibited when the TGLNA field is P or W.

**76\_DBA**

Conditions

REMOVED:  
Prohibited when TGLNA is P.  
ADDED:  
Prohibited when TGLNA is P or W.

**78\_LNUM**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**82\_TKIND**

Conditions

REMOVED:  
Required when ACT is N, C, T, or V, and TGLNA is populated.  
ADDED:  
Required when ACT is N, C, or V, and TGLNA is populated.

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**83\_LTGN**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**84\_ECCKT**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**86\_TC\_OPT**

Conditions

ADDED;  
Prohibited when TGLNA is P or W.

**87\_TC\_TO\_PRI**

Conditions

REMOVED:  
Prohibited when the TGLNA field is P.  
ADDED:  
Prohibited when the TGLNA field is P or W.

**101b\_CABLE\_ID**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**101c\_DIN**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**101i\_IWT**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**101s\_TTP**

Conditions

REMOVED;  
Prohibited when TGLNA is P.  
ADDED:  
Prohibited when TGLNA is P or W.

# FORM: DIGITAL TRUNKING RESALE SERVICE

## 46\_DGOUT

Legend: Modified New Deleted

Conditions

ADDED:

Prohibited when TGLNA is P or W.

## 48\_TGTN

Conditions

ADDED:

Prohibited when TGLNA is P, W or X.

## 51\_GLARE

Conditions

ADDED:

Prohibited when TGLNA is P.

## 52\_PIC\_(TRKS)

Conditions

REMOVED:

Prohibited when TGLNA is D.

ADDED:

Prohibited when TGLNA is D or W.

## 53\_LPIC\_(TRKS)

Conditions

REMOVED:

Prohibited when TGLNA is D.

ADDED:

Prohibited when TGLNA is D or W.

## 55\_TGPULSE

Conditions

ADDED:

Prohibited when TGLNA is P or X.

## 56\_TGSGNL

Conditions

ADDED:

Prohibited when TGLNA is P or X.

## 57\_DID\_IND

Conditions

ADDED:

Prohibited when TGLNA is P or W.

## 62\_DTNR

Conditions

ADDED:

Prohibited when TGLNA is P.

## 65\_CFA\_(TRKS)

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**77\_DBA**

Conditions

ADDED:  
Prohibited when TGLNA is P or X.

**79\_LNUM**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**82\_TNS**

Conditions

ADDED:  
Prohibited when TGLNA is P.

**84\_TKIND**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**85\_LTGN**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**86\_ECCKT**

Conditions

ADDED:  
Prohibited when TGLNA is D, P or W.

**87\_TC\_OPT**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**96\_TERS**

Conditions

ADDED:  
Prohibited when TGLNA is P.

**98\_PIC**

Conditions

ADDED:  
Prohibited when TGLNA is D or W.

**99\_LPIC**

Conditions

ADDED:  
Prohibited when TGLNA is D or W.

**101\_BLOCK**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**101a\_CABLE\_ID**

Conditions

ADDED:  
Prohibited when TGLNA is P.

**101b\_DIN**

Conditions

ADDED:  
Prohibited when TGLNA is P or W.

**101c\_FPI**

Conditions

REMOVED:  
Prohibited when the TGLNA is W.  
ADDED:  
Prohibited when the TGLNA is D or W.

**101e\_IWJK**

Conditions

REMOVED:  
Prohibited when TGLNA is W or P.  
ADDED:  
Prohibited when TGLNA is D, P or W.

**101f\_IWJQ**

Conditions

REMOVED:  
Prohibited when TGLNA is W or P.  
ADDED:  
Prohibited when TGLNA is D, P or W.

**101g\_IWT**

Conditions

ADDED:  
Prohibited when TGLNA is D, P or W.

**101i\_JK\_CODE**

Conditions

REMOVED:  
Prohibited when TGLNA is W or P.  
ADDED:  
Prohibited when TGLNA is D, P or W.

**101j\_JK\_NUM**

Conditions

REMOVED:  
Prohibited when TGLNA is W or P.  
ADDED:  
Prohibited when TGLNA is D, P or W.

## 101k\_JK\_POS

### Conditions

REMOVED:  
 Prohibited when TGLNA is W or P.  
 ADDED:  
 Prohibited when TGLNA is D, P or W.

## 101I\_JR

### Conditions

REMOVED:  
 Prohibited when TGLNA is W or P.  
 ADDED:  
 Prohibited when TGLNA is D, P or W.

# 9-State LSOR Version 10.25 Revision Updates (03/18/17)

## 5c. AT&T Error Codes & Messages

### ADDED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
R9241	SUP INVALID. PREVIOUS VERSION UNRESOLVED

### REVISED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
R5120	REMOVED: PROJECT FIELD MUST BE POPULATED WHEN PORTING 51 OR MORE NUMBERS ADDED: PROJECT FILED MUST BE POPULATED WHEN PORTING 100 OR MORE NUMBERS

### REMOVED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
------------	---------------

None at this time

# FORM: LOCAL SERVICE REQUEST

Legend: Modified New Deleted

## 26\_PROJECT

### Conditions

REMOVED:

Required when REQTYT is C (LNP) and 51 or more telephone numbers are being ported.

ADDED:

Required when REQTYT is C (LNP) and 100 or more telephone numbers are being ported.

### Notes

REMOVED:

Type 1 Wireless Ports over 50 numbers, REQTYT C, must be Project Managed. Contact the AT&T Southeast Project Manager prior to submitting the request.

ADDED:

Type 1 Wireless Ports over 100 numbers, REQTYT C, must be Project Managed. Contact the AT&T Southeast Project Manager prior to submitting the request.

## 37\_SUP

### Conditions

ADDED:

When REQTYT equals C and SUP equals 2 or 3, the previous version of the LSR cannot be in New, Pending or Error status.

# FORM: PORT SERVICE

Legend: Modified New Deleted

## 05\_PQTY

### Usage Matrix

This field is conditional.

	ACTIVITIES										
REQTYT - Product	N	C	D	T	R	V	W	S	B	Y	L
REQTYT F-Port Service	R	R	P			R		R	P		P
REQTYT M-2-Wire ISDN Basic Rate-BRI Digital Port/Loop UNE Combination	<span style="background-color: #FF4500;">CR</span>	<span style="background-color: #90EE90;">CR</span>	P	P	P	<span style="background-color: #90EE90;">CR</span>	P	P	P	P	P

<b>REQTYP M-UNE-P/WLP Bus/Res (Switched Combo Bus/Res)</b>	R	R	P	R	P	R	P	R	P	P	P
<b>REQTYP M-UNE-P/WLP Remote Call Forwarding (RCF Switched)</b>	CR	CR	P	CR	P	CR	P	P	P	P	P

## 09\_LNUM

### Usage Matrix

This field is conditional.

	ACTIVITIES										
<b>REQTYP - Product</b>	N	C	D	T	R	V	W	S	B	Y	L
<b>REQTYP F-Port Service</b>	R	R	P			R		R	P		P
<b>REQTYP M-2-Wire ISDN Basic Rate-BRI Digital Port/Loop UNE Combination</b>	CR	CR	P	P	P	CR	P	P	P	P	P
<b>REQTYP M-UNE-P/WLP Bus/Res (Switched Combo Bus/Res)</b>	R	R	P	R	P	R	P	R	P	P	P
<b>REQTYP M-UNE-P/WLP Remote Call Forwarding (RCF Switched)</b>	CR	CR	P	CR	P	CR	P	P	P	P	P

## 16\_TNS

### Usage Matrix

This field is conditional.

	ACTIVITIES										
<b>REQTYP - Product</b>	N	C	D	T	R	V	W	S	B	Y	L
<b>REQTYP F-Port Service</b>	R	R	P			R		R	P		P
<b>REQTYP M-2-Wire ISDN Basic Rate-BRI Digital Port/Loop UNE Combination</b>	CR	CR	P	P	P	CR	P	P	P	P	P



<b>REQTYP M-UNE-P/WLP Bus/Res (Switched Combo Bus/Res)</b>	R	R	P	R	P	R	P	R	P	P	P
<b>REQTYP M-UNE-P/WLP Remote Call Forwarding (RCF Switched)</b>	CR	CR	P	CR	P	CR	P	P	P	P	P

### 30\_ECCKT

**Conditions**

ADDED:

Required when REQTYP is M and LNA is C or V for 2-Wire ISDN Basic Rate-BRI Digital Port/Loop UNE Combination.

### 74d\_MATN

**Conditions**

ADDED:

Required when LNA is N, P, W or X.

## FORM: RESALE SERVICE

Legend: Modified New Deleted

### 28\_LPIC

**Conditions**

Removed:

Prohibited when LNA is D.

ADDED:

Prohibited when LNA is D or W.

### 30\_TC\_OPT

**Conditions**

REMOVED:

Prohibited when LNA is N, P or B for Resale non-complex.

ADDED:

Prohibited when LNA is N, P, W or B for Resale non-complex.

### 63f\_TC\_FR

**Conditions**

REMOVED:

Prohibited when LNA is D, X, W, L or B.

ADDED:

Prohibited when LNA is D, X, W, L, P or B.

## FORM: RESALE COMPLEX SERVICE

Legend: Modified New Deleted

### 50\_BA

Conditions

ADDED:

Prohibited when LNA is D, P or W.

### 63d\_MATN

Usage Matrix

This field is conditional.

	ACTIVITIES					
REQTYP - Product	N	C	D	T	V	W
REQTYP E-Wide Area Transfer Service (WATS)	CP	CP	P	P	CP	P

### 63e\_SDI

Conditions

Prohibited when LNA is D.

Usage Matrix

This field is conditional.

	ACTIVITIES					
REQTYP - Product	N	C	D	T	V	W
REQTYP E-Wide Area Transfer Service (WATS)	CP	CP	P	P	CP	P

## FORM: CENTREX RESALE SERVICE

### 07\_CB

Conditions

ADDED:

Prohibited when LNA is D.

### 07a\_SNA

Conditions

ADDED:

Prohibited when LNA is D.

### 39\_TERS

Conditions

ADDED:

Legend: Modified New Deleted

Prohibited when LNA is D.

## 61\_FPI

### Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES							
	N	C	D	T	V	W	S	B
REQTYP P-Centrex Service		O	P	O	O	P		
REQTYP P-ESSX Service		CO	P	P	P	P		
REQTYP P-MultiServ/MultiServ PLUS		CO	P	P	CO	P		

## 75ff\_CPG

### Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES							
	N	C	D	T	V	W	S	B
REQTYP P-Centrex Service		O	P	O	O	P		
REQTYP P-ESSX Service		CO	P	P	P	P		
REQTYP P-MultiServ/MultiServ PLUS		CO	P	P	CO	P		

## 75jj\_ST

### Conditions

ADDED:

Prohibited when LNA is D.

## 9-State LSOR Version 10.26 Revision Updates (11/11/17)

### AT&T Error Codes & Messages

#### 5c. AT&T Error Codes & Messages

##### ADDED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
<i>None at this time</i>	

##### REVISED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
<i>None at this time</i>	

##### REMOVED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
------------	---------------

*None at this time*

---

# FORM: LOOP SERVICE

Legend Modified New Deleted

## 10 SLTN

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

## 12 BTRL

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

## 13 CKR

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	OP	P	OP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**14 TSP**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CO	PO	CP	PO	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CO	CO	CP	CO	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CO	CO	CP	CO	P	P	P

**15 TNT**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**18 SAN**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**19 ECCKT**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<i>REQTYP - Product</i>	N	C	D	T	R	V	W
<i>REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)</i>	C	PC	CR	PC	P	P	P
<i>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</i>	C	C	CR	C	P	P	P
<i>REQTYP A-Single Bandwidth Commingling (SBWC)</i>	C	C	CR	C	P	P	P

**23 CFA**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<i>REQTYP - Product</i>	N	C	D	T	R	V	W
<i>REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)</i>	C	PC	CP	PC	P	P	P
<i>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</i>	C	C	CP	C	P	P	P
<i>REQTYP A-Single Bandwidth Commingling (SBWC)</i>	C	C	CP	C	P	P	P



**30 SYSTEM ID**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**31 CTI**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

--	--	--	--	--	--	--	--

### 32 CABLE ID

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	C	PC	CP	PC	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	C	C	CP	C	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	C	C	CP	C	P	P	P

### 34 CHAN/PAIR

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	C	PC	CP	PC	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	C	C	CP	C	P	P	P

<b>REQTYP A-Single Bandwidth Commingling (SBWC)</b>	C	C	CP	C	P	P	P

### 35 RELAY RACK

Usage Matrix

This field is conditional.

	ACTIVITIES						
<b>REQTYP - Product</b>	N	C	D	T	R	V	W
<b>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</b>	CP	P	CP	P	P	P	P
<b>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</b>	CP	CP	CP	CP	P	P	P
<b>REQTYP A-Single Bandwidth Commingling (SBWC)</b>	CP	CP	CP	CP	P	P	P

### 36 SHELF

Usage Matrix

This field is conditional.

	ACTIVITIES						
<b>REQTYP - Product</b>	N	C	D	T	R	V	W
<b>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</b>	CP	P	CP	P	P	P	P
<b>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</b>	CP	CP	CP	CP	P	P	P

<b>REQTYP A-Single Bandwidth Commingling (SBWC)</b>	CP	CP	CP	CP	P	P	P

**37 SLOT**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<b>REQTYP - Product</b>	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>R</b>	<b>V</b>	<b>W</b>
<b>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</b>	CP	P	CP	P	P	P	P
<b>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</b>	CP	CP	CP	CP	P	P	P
<b>REQTYP A-Single Bandwidth Commingling (SBWC)</b>	CP	CP	CP	CP	P	P	P

**40 JK CODE**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<b>REQTYP - Product</b>	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>R</b>	<b>V</b>	<b>W</b>
<b>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</b>	C	PC	CP	PC	P	P	P

<b>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</b>	C	C	CP	C	P	P	P

**41 JK NUM**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<b>REQTYP - Product</b>	N	C	D	T	R	V	W
<b>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</b>	C	PC	CP	PC	P	P	P
<b>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</b>	C	C	CP	C	P	P	P

**42 JK POS**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<b>REQTYP - Product</b>	N	C	D	T	R	V	W
<b>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</b>	C	PC	CP	PC	P	P	P
<b>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</b>	C	C	CP	C	P	P	P

**43 JR**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CO	PC	CP	PO	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CO	C	CP	C	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CO	C	CP	CO	P	P	P

**44 IWT**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled-Ordinarily Combined UNEs (OCU)	C	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	C	C	CP	P	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	C	C	CP	C	P	P	P

**45 NIDR**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CO	PC	CP	PO	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CO	C	CP	CO	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CO	C	CP	CO	P	P	P

**46 IWJK**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	C	PC	CP	PC	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	C	C	CP	C	P	P	P

**47 IWJQ**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<i>REQTYP - Product</i>	N	C	D	T	R	V	W
<i>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</i>	C	PC	CP	PC	P	P	P
<i>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</i>	C	PC	CP	C	P	P	P

**48 DISC NBR**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<i>REQTYP - Product</i>	N	C	D	T	R	V	W
<i>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</i>	CP	P	CP	P	P	P	P
<i>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</i>	CP	CP	CP	CP	P	P	P
<i>REQTYP A-Single Bandwidth Commingling (SBWC)</i>	CP	CP	CP	CP	P	P	P

**50 TC OPT**

Usage Matrix

This field is conditional.

	ACTIVITIES
--	------------



REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**51 TC TO PRI**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**52 TC TO SEC**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**53 TCID**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**54 TC NAME**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**55 TC PER**

Usage Matrix

This field is conditional.

	ACTIVITIES						
REQTYP - Product	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**58d CHAN/PAIR2**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	C	PC	CP	PC	P	P	P
REQTYP A-EELs-4w VG	PC	PC	P	PC	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	C	C	CP	C	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	C	C	CP	C	P	P	P

**58e CMA**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P

**58f IWTQ**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	CP	CP	CP	CP	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

**58g SCFA**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES						
	N	C	D	T	R	V	W
REQTYP A- Commingled- Ordinarily Combined UNEs (OCU)	CP	P	CP	P	P	P	P
REQTYP A-Ordinarily Combined UNEs (OCU) and EELs	C	C	CP	C	P	P	P
REQTYP A-Single Bandwidth Commingling (SBWC)	CP	CP	CP	CP	P	P	P

--	--	--	--	--	--	--	--

**58h TC FR**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<i>REQTYP - Product</i>	N	C	D	T	R	V	W
<i>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</i>	P	P	P	CP	P	P	P
<i>REQTYP A-Single Bandwidth Commingling (SBWC)</i>	P	P	P	CP	P	P	P

**58i TER**

Usage Matrix

This field is conditional.

	ACTIVITIES						
<i>REQTYP - Product</i>	N	C	D	T	R	V	W
<i>REQTYP A-Commingled-Ordinarily Combined UNEs (OCU)</i>	CP	P	CP	P	P	P	P
<i>REQTYP A-Ordinarily Combined UNEs (OCU) and EELs</i>	CP	CP	CP	CP	P	P	P
<i>REQTYP A-Single Bandwidth Commingling (SBWC)</i>	CP	CP	CP	CP	P	P	P

# FORM: RESALE PRIVATE LINE

Legend Modified New Deleted

## 15 SANO

### Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
REQTYP K-Asynchronous Transfer Mode (ATM) Technology	R	R	P	R	R	P
REQTYP K-Dedicated Ethernet	R	C	P	R	C	P
REQTYP K-Frame Relay (Fast Packet Services)	R	R	P	R	R	P
REQTYP K-LIGHTGATE	R	C	P	P	C	P
REQTYP K-MegaLink Service	R	C	P	R	C	P
REQTYP K-Metro Ethernet	CR	C	P	P	C	P
REQTYP K-Native Mode LAN Interconnection (NMLI)	P	C	P	P	C	P
REQTYP K-Private Line	CR	C	P	C	C	P
REQTYP K-Resale Service (TIE Lines)	CR	C	P	C	C	P
REQTYP K-SMARTRing Service	R	C	P	P	C	P
REQTYP K-SynchroNet Service	CR	C	P	C	C	P

## 16 SASF

### Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
REQTYP K-Asynchronous Transfer Mode (ATM) Technology	OC	OC	P	OC	OC	P

<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	C	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**17 SASD**  
Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>V</b>	<b>W</b>
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	C	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P



<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**18 SASN**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	R	RC	P	R	R	P
<b>REQTYP K-Dedicated Ethernet</b>	R	C	P	R	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	R	RC	P	R	R	P
<b>REQTYP K-LIGHTGATE</b>	R	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	R	C	P	R	C	P
<b>REQTYP K-Metro Ethernet</b>	CR	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CR	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CR	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	R	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	CR	C	P	C	C	P

**19 SATH**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W

<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	OC	OC	P	O	OC	P
<b>REQTYP K-Dedicated Ethernet</b>	RC	C	P	RC	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	RC	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	RC	C	P	RC	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	RC	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**20 SASS**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	C	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P

<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**41 ACC**  
Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>V</b>	<b>W</b>
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	C	C	P	C	C	P
<b>REQTYP K-Dedicated Ethernet</b>	R	C	P	R	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	C	C	P	C	RC	P
<b>REQTYP K-LIGHTGATE</b>	RC	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	RC	C	P	RC	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	R	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**50 SANO**  
Usage Matrix

This field is conditional.

	ACTIVITIES					
<i>REQTYP - Product</i>	N	C	D	T	V	W
<i>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</i>	R	R	P	R	R	P
<i>REQTYP K-Dedicated Ethernet</i>	R	C	P	R	C	P
<i>REQTYP K-Frame Relay (Fast Packet Services)</i>	R	R	P	R	R	P
<i>REQTYP K-LIGHTGATE</i>	R	C	P	P	C	P
<i>REQTYP K-MegaLink Service</i>	R	C	P	R	C	P
<i>REQTYP K-Metro Ethernet</i>	CR	C	P	P	C	P
<i>REQTYP K-Native Mode LAN Interconnection (NMLI)</i>	P	C	P	P	C	P
<i>REQTYP K-Private Line</i>	CR	C	P	C	C	P
<i>REQTYP K-Resale Service (TIE Lines)</i>	CR	C	P	C	C	P
<i>REQTYP K-SMARTRing Service</i>	R	C	P	P	C	P
<i>REQTYP K-SynchroNet Service</i>	CR	C	P	C	C	P

**51 SASF**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<i>REQTYP - Product</i>	N	C	D	T	V	W
<i>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</i>	OC	OC	P	OC	OC	P
<i>REQTYP K-Dedicated Ethernet</i>	C	C	P	C	C	P
<i>REQTYP K-Frame Relay (Fast Packet Services)</i>	OC	OC	P	OC	OC	P
<i>REQTYP K-LIGHTGATE</i>	C	C	P	P	C	P
<i>REQTYP K-MegaLink Service</i>	C	C	P	C	C	P

<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**52 SASD**

Usage Matrix

This field is conditional.

<b>REQTYP - Product</b>	<b>ACTIVITIES</b>					
	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>V</b>	<b>W</b>
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	C	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**53 SASN**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
REQTYP K-Asynchronous Transfer Mode (ATM) Technology	R	RC	P	R	R	P
REQTYP K-Dedicated Ethernet	R	C	P	R	C	P
REQTYP K-Frame Relay (Fast Packet Services)	R	RC	P	R	R	P
REQTYP K-LIGHTGATE	R	C	P	P	C	P
REQTYP K-MegaLink Service	R	C	P	R	C	P
REQTYP K-Metro Ethernet	CR	C	P	P	C	P
REQTYP K-Native Mode LAN Interconnection (NMLI)	P	C	P	P	C	P
REQTYP K-Private Line	CR	C	P	C	C	P
REQTYP K-Resale Service (TIE Lines)	CR	C	P	C	C	P
REQTYP K-SMARTRing Service	R	C	P	P	C	P
REQTYP K-SynchroNet Service	CR	C	P	C	C	P

**54 SATH**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
REQTYP K-Asynchronous Transfer Mode (ATM) Technology	OC	OC	P	OC	OC	P
REQTYP K-Dedicated Ethernet	RC	C	P	RC	C	P
REQTYP K-Frame Relay (Fast Packet Services)	OC	OC	P	OC	OC	P
REQTYP K-LIGHTGATE	RC	C	P	P	C	P

<b>REQTYP K-MegaLink Service</b>	RC	C	P	RC	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	RC	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**55 SASS**

Usage Matrix

This field is conditional.

<b>REQTYP - Product</b>	<b>ACTIVITIES</b>					
	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>V</b>	<b>W</b>
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	C	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P

<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P
------------------------------------	---	---	---	---	---	---

**69 ACTEL NO**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	C	C	P	C	C	P
<b>REQTYP K-Dedicated Ethernet</b>	R	C	P	R	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	C	C	P	C	RC	P
<b>REQTYP K-LIGHTGATE</b>	RC	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	RC	C	P	RC	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	R	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**71 AACTEL**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P



<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	C	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**72 IWO**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	O	O	P	O	O	P
<b>REQTYP K-Dedicated Ethernet</b>	O	O	P	O	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	O	O	P	O	O	P
<b>REQTYP K-LIGHTGATE</b>	O	O	P	P	O	P
<b>REQTYP K-MegaLink Service</b>	O	O	P	O	O	P
<b>REQTYP K-Metro Ethernet</b>	CO	CO	P	P	CO	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CO	CO	P	CO	CO	P

<b>REQTYP K-SMARTRing Service</b>	O	O	P	P	O	P
<b>REQTYP K-SynchroNet Service</b>	CO	CO	P	CO	CO	P

**76 ACC**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	C	C	P	C	C	P
<b>REQTYP K-Dedicated Ethernet</b>	R	C	P	R	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	C	C	P	C	RC	P
<b>REQTYP K-LIGHTGATE</b>	RC	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	RC	C	P	RC	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	R	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**79 FBI**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	P	P	P	P	OC	P

<b>REQTYP K-Dedicated Ethernet</b>	P	P	P	P	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	P	OC	P	P	OC	P
<b>REQTYP K-LIGHTGATE</b>	P	P	P	P	OC	P
<b>REQTYP K-MegaLink Service</b>	P	P	P	P	OC	P
<b>REQTYP K-Metro Ethernet</b>	CP	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CP	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CP	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	P	P	P	P	O	P
<b>REQTYP K-SynchroNet Service</b>	CP	C	P	C	C	P

**092 DNUM**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>V</b>	<b>W</b>
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	P	P	P	P	P	P
<b>REQTYP K-Dedicated Ethernet</b>	P	P	P	P	P	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	P	OC	P	P	P	P
<b>REQTYP K-LIGHTGATE</b>	P	P	P	P	P	P
<b>REQTYP K-MegaLink Service</b>	P	P	P	P	P	P
<b>REQTYP K-Metro Ethernet</b>	CP	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CP	C	P	C	C	P

<b>REQTYP K-Resale Service (TIE Lines)</b>	CP	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	P	P	P	P	P	P
<b>REQTYP K-SynchroNet Service</b>	CP	C	P	C	C	P

**93 DISC ECCKT**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	P	P	P	P	P	P
<b>REQTYP K-Dedicated Ethernet</b>	P	C	P	P	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	P	C	P	P	P	P
<b>REQTYP K-LIGHTGATE</b>	P	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	P	C	P	P	C	P
<b>REQTYP K-Metro Ethernet</b>	CP	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CP	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CP	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	P	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	CP	C	P	C	C	P

**94 REMARKS**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W

<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	O	O	P	O	P	P
<b>REQTYP K-Dedicated Ethernet</b>	O	O	P	O	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	O	O	P	O	O	P
<b>REQTYP K-LIGHTGATE</b>	R	R	P	P	R	P
<b>REQTYP K-MegaLink Service</b>	OR	OR	P	OR	OR	P
<b>REQTYP K-Metro Ethernet</b>	CO	CO	P	P	CO	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	CO	P	P	CO	P
<b>REQTYP K-Private Line</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-SMARTRing Service</b>	R	R	P	P	R	P
<b>REQTYP K-SynchroNet Service</b>	CO	CO	P	CO	CO	P

**96a CKTA**

Usage Matrix

This field is conditional.

<b>REQTYP - Product</b>	<b>ACTIVITIES</b>					
	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>V</b>	<b>W</b>
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	R	R	P	R	R	P
<b>REQTYP K-Dedicated Ethernet</b>	R	R	P	R	R	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	R	R	P	R	R	P
<b>REQTYP K-LIGHTGATE</b>	R	R	P	P	R	P
<b>REQTYP K-MegaLink Service</b>	R	R	P	R	R	P
<b>REQTYP K-Metro Ethernet</b>	CR	CR	P	P	CR	P

<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	CR	P	P	CR	P
<b>REQTYP K-Private Line</b>	CR	CR	P	CR	CR	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CR	CR	P	CR	CR	P
<b>REQTYP K-SMARTRing Service</b>	R	R	P	P	R	P
<b>REQTYP K-SynchroNet Service</b>	CR	CR	P	CR	CR	P

**96b SVC CD**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	P	P	P	P	P	P
<b>REQTYP K-Dedicated Ethernet</b>	P	C	P	P	P	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	P	P	P	P	P	P
<b>REQTYP K-LIGHTGATE</b>	P	C	P	P	P	P
<b>REQTYP K-MegaLink Service</b>	P	C	P	P	P	P
<b>REQTYP K-Metro Ethernet</b>	CP	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CP	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CP	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	P	C	P	P	P	P
<b>REQTYP K-SynchroNet Service</b>	CP	C	P	C	C	P

**96c MTP**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
REQTYP K-Asynchronous Transfer Mode (ATM) Technology	OC	OC	P	OC	P	P
REQTYP K-Dedicated Ethernet	P	P	P	P	P	P
REQTYP K-Frame Relay (Fast Packet Services)	OC	P	P	OC	P	P
REQTYP K-LIGHTGATE	P	P	P	P	P	P
REQTYP K-MegaLink Service	P	P	P	P	P	P
REQTYP K-Metro Ethernet	C	C	P	P	C	P
REQTYP K-Native Mode LAN Interconnection (NMLI)	P	C	P	P	C	P
REQTYP K-Private Line	C	C	P	C	C	P
REQTYP K-Resale Service (TIE Lines)	C	C	P	C	C	P
REQTYP K-SMARTRing Service	P	P	P	P	P	P
REQTYP K-SynchroNet Service	C	C	P	C	C	P

**96e CKTTYP**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
REQTYP K-Asynchronous Transfer Mode (ATM) Technology	R	R	P	R	OR	P
REQTYP K-Dedicated Ethernet	R	R	P	R	R	P
REQTYP K-Frame Relay (Fast Packet Services)	R	OR	P	R	OR	P
REQTYP K-LIGHTGATE	R	R	P	P	R	P
REQTYP K-MegaLink Service	R	R	P	R	R	P

<b>REQTYP K-Metro Ethernet</b>	R	R	P	P	R	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	R	P	P	R	P
<b>REQTYP K-Private Line</b>	R	R	P	R	R	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	R	R	P	R	R	P
<b>REQTYP K-SMARTRing Service</b>	R	R	P	P	R	P
<b>REQTYP K-SynchroNet Service</b>	R	R	P	R	R	P

**103 JR**

Usage Matrix

This field is conditional.

	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP - Product</b>						
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OC	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	C	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**117 FA**



Usage Matrix

This field is conditional.

	ACTIVITIES					
<i>REQTYP - Product</i>	N	C	D	T	V	W
<i>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</i>	OR	OC	P	OC	OC	P
<i>REQTYP K-Dedicated Ethernet</i>	R	C	P	RC	C	P
<i>REQTYP K-Frame Relay (Fast Packet Services)</i>	OR	OC	P	OC	OC	P
<i>REQTYP K-LIGHTGATE</i>	R	C	P	P	C	P
<i>REQTYP K-MegaLink Service</i>	R	C	P	RC	C	P
<i>REQTYP K-Metro Ethernet</i>	CR	C	P	P	C	P
<i>REQTYP K-Native Mode LAN Interconnection (NMLI)</i>	P	C	P	P	C	P
<i>REQTYP K-Private Line</i>	CR	C	P	C	C	P
<i>REQTYP K-Resale Service (TIE Lines)</i>	CR	C	P	C	C	P
<i>REQTYP K-SMARTRing Service</i>	R	C	P	P	C	P
<i>REQTYP K-SynchroNet Service</i>	CR	C	P	C	C	P

**118 FEATURE**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<i>REQTYP - Product</i>	N	C	D	T	V	W
<i>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</i>	C	C	P	C	C	P
<i>REQTYP K-Dedicated Ethernet</i>	RC	C	P	RC	C	P
<i>REQTYP K-Frame Relay (Fast Packet Services)</i>	C	C	P	C	C	P
<i>REQTYP K-LIGHTGATE</i>	C	C	P	P	C	P

<b>REQTYP K-MegaLink Service</b>	RC	C	P	RC	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

## 119 FEATURE DETAIL

### Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Dedicated Ethernet</b>	O	O	P	O	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-LIGHTGATE</b>	P	O	P	P	O	P
<b>REQTYP K-MegaLink Service</b>	O	O	P	O	O	P
<b>REQTYP K-Metro Ethernet</b>	CO	CO	P	P	CO	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-SMARTRing Service</b>	P	O	P	P	O	P

<b>REQTYP K-SynchroNet Service</b>	CO	CO	P	CO	CO	P
------------------------------------	----	----	---	----	----	---

**126 JR**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-LIGHTGATE</b>	C	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	C	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

**140 FA**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	OR	CO	P	CO	CO	P
<b>REQTYP K-Dedicated Ethernet</b>	R	C	P	R	C	P

<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	OR	OC	P	OC	OC	P
<b>REQTYP K-LIGHTGATE</b>	R	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	R	C	P	RC	C	P
<b>REQTYP K-Metro Ethernet</b>	CR	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CR	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CR	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	R	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	CR	C	P	C	C	P

**141 FEATURE**

Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	C	C	P	C	C	P
<b>REQTYP K-Dedicated Ethernet</b>	C	C	P	C	C	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	C	C	P	C	C	P
<b>REQTYP K-LIGHTGATE</b>	RC	C	P	P	C	P
<b>REQTYP K-MegaLink Service</b>	C	C	P	C	C	P
<b>REQTYP K-Metro Ethernet</b>	C	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	C	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	C	C	P	C	C	P

<b>REQTYP K-SMARTRing Service</b>	RC	C	P	P	C	P
<b>REQTYP K-SynchroNet Service</b>	C	C	P	C	C	P

## 142 FEATURE DETAIL

### Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Dedicated Ethernet</b>	O	O	P	O	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-LIGHTGATE</b>	P	CO	P	P	CO	P
<b>REQTYP K-MegaLink Service</b>	O	O	P	O	O	P
<b>REQTYP K-Metro Ethernet</b>	CO	CO	P	P	CO	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-SMARTRing Service</b>	P	O	P	P	O	P
<b>REQTYP K-SynchroNet Service</b>	CO	CO	P	CO	CO	P

## 142g FRF

### Usage Matrix

This field is conditional.

REQTYP - Product	ACTIVITIES					
	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	P	P	P	P	P	P

<b>REQTYP K-Dedicated Ethernet</b>	R	O	P	R	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	P	P	P	P	P	P
<b>REQTYP K-LIGHTGATE</b>	P	OC	P	P	OC	P
<b>REQTYP K-MegaLink Service</b>	R	OC	P	RC	OC	P
<b>REQTYP K-Metro Ethernet</b>	CR	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CR	C	P	C	C	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CR	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	P	O	P	P	O	P
<b>REQTYP K-SynchroNet Service</b>	CR	C	P	C	C	P

**142t LC**  
Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	<b>N</b>	<b>C</b>	<b>D</b>	<b>T</b>	<b>V</b>	<b>W</b>
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	P	P	P	P	P	P
<b>REQTYP K-Dedicated Ethernet</b>	R	O	P	R	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	P	P	P	P	P	P
<b>REQTYP K-LIGHTGATE</b>	P	OC	P	P	OC	P
<b>REQTYP K-MegaLink Service</b>	R	OC	P	R	OC	P
<b>REQTYP K-Metro Ethernet</b>	CR	C	P	P	C	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	C	P	P	C	P
<b>REQTYP K-Private Line</b>	CR	C	P	C	C	P

<b>REQTYP K-Resale Service (TIE Lines)</b>	CR	C	P	C	C	P
<b>REQTYP K-SMARTRing Service</b>	P	O	P	P	O	P
<b>REQTYP K-SynchroNet Service</b>	CR	C	P	C	C	P

**142u LCON TEL NO**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W
<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	P	P	P	P	P	P
<b>REQTYP K-Dedicated Ethernet</b>	O	O	P	O	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	P	P	P	P	P	P
<b>REQTYP K-LIGHTGATE</b>	O	O	P	P	O	P
<b>REQTYP K-MegaLink Service</b>	O	O	P	O	O	P
<b>REQTYP K-Metro Ethernet</b>	CO	CO	P	P	CO	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	CO	P	P	CO	P
<b>REQTYP K-Private Line</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-SMARTRing Service</b>	O	O	P	P	O	P
<b>REQTYP K-SynchroNet Service</b>	CO	CO	P	CO	CO	P

**142v LCON TEL NO**

Usage Matrix

This field is conditional.

	ACTIVITIES					
<b>REQTYP - Product</b>	N	C	D	T	V	W

<b>REQTYP K-Asynchronous Transfer Mode (ATM) Technology</b>	P	P	P	P	P	P
<b>REQTYP K-Dedicated Ethernet</b>	O	O	P	O	O	P
<b>REQTYP K-Frame Relay (Fast Packet Services)</b>	P	P	P	P	P	P
<b>REQTYP K-LIGHTGATE</b>	O	O	P	P	O	P
<b>REQTYP K-MegaLink Service</b>	O	O	P	O	O	P
<b>REQTYP K-Metro Ethernet</b>	CO	CO	P	P	CO	P
<b>REQTYP K-Native Mode LAN Interconnection (NMLI)</b>	P	CO	P	P	CO	P
<b>REQTYP K-Private Line</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-Resale Service (TIE Lines)</b>	CO	CO	P	CO	CO	P
<b>REQTYP K-SynchroNet Service</b>	CO	CO	P	CO	CO	P

## 9-State LSOR Version 10.27 Revision Updates (03/17/18)

### AT&T Error Codes & Messages

#### 5c. AT&T Error Codes & Messages

##### ADDED ERROR CODES & MESSAGES

ERROR CODE	ERROR MESSAGE
None at this time	

##### REVISED ERROR CODES & MESSAGES



ERROR CODE	ERROR MESSAGE
<i>None at this time</i>	

**REMOVED ERROR CODES & MESSAGES**

ERROR CODE	ERROR MESSAGE
<i>None at this time</i>	