
BellSouth Business Markets

675 West Peachtree Street
Atlanta, Georgia 30375

**Carrier Notification
SN91085191**

Date: June 30, 2006

To: Competitive Local Exchange Carriers (CLEC)

Subject: CLECs – (Documentation/Guides Interconnection/Contractual) – **REVISED** - Update to CLEC Information Packages for Final Phase of Triennial Review Order Commingling Requirement (Originally posted on September 30, 2005)

This is to advise that on September 30, 2005, BellSouth updated its CLEC Information Packages to reflect the final phase of the Federal Communications Commission's (FCC) Triennial Review Order (TRO) commingling requirement. This phase will include commingled Switched Access entrance facilities as well as commingling a single bandwidth circuit. Any commingling applications that were not incorporated within the planning for this phase should be addressed through the Bona Fide Request (BFR) process. **Also, Commingling is only available for REQ TYP A. The commingling application field has been added to the Manual LSOG6 LS-Loop Service Form (RF#3904), and can be found on the BellSouth Interconnection Services Web site at:**

http://interconnection.bellsouth.com/tools_forms_and_reports/forms/webforms/lzog6/index.html

The following CLEC Information Packages listed below have been updated:

Unbundled Dedicated Transport – Currently Combined UNE Combinations
Unbundled Dedicated Transport – Ordinarily Combined UNE Combinations
Unbundled Dedicated Transport – UNEs
Unbundled Dedicated Transport – Unbundled Dark Fiber

These documents may be found on the BellSouth Interconnection Services Web site at:

<http://www.interconnection.bellsouth.com/guides/html/unes.html>

In addition, the attached support information for ordering purposes **was** included in the BellSouth Local Ordering Handbook (LOH), **implemented on** November 4, 2005.

If you have any questions, please contact your BellSouth local support manager.

Sincerely,

ORIGINAL SIGNED BY KRISTEN E. SHORE

Kristen E. Shore – Director
BellSouth Business Markets

Attachments

Single Bandwidth Commingling (SBWC)

Single Bandwidth Commingling is a combination of wholesale tariff and UNE (Unbundled Network Element)

Product Listing

Single Bandwidth Commingling is a combination of Unbundled Dedicated Transport and Special Access: which includes interoffice channel, Local Channel, and Loops, with or without multiplexing functionality (Channelization). The Local Channel must always be Special Access.

This offering is intended to provide connectivity from end user locations (EU) and serving wire centers to the CLEC(s) collocated point of presence or to a Non-collocated exchange and exchange access.

Availability:

Available in all 9 states (Alabama, Florida, Georgia, Kentucky, Louisiana, Mississippi, North Carolina, South Carolina, and Tennessee)

Restrictions:

- DS1 and above loop transport must go to collocation.
- These products must be negotiated in the CLEC Interoffice Agreement (New or Amended contract).

LSR Restrictions:

When ordering a combination of elements with the **same service level** the Single Bandwidth Commingled should be ordered on the same LSR.

When ordering a combination of elements with **different service levels** the Single Bandwidth Commingled must be submitted on different LSR(s).

When the Single Bandwidth Commingled is riding a higher-level service, the higher level service must be installed prior to ordering the Single Bandwidth Commingled (e.g., Single Bandwidth Commingled is a 64 kbps circuit riding a DS1 circuit), the DS1 circuit identification along with the designated “channel of slot” number *must* be identified in the CFA field on the LSR for the 64 kbps Single Bandwidth Commingled order.

Conversions:

Single Tariff conversions, or conversion spread sheets are submitted using ACT of C. Tariff conversions must be submitted to the CLEC Local Support Manager (LSM). Tariff conversions are handled like a switch-as-is request. The CLEC will not be allowed to change the service configuration of the circuit during the conversion. Refer to the appropriate BellSouth® Local Support Manager (LSM) for additional information regarding the Tariff conversion process for SBWC service.

Basic Service Features:

Dedicated Transport - provides dedicated point to point to a single customer. Dedicated Transport consists of four (4) possible network elements, Local Channel (LC), Interoffice Channel (IOC), Unbundled Local Loop (LL) and Channelization (MUX).

- **Local Channel** - provides a dedicated point-to-point transmission path and it's associated electronics between the Non-located Point of Presence (POP) and the POP Serving Wire Center (POP SWC). This element must be Special Access.
- **Interoffice Channel** - provides a dedicated point-to-point transmission path and it's associated electronics between the POP and End User Serving Wire Centers (SWC).
- **Local Loop** - provides a dedicated point-to-point transmission path and the associated electronics between the end user's (EU) premises and the end user's SWC (EU SWC).
- **Channelization** - provides a multiplexing function when a higher capacity level of service is separated to deliver service at a lower capacity level. Channelization is accomplished through the use of a multiplexer. When the high capacity level of service is channelized, a (MUX) will apply. When the lower capacity level of service is connected to a MUX, a Central Office Channel Interface (COCI) will apply. Lower level services "ride" the channelized facility. A multiplexer (MUX) can be located in the POP SWC, the end user's SWC, or in a remote Central Office (CO).

NOTE: Channelization equipment is not placed on a customer's premise for these services.

Ordering Forms/Screens

The following chart illustrates the required, conditional and optional forms/screens for ordering this service. Detailed information will follow to assist you in filling out each of these forms/screens.

Forms/Screens Single Bandwidth Commingling (SBWC)
R = Required C = Conditional O = Optional

Combinations offered at different service levels must be ordered on separate LSR's. Service Inquiries are required on all DS3/STS-1 and all Channelized Services. End User form is not required with Channelized Services.

Service Inquiry Form Instructions

Service Inquiry begins when the CLEC sends the completed SI and LSR forms to the UNE CRSG. The UNE CRSG will add information to the SI and forward it to Network. Network will check for available facilities, and if facilities are available, will add the appropriate information to the SI before returning it to the UNE CRSG. The UNE CRSG will then submit both the completed SI and the LSR to the LCSC who will process for order issuance.

NOTE: A separate SI is required for each unique A and Z combination. A separate SI is required for each level of service even if they have the same A and Z combination; do not mix speeds on the same SI.

Completing the DL Form/Screen

If directory listings are required, refer to **REQTYP J** for more information on completing the DL form/screen.

Completing the LSR and EU Forms/Screens

Account level activities (ACT) apply to the entire account. A complete list of ACTs and their definition can be found in the Data Dictionary entry for ACT.

The following chart shows all of the valid account level activities for this service.

Valid Account Level Activities Single Bandwith Commingling (SBWC)										
N	C	D	T	R	V	S	B	W	L	Y
X	X	X	X	-	-	-	-	-	-	-
Note: "X" denotes valid account level activities. A dash (-) indicates a non-valid account level activity.										

The Required, Conditional and Optional (R/C/O) fields on the LSR and EU forms/screens will be given for every valid ACT code in the **ACT Tables** section.

Completing the LS Form/Screen

The Loop Service (LS) form/screen may be required or invalid depending on the account level activity. Each account level activity has valid Line Level Activities (LNAs). These LNAs determine how, or if, the LS form/screen should be populated. A complete list of LNAs and their definition can be found in the Data Dictionary entry for LNA.

The following chart gives the valid LNAs for each account level activity (ACT) and the associated LS form/screen usage for this service.

If ACT is:	Then LNA is:	And LS form is:
N	N	Required
C	C	Required
D	D	Required
T	N	Required

The Required, Conditional and Optional (R/C/O) fields for the Loop Service (LS) form/screen are listed according to the Line Level Activity (LNA) in the **LNA Tables** Section

Single Bandwidth Commingling (SBWC) RCO Tables

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored.

Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the Data Dictionary for clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqtyp A, SBWC

ACT= C: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
SPEC (M)	TOS (M)	

Conditional

AI (M)	APOT (M)	BI1 (M)
CUST (M)	DSGCON (M)	DSGCON-CITY (M)
DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)	DSGCON-ROOM/MAIL STOP (M)
DSGCON-STATE (M)	DSGCON-STREET (M)	DSGCON-TEL NO. (M)
DSGCON-ZIP CODE (M)	LSO (M)	NOR (M)
RPON (M)	SUP (M)	VER (M)

Optional

DRC* (M)	EXP (M)	PROJECT (M)
REMARKS (M)	RORD (M)	SCA (M)

ACT Tables: Reqtvp A, SBWC

ACT= C: EU

Required

AN (M)	CITY (M)	NAME (M)
PG_OF_ (M)	PON (M)	SASN (M)
STATE (M)	ZIP (M)	

Conditional

AAI (M)	ACC (M)	EAN
LD1 (M)	LD2 (M)	LD3 (M)
LV1 (M)	LV2 (M)	LV3 (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

LCON-NAME (M)	LCON-TEL NO. (M)	
---------------	------------------	--

ACT= D: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	NC (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	SPEC (M)	TOS (M)

Conditional

CUST (M)	LSO (M)	NOR (M)
RPON (M)	SUP (M)	VER (M)

Optional

PROJECT (M)	REMARKS (M)	RORD (M)
-------------	-------------	----------

ACT= D: EU

Required

AN (M)	NAME (M)	PG_OF_ (M)
PON (M)		

ACT Tables: Reqtvp A, SBWC

Conditional

VER (M)

ACT= N: LSR

Required

ACNA (M)

AN (M)

CCNA (M)

IMPCON (M)

INIT-FAX NO. (M)

NCI (M)

REQTYP (M)

SPEC (M)

ACT (M)

BAN1 (M)

D/TSENT (M)

IMPCON-TEL NO. (M)

INIT-TEL NO. (M)

PG_OF_ (M)

SC (M)

TOS (M)

ACTL (M)

CC (M)

DDD (M)

INIT (M)

NC (M)

PON (M)

SECNCI (M)

Conditional

AI (M)

CUST (M)

DSGCON-FAX NO. (M)

DSGCON-STATE (M)

DSGCON-ZIP CODE (M)

PROJECT (M)

VER (M)

APOT (M)

DSGCON (M)

DSGCON-FLOOR (M)

DSGCON-STREET (M)

LSO (M)

RPON (M)

BI1 (M)

DSGCON-CITY (M)

DSGCON-ROOM/MAIL STOP (M)

DSGCON-TEL NO. (M)

NOR (M)

SUP (M)

Optional

DRC* (M)

RORD (M)

EXP (M)

REMARKS (M)

ACT= N: EU

Required

AN (M)

PG_OF_ (M)

STATE (M)

CITY (M)

PON (M)

ZIP (M)

NAME (M)

SASN (M)

ACT Tables: Reqtvp A, SBWC

Conditional

AAI (M)	ACC (M)	IWBAN (M)
IWCON (M)	IWCON-TEL NO. (M)	LD1 (M)
LD2 (M)	LD3 (M)	LV1 (M)
LV2 (M)	LV3 (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)		

ACT= T: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
SPEC (M)	TOS (M)	

Conditional

AI (M)	APOT (M)	BI1 (M)
CUST (M)	DSGCON (M)	DSGCON-CITY (M)
DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)	DSGCON-ROOM/MAIL STOP (M)
DSGCON-STATE (M)	DSGCON-STREET (M)	DSGCON-TEL NO. (M)
DSGCON-ZIP CODE (M)	LSO (M)	NOR (M)
PROJECT (M)	RPON (M)	SUP (M)
VER (M)		

Optional

DRC* (M)	EXP (M)	REMARKS (M)
RORD (M)		

ACT Tables: Reqtvp A, SBWC

ACT= T: EU

Required

AN (M)	CITY (M)	NAME (M)
PG_OF_ (M)	PON (M)	SASN (M)
STATE (M)	ZIP (M)	

Conditional

AAI (M)	ACC (M)	IWBAN (M)
IWCON (M)	IWCON-TEL NO. (M)	LD1 (M)
LD2 (M)	LD3 (M)	LV1 (M)
LV2 (M)	LV3 (M)	SANO (M)
SASD (M)	SASF (M)	SASS (M)
SATH (M)	VER (M)	

Optional

IWO* (M)	LCON-NAME (M)	LCON-TEL NO. (M)
REMARKS (M)		

LNA Tables: Reqtvp A, SBWC 2w ISDN-BRI

LNA= C: LS

Required

AN (M)	CABLE ID (M)	CHAN/PAIR (M)
LNA (M)	LNUM (M)	LQTY (M)
PG_OF_ (M)	PON (M)	CMA (M)

Conditional

VER (M)

Optional

ECCKT (M)	REMARKS (M)	TSP (M)
-----------	-------------	---------

LNA= D: LS

Required

AN (M)	ECCKT (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

VER (M)

LNA= N: LS

Required

AN (M)	CABLE ID (M)	CHAN/PAIR (M)
LNA (M)	LNUM (M)	LQTY (M)
PG_OF_ (M)	PON (M)	CMA (M)

Conditional

ECCKT (M)	IWJK (M)	IWJQ (M)
JK CODE (M)	JK NUM (M)	JK POS (M)
REMARKS (M)	VER (M)	

Optional

JR* (M)	NIDR* (M)	TSP (M)
---------	-----------	---------

LNA Tables: Reqtvp A, SBWC 2w Voice Grade

LNA= C: LS

Required

AN (M)	CABLE ID (M)	CHAN/PAIR (M)
LNA (M)	LNUM (M)	LQTY (M)
PG_OF_ (M)	PON (M)	CMA (M)

Conditional

VER (M)

Optional

ECCKT (M)	REMARKS (M)	TSP (M)
-----------	-------------	---------

LNA= D: LS

Required

AN (M)	ECCKT (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

VER (M)

LNA= N: LS

Required

AN (M)	CABLE ID (M)	CHAN/PAIR (M)
LNA (M)	LNUM (M)	LQTY (M)
PG_OF_ (M)	PON (M)	CMA (M)

Conditional

ECCKT (M)	IWJK (M)	IWJQ (M)
JK CODE (M)	JK NUM (M)	JK POS (M)
REMARKS (M)	VER (M)	

Optional

JR* (M)	NIDR* (M)	TSP (M)
---------	-----------	---------

LNA Tables: Reqtvp A, SBWC 4w Voice Grade

LNA= C: LS

Required

AN (M)	CABLE ID (M)	CHAN/PAIR (M)
CHAN/PAIR 2 (M)	LNA (M)	LNUM (M)
LQTY (M)	PG_OF_ (M)	PON (M)

CMA (M)

Conditional

VER (M)

Optional

ECCKT (M)	REMARKS (M)	TSP (M)
-----------	-------------	---------

LNA= D: LS

Required

AN (M)	ECCKT (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

VER (M)

LNA= N: LS

Required

AN (M)	CABLE ID (M)	CHAN/PAIR (M)
CHAN/PAIR 2 (M)	LNA (M)	LNUM (M)
LQTY (M)	PG_OF_ (M)	PON (M)

CMA (M)

Conditional

ECCKT (M)	IWJK (M)	IWJQ (M)
JK CODE (M)	JK NUM (M)	JK POS (M)
REMARKS (M)	VER (M)	

Optional

JR* (M)	NIDR* (M)	TSP (M)
---------	-----------	---------

LNA Tables: Reqtvp A, SBWC 56 / 64 kbps

LNA= C: LS

Required

AN (M)	CABLE ID (M)	CHAN/PAIR (M)
CHAN/PAIR 2 (M)	LNA (M)	LNUM (M)
LQTY (M)	PG_OF_ (M)	PON (M)

CMA (M)

Conditional

VER (M)

Optional

ECCKT (M)	REMARKS (M)	TSP (M)
-----------	-------------	---------

LNA= D: LS

Required

AN (M)	ECCKT (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

VER (M)

LNA= N: LS

Required

AN (M)	CABLE ID (M)	CHAN/PAIR (M)
CHAN/PAIR 2 (M)	LNA (M)	LNUM (M)
LQTY (M)	PG_OF_ (M)	PON (M)

CMA (M)

Conditional

ECCKT (M)	JK CODE (M)	JK NUM (M)
JK POS (M)	REMARKS (M)	VER (M)

Optional

NIDR* (M)	TSP (M)
-----------	---------

LNA Tables: Reqtvp A, SBWC DS-1

LNA= C: LS

Required

AN (M)	CFA (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

VER (M)

Optional

ECCKT (M)	REMARKS (M)	TSP (M)
-----------	-------------	---------

LNA= D: LS

Required

AN (M)	ECCKT (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

VER (M)

LNA= N: LS

Required

AN (M)	CFA (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

ECCKT (M)	IWJK (M)	IWJQ (M)
JK CODE (M)	JK NUM (M)	JK POS (M)
REMARKS (M)	VER (M)	

Optional

JR* (M)	NIDR* (M)	TSP (M)
---------	-----------	---------

LNA Tables: Reqtvp A, SBWC DS-3/STS-1

LNA= C: LS

Required

AN (M)	CFA (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

VER (M)

Optional

ECCKT (M)	REMARKS (M)	TSP (M)
-----------	-------------	---------

LNA= D: LS

Required

AN (M)	ECCKT (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

VER (M)

LNA= N: LS

Required

AN (M)	CFA (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)	CMA (M)	

Conditional

ECCKT (M)	IWJK (M)	IWJQ (M)
JK CODE (M)	JK NUM (M)	JK POS (M)
VER (M)		

Optional

JR* (M)	NIDR* (M)	REMARKS (M)
TSP (M)		

TOS

Type of Service
LSR Form / Screen
LSOG6 / ELMS6

Definition

Identifies the type of service for the line ordered.

Definition Notes

Note 1: The type of service identifies the end user account as business, residential or government.

Valid Entries

1st Character (type)

1 = Business
2 = Residence
3 = Government
4 = Coin

2nd Character (product)

A = Multi-Line (Not Applicable for Complex Service.)
B = Single Line (Not Applicable for Complex Service.)
C = Coin
D = All other complex services
E = BellSouth® Centrex®, ESSX®, and MultiServ®, and UNE-P/WLP Centrex

G = Commingling

H = ISDN-BRI
J = PBX Trunk
P = LINE SPLITTING
Q = DID
R = Line Share
9 = EELs
- (hyphen) = not applicable

3rd Character (class)

M = Measured
F = Flat Rate
G = Message
- (hyphen) = not applicable

4th Character

G = E911 Call Locator Capability Service for DID/PBX UNE-P/WLP
N = CO Based Line Share/Line Splitting DLEC Owned Splitter
W = WATS
S = Toll Free Dialing
R = Remote Call Forwarding
F = FXS (Foreign Exchange Service)
Y = Hotel/Motel
Z = Hospital
- (hyphen) = not applicable

Valid Entry Notes

Note 1: A 4th character of F (in the TOS field) is only valid for Complex Services when Foreign Exchange Service exists on the account.

Note 2: The 4th character of TOS values of W, or S is not valid for electronic ordering.

Note #: The 2nd character of TOS value of G is not valid for electronic ordering.

Note 3: The 3rd character of this field must not be F when the REQ TYP is F.

SN91085191
Attachment

- Note 4: The 2nd character of TOS must be a (Hyphen) when the REQ TYP is J.
- Note 5: The 3rd character of TOS must be a (Hyphen) when the REQ TYP is J or A.
- Note 6: When the 1st character of TOS is 2, the only valid entry for the 2nd character is A, B, H, J, P, R or Hyphen.
- Note 7: When the 1st character of the TOS is 3 the 2nd character of TOS must not be R or P.
- Note 8: When 1st character of the TOS is 1, 2 or 3, the 2nd character must not be C.
- Note 9: When the 1st character of the TOS is '4', then the 2nd character must be C.
- Note 10: (Excluding REQ TYP C-Complex LNP) if a request is submitted and the RPON field is populated, the TOS must be as follows: 1st character 1, 2 or 4; 2nd character A, B, C, H, J, P or R; 3rd character M, F, G or - (Hyphen); 4th Character - (Hyphen) (For Line Share/Line Splitting DLEC owned Splitter 4th character can be N)
- Note 11: For REQ TYP C- Complex LNP Services, when the RPON field is populated, the RPON LSRs must reflect the TOS of record. For example, if the service type is BRI the 1st two characters of TOS is 1H.
- Note 12: When the REQ TYP is A (Excluding Line Share/Line Splitting DLEC Owned Splitter), the valid TOS entries are: 1st character = 1; 2nd character = A, B, or 9; 3rd character = (Hyphen); 4th Character = (Hyphen)
- Note 13: The 3rd character of the TOS must be a - (HYPHEN) when the REQ TYP is N and the 4th character of the TOS field is Y or Z.
- Note 14: When the 4th character of the TOS field is F, the 2nd character must be A, B, H or J.
- Note 15: When the 1st character of the TOS field is 4, the 4th character must be a - (Hyphen)
- Note 16: The 4th character of the TOS field must be a - (Hyphen) when the REQ TYP is J.
- Note 17: When both PBX and DID trunks are on the same request the 2nd character of the TOS must be Q.
- Note 18: When the 4th character of this field is N, 2nd character of the TOS must be R or P.
- Note 19: When the LSR request is for Remote Call Forwarding (RCF) the valid values for TOS must be: 1st character: 1, 2, or 3; 2nd character: A or B; 3rd character: F or M; 4th character: R.
- Note 20: When the 4th character of this field is R the REQ TYP must be E or M.
- Note 21: The TOS must be one of the following when changing from a residence class of service to a business class of service and the REQ TYP is E (Non-Complex) or M (Switched Combination RES/BUS): 1AM-; 1BM-; 1AF-; 1BF-
- Note 22: The TOS must be one of the following when changing from a business class of service to a residence class of service and the REQ TYP is E (Non-Complex) or M (Switched Combination RES/BUS): 2AM-; 2BM-; 2AF-; 2BF-
- Note 23: The TOS must be one of the following when changing from a business class of service to a residence class of service or from a residence to a business class of service and the REQ TYP is J: 1---; 2---
- Note 24: When the 2nd character of TOS is - (hyphen) the REQ TYP must be JB
- Electronic
- Note 25: For REQ TYP = C, when the 4th character of TOS is F, then the 2nd character of TOS = D is prohibited.
- Manual
- Note 26: When the REQ TYP is P the 2nd character of the TOS field must be E.
- Note 27: When the 2nd character of the TOS field is E, the 1st character must not be 2 or 4.
- Note 28: When the REQ TYP is M (UNE-P/WLP Centrex) the 2nd character of the TOS must be E, the 3rd must be M, and the 4th must be a hyphen (-).
- Note 29: When the REQ TYP is E (WATS), the 2nd character of the TOS must be D, and the 4th character must be W.
- Note 30: When the REQ TYP is E (Toll Free Dialing), the 2nd character of the TOS must be D and the 4th character must be S.
- Note 31: The 4th character of the TOS must be F when the request is for foreign exchange (FX) or foreign central office (FCO).
- Note 32: The 4th character of the TOS must be Y when the request is for Hotel/Motel service.

SN91085191
Attachment

Note 33: The 4th character of the TOS must be Z when the request is for Hospital Service.

Note 34: When the 2nd character of the TOS is P and the splitter is DLEC owned, the 4th character of the TOS must be N.

Note 35: When the 4th character of the TOS field is G, the 2nd character must be Q or D.

Note 36: When the REQTYP is J, with ACT of D and the class of service on the Customer Service Record (CSR) is LNPBL or MSA, the 1st character of the TOS must be 1.

Note 37: When the REQTYP is J, with ACT of D and the class of service on the Customer Service Record (CSR) is LNPRL or MHT, the 1st character of the TOS must be 2.

Note 38: When the REQTY = A and the product is Single Bandwith Commingling (SWBC) the 2nd character of TOS must be "G".

Data Characteristics

4 alpha/numeric characters

Examples

1AM-
1R-N

Conditional Usage Notes

None

Business Rules

Rule 1: For REQTYP A, Designed and Non-Designed Loops, the 2nd character of the TOS should indicate multi-line or single line based on the number of circuits being requested on the LSR, except for Line Sharing, Line Splitting and EELs.

Rule 2: For REQTYP B and C, the TOS field must reflect the service that is currently on the BellSouth CSR.

Rule 3: If the data in the LNECLS SVC field is a business class of service then the first character of the TOS must be 1.

Rule 4: If the data in the LNECLS SVC field is a residence class of service, then the first character of the TOS must be 2.

Rule 5: The Third and Fourth Characters of this field must be a hyphen (-) for REQTYPs B and C, NPT = D (LNP/WLNP).

Electronic

Rule 6: [BULK Option 1] For UNE to UNE BULK Ordering, TOS (Default) field is required once for every UNE to UNE BULK request. Note: If there is a mixture of account classes of service, TOS (Override) may be shown per EATN.

Rule 7: [BULK Option 1] TOS (Default) For UNE to UNE BULK Ordering Note: If TOS entered at the BULK [Header] level, then all EATNs on BULK request will default to this TOS value.

Rule 8: [BULK Option 1] TOS (Override) is optional for UNE BULK Ordering. Note: Overridable at the Account level.

Manual

Rule 9: If REQTYP = M (for UNE-P Centrex) the 2nd character of the TOS field must be E and the 3rd character must be M.

Rule 10: When the fourth character of the TOS is "G", the LSR must be submitted manually.

***** End of definition for field TOS *****

CMA

Commingling Arrangement
LS Form / Screen
LSOG6 / ELMS6

Definition

Identifies the billing configuration in a commingled service arrangement for same bandwidth segments.

Definition Notes

None

Valid Entries

A = Combination 1

B = Combination 2

C = Combination 3

D = Combination 4

E = Combination 5

F = Combination 6

G = Combination 7

Valid Entry Notes

Manual:

NOTE 1: The valid entry of "A" (Combination 1) is used to order a configuration consisting of a Special Access local channel, a UNE interoffice channel and a UNE loop.

NOTE 2: The valid entry of "B" (Combination 2) is used to order a configuration consisting of a Special Access local channel, a UNE interoffice channel and a Special Access loop.

NOTE 3: The valid entry of "C" (Combination 3) is used to order a configuration consisting of a Special Access local channel, a Special Access interoffice channel and a UNE loop.

NOTE 4: The valid entry of "D" (Combination 4) is used to order a configuration consisting of a Special Access interoffice channel and a UNE loop.

NOTE 5: The valid entry of "E" (Combination 5) is used to order a configuration consisting of a UNE interoffice channel and a Special Access loop.

NOTE 6: The valid entry of "F" (Combination 6) is used to order a configuration consisting of a Special Access local channel and a UNE loop.

NOTE 7: The valid entry of G (Combination 7) is used to order a configuration consisting of a Special Access Local Channel and **UNE** interoffice channel

Data Characteristics

1 alpha character

Examples

A

Conditional Usage Notes

Manual

None

Business Rules

Manual

Rule 1: This field is a Manual only field.

***** End of definition for field CMA *****



Loop Service

LSOG6

Administrative Section

PON VER AN ATN
 LQTY PG_ OF

Service Details

LOCNUM	LNUM	LNA	SLTN	LMT	BTRL	CKR	CMA		
TSP			SAN						
ECCKT									
RESID	CFA						CCEA		
SYSTEM ID	CTI	CABLE ID	CBCID	CHANPAIR	CTI	CABLE ID	CBCID	CHANPAIR	
CTI	CABLE ID	CBCID	CHANPAIR	RELAY RACK			SHELF	SLOT	
SPORT	UNIT	JKCODE	JKNUM	JKPOS	JR	NIDR	IWJK	IWJQ	IWJK
IWJK	IWJQ	DISC NBR				TER			TC OPT
TC TO PRI			TC TO SEC			TCID	TC NAME		
TCID	TC NAME							TC PER	
LEAN			LEATN						



Loop Service (Continued)

LSOG6

Administrative Section

PON VER AN ATN
 LQTY PG_ OF

Service Details

LOCNUM	LNUM	LNA	STLN	LMT	BTRL	CKR	CMA			
TSP			SAN							
ECCKT										
RESID	CFA						CCEA			
SYSTEM ID	CTI	CABLE ID	CBCID	CHANPAIR	CTI	CABLE ID	CBCID	CHANPAIR		
CTI	CABLE ID	CBCID	CHANPAIR	RELAY RACK			SHELF	SLOT		
SPORT	UNIT	JKCODE	JKNUM	JKPOS	JR	NIDR	IWJK	IWJQ	IWJK	IWJQ
IWJK	IWJQ	DISC NBR				TER				TC OPT
TC TO PRI			TC TO SEC			TCID		TC NAME		
TCID	TC NAME							TC PER		
LEAN				LEATN						



Loop Service (Continued)

LSOG6

Administrative Section

PON VER AN ATN
 LQTY PG_ OF

Service Details

LOCNUM	LNUM	LNA	STLN	LMT	BTRL	CKR	CMA		
TSP			SAN						
ECCKT									
RESID	CFA						CCEA		
SYSTEM ID	CTI	CABLE ID	CBCID	CHANPAIR	CTI	CABLE ID	CBCID	CHANPAIR	
CTI	CABLE ID	CBCID	CHANPAIR	RELAY RACK			SHELF	SLOT	
SPORT	UNIT	JKCODE	JKNUM	JKPOS	JR	NIDR	IWJK	IWJQ	IWJK
IWJK	IWJQ	DISC NBR				TER			TC OPT
TC TO PRI			TC TO SEC			TCID	TC NAME		
TCID	TC NAME							TC PER	
LEAN				LEATN					

REMARKS

TCMI TCMESS