

**BellSouth Interconnection Services**

675 West Peachtree Street  
Atlanta, Georgia 30375

**Carrier Notification****SN91083847**

Date: October 10, 2003

To: Competitive Local Exchange Carriers (CLEC)

Subject: CLECs – (Documentation/Guides) - Update to the BellSouth Local Ordering Handbook (LOH) Version 14.0a for the New Local Service Ordering Guide 6 (LSOG 6) and EDI Local Mechanization Specifications 6 (ELMS 6) for Release 14.0

This is to advise that BellSouth has identified the following documentation defects in the LOH Version 14.0a for the new LSOG 6 and ELMS 6 for Release 14.0.

<b>CCP Number</b>	<b>Description Of The Change</b>
1173	Added a new section called "Posting of CSR Information" to the Interconnection Web Portal at this URL address: <a href="http://www.interconnection.bellsouth.com/guides/bpobr/html/gcsrj001/index.htm">http://www.interconnection.bellsouth.com/guides/bpobr/html/gcsrj001/index.htm</a>  Added a new section under number 1, as follows: 1.4 Posting of CSR
1377	Correcting the business rules, forms and interfaces to permit ordering inside wire and jacks for REQ TYP M. BellSouth will document the manual process for ordering jacks on UNE-P REQ TYP M (Non-Complex) currently support jacks on the port service form/screen for ELMS 6. BellSouth has initiated a request through OBF to add the jack fields to the PS form and the request has been worked through OBF, however will not appear on a manual form prior to LSOG 7. BellSouth will document the manual process for ordering jacks on UNE-P REQ TYP M (Non-Complex) in the LOH.
1417	Modifications to DACT R/C/O tables
1418	Modifications to data dictionary various practices 14.0 to align with XML SCHEMA and UR
1419	Modify the DFDT and CHC fields for LNP to resale

Please refer to the attachments for specific details of the changes listed above.

These changes will be reflected in the next update of the LOH Version 14.0b for the new LSOG 6 and ELMS 6 for Release 14.0, scheduled to be posted November 24, 2003.

A summary of all changes within this document will be listed in the **Summary of Changes Section**. This update can be found on the BellSouth Interconnection Services' Web site in the Customer Guides Section at:

<http://www.interconnection.bellsouth.com/guides/html/leo.html>

Please contact your BellSouth Local Support Manager with any questions.

Sincerely,

**Original signed by Pam Tipton for Jerry Hendrix**

Jerry Hendrix – Assistant Vice President  
BellSouth Interconnection Services

Attachments

## CCP 1173 Attachment Listed Below

### PRE-ORDER Web Portal Post information at this location:

<http://www.interconnection.bellsouth.com/guides/bpobr/html/gcsrj001/index.htm>

#### NOTE:

Make this a new section under the “CSR Job Aid” Section, Labeled Section 1.4

## (New Section Title) >> Posting of CSR Information

There is no established official BellSouth ‘standard’ interval for the posting of CSR information to customer accounts upon the completion of service order activity. As is done for its own retail account records, BellSouth generally provides CSR updates to CLEC accounts within one business day of *the completion of the processing of an error-free service order.*

One situation that may affect a CSR update is the timing of the completion of the service order activity. During the bill preparation phase at the end of a billing cycle, the CSR for a given account may be ‘frozen’ for up to four business days. Therefore, if an attempted CSR update occurs at the beginning of this ‘frozen’ period, CSR update may not take place for up to four business days.

Other variables may affect updates to the CSR. For example, a CLEC service order may have proper information to allow provisioning to be completed, but various types of errors in coding on the service order may prevent the order from posting to billing and updating to the CSR. A BellSouth billing representative must manually correct these types of service order errors, as is the case for BellSouth's own retail service orders. This error correction process generally takes only one or two business days. However, some exceptions do exist that increase the time required for error correction. These exceptions include errors that require programmer intervention.

In the event that a CSR is not updated within the Guidelines set forth in the paragraphs above, a CLEC should contact the LCSC.

**CCP 1377 Attachment Listed Below**

**14.0 Ordering**

**Reqtyp M**

**Switched Combo BUS/RES (UNE P BUS/RES)**

**Product Listing**

**Switched Combo BUS/RES (UNE P BUS/RES)**

This service offering is defined as a UNE 2-wire Port that is provisioned in the BellSouth® switch and a UNE voice grade loop which are rebundled to create the equivalent of BellSouth® Retail or Resale service. This combination will always be measured and include switching functionality, shared interoffice transport, tandem switching, and a cross connect element. When combined, these elements will provide an end-to-end service. The Port functionality includes access to all vertical features as well as other functions and capabilities available in the central office switch.

**Ordering Forms/Screens**

The following chart illustrates the required, conditional and optional forms/screens for ordering this service. Detailed information will follow to assist you in filling out each of these forms/screens.

<b>Forms/Screens</b>										
<b>Switched Combo BUS/RES (UNE P BUS/RES)</b>										
<b>LSR</b>	<b>Hunting</b>	<b>EU</b>	<b>DL</b>	<b>RS</b>	<b>DRS</b>	<b>PS</b>	<b>NP</b>	<b>LS</b>	<b>LSNP</b>	<b>RP L</b>
<b>R</b>	<b>O [1]</b>	<b>R</b>	<b>C [2]</b>			<b>C [3]</b>				
R = Required C = Conditional O = Optional										

[1] = Hunting is optional only when ACT is N, C, T or V. Otherwise, Hunting is prohibited.

[2] = The DL form/screen is required when ACT = N or T.

[3] = The PS form/screen is required only when ACT = N, C, T or V. Otherwise, the PS form/screen is not required.

**Note:** Changes to the UNECN Unbundled Contact Name, are not allowed with Non-Complex REQ TYP M, ACTs of B, L, S, and Y.

### Completing the DL Form/Screen

If directory listings are required, refer to **REQ TYP J** for more information on completing the DL form/screen.

### Completing the Hunting Section on the LSR Form/Screen

Hunting is an optional feature only when the ACT is N, C, T or V. For more information on Hunting, refer to **REQ TYP E - Hunting** for information on Hunting for UNE Switched Combinations.

Note: ELECTRONIC ORDERS - When ACT is V, if Hunting exists on the account being converted and the CLEC wishes to *keep the EXISTING hunting*, the HA field should be populated with "E" and all other required fields populated, **or** the HA field should **not be populated** (NO Hunting Page submitted Electronically).

### Completing the LSR and EU Forms/Screens

**Account level activities (ACT)** apply to the entire account. A complete list of ACTs and their definition can be found in the Data Dictionary entry for ACT.

The following chart shows all of the valid account level activities for this service.

Valid Account Level Activities Switched Combo BUS/RES (UNE P BUS/RES)										
N	C	D	T	R	V	S	B	W	L	Y
X	X	X	X	-	X	X	X	X*	X	X
Note: "X" denotes valid account level activities. A dash (-) indicates a non-valid account level activity.										

\* = ACT of W is only allowed for this REQ TYP when the current account is a UNE-P account migrating to a new LSP (UNE-P to UNE-P) or for bulk ordering.

The Required, Conditional and Optional (R/C/O) fields on the LSR and EU forms/screens will be given for every valid ACT code in the **ACT Tables** section.

## Completing the PS Form/Screen

The Port Service (PS) form/screen may be required or invalid depending on the account level activity. Each account level activity has valid Line Level Activities (LNAs). These LNAs determine how, or if, the PS form/screen should be populated. A complete list of LNAs and their definition can be found in the Data Dictionary entry for LNA.

The following chart gives the valid LNAs for each account level activity (ACT) and the associated PS form/screen usage for this service.

If ACT is:	Then LNA is:	And PS form/screen is:
<b>N</b>	N	Required
<b>C</b>	N, C, D, P or X	Required
<b>D</b>	Prohibited	Not Required
<b>V</b>	N, G, V, W, P, D or X	Required
<b>T</b>	N, T	Required
<b>S</b>	L or B	Required
<b>B</b>	Prohibited	Not Required
<b>W</b>	Prohibited	Not Required
<b>L</b>	Prohibited	Not Required
<b>Y</b>	Prohibited	Not Required

**NOTE:** Jacks and wiring may be requested manually only utilizing FEATURE/FEATURE DETAIL fields of the PS-Port Service Form.

The Required, Conditional and Optional (R/C/O) fields for the PS form/screen are listed according to the Line Level Activity (LNA) in the **LNA Tables** Section.

## CCP 1417 Attachment Listed Below

### LOH Version 14.0A RCO Tables

Notes:

- (M) = Fields used only for manual orders
- (E) = Fields used only for electronic orders
- (\*) = Optional fields that force at least one conditional field to become required.
- (\*\*) = See additional clarification in the Data Dictionary.
- All unmentioned fields are either invalid, not applicable, prohibited or not supported.

ACT Tables: Reqtyp J, Directory Listing (14.0A)

**ACT= C: LSR**

**Required**

ACT	BAN1	CC
CCNA	D/TSENT	DDD
INIT	INIT-FAX NO.	INIT-TEL NO.
PG_OF_ (M)	PON	REQTYP
SC	TOS	

**Conditional**

AN	ATN	BI1
CIC	CUST	SUP
VER		

**Optional**

REMARKS	RPON	
---------	------	--

**ACT= C: EU****Required**

CITY	NAME	PG_OF_ (M)
PON (M)	SASN	STATE
ZIP		

**Conditional**

AAI	AN (M)	ATN (M)
EAN	EATN	SANO
VER (M)		

**Optional**

LD1	LD2	LD3
SASD	SASF	SASS
SATH		

Updated 9/10/2003

Page 1 of 8

*ACT Tables: Reqtyp J, Directory Listing (14.0A)***ACT= D: LSR****Required**

ACT	BAN1	CC
CCNA	D/TSENT	DDD
INIT	INIT-FAX NO.	INIT-TEL NO.
PG_OF_ (M)	PON	REQTYP
SC	TOS	

**Conditional**

AN	ATN	BI1
CIC	CUST	SUP
VER		

**Optional**  
 REMARKS

RPON

**ACT= D: EU**

**Required**  
 NAME

PG\_OF\_ (M)

PON (M)

**Conditional**

AN (M)

ATN (M)

FB-BILLCON

FB-BILLNM

FB-CITY

FB-STATE

FB-STREET

FB-ZIP CODE

TEL NO-FBCON

VER (M)

**Optional**

FB-FLOOR

FBI\*

FB-ROOM

FB-SBILLNM

**ACT= N: LSR**

**Required**

ACT

BAN1

CC

CCNA

D/TSENT

DDD

INIT

INIT-FAX NO.

INIT-TEL NO.

PG\_OF\_ (M)

PON

REQTYP

SC

TOS

Updated 9/10/2003

Page 2 of 8

*ACT Tables: Reqtyp J, Directory Listing (14.0A)*

**Conditional**

AN

ATN

B11

CIC

CUST

SUP

VER

**Optional**

REMARKS

RPON

**ACT= N: EU**

**Required**

CITY

NAME

PG\_OF\_ (M)

PON (M)

SASN

STATE

ZIP

**Conditional**

AAI

AN (M)

ATN (M)

SANO

VER (M)



**Optional**

LD1	LD2	LD3
SASD	SASF	SASS
SATH		

**ACT= R: LSR****Required**

ACT	BAN1	CC
CCNA	D/TSENT	DDD
INIT	INIT-FAX NO.	INIT-TEL NO.
PG_OF_ (M)	PON	REQTYP
SC	TOS	

**Conditional**

AN	ATN	BI1
CIC	CUST	SUP
VER		

**Optional**

REMARKS	RPON	
---------	------	--

Updated 9/10/2003

Page 3 of 8

*ACT Tables: Reqtyp J, Directory Listing (14.0A)***ACT= R: EU****Required**

CITY	NAME	PG_OF_ (M)
PON (M)	SASN	STATE
ZIP		

**Conditional**

AAI	AN (M)	ATN (M)
EAN	EATN	SANO
VER (M)		

**Optional**

LD1	LD2	LD3
SASD	SASF	SASS
SATH		

Updated 9/10/2003

*LACT Tables: Reqtyp J, Directory Listing (14.0A)***LACT= D: DL****Required**

DLNUM	LACT	PG_OF_ (M)
PON (M)	RTY	SC1 (M)

**Conditional**

ADV	ALI	AN (M)
ATN (M)	INS1	LNFN
LTN	VER (M)	WPP

**Optional**

NSTN

**LACT= I: DL****Required**

DLNUM	DOI	LACT
LNLN	LTY	PG_OF_ (M)
PLS (M)	PON (M)	RTY
SC1 (M)	STYC	TOA

**Conditional**

ADI	ADV	ALI
AN (M)	ATN (M)	DES
DIRNAME	DLNM	FAINFO
FATN	LALOC	LANO
LAPR	LASD	LASF
LASN	LASS	LAST
LATH	LNFN	LNPL
LTEXT	LTN	LTXNUM
LTXTY	NICK	NSTN
PLA	PLINFO	PLTN
SIC	VER (M)	WPP
YPH		

**Optional**

BRO	DIRSUB	DML
SO	TITLE1	TITLE2
TL		

Updated 9/10/2003

Page 5 of 8

*LACT Tables: Reqtyp J, Directory Listing (14.0A)***LACT= N: DL****Required**

DLNUM	DOI	LACT
LNLN	LTY	PG_OF_ (M)
PLS (M)	PON (M)	RTY
SC1 (M)	STYC	TOA

**Conditional**

ADI	ADV	ALI
AN (M)	ATN (M)	BRO
DES	DIRNAME	DIRSUB
DLNM	DML	FAINFO
FATN	LALOC	LANO
LAPR	LASD	LASF
LASN	LASS	LAST
LATH	LNFN	LNPL
LTEXT	LTN	LTXNUM
LXTY	NICK	NSTN
PLA	PLINFO	PLS (E)
PLTN	SIC	VER (M)
WPP	YPH	

**Optional**

SO	TITLE1	TITLE2
TL		

**LACT= O: DL****Required**

DLNUM	LACT	PG_OF_ (M)
PLS (M)	PON (M)	RTY
SC1 (M)		

**Conditional**

ADI	ADV	ALI
AN (M)	ATN (M)	LASN
LNFN	PLS (E)	VER (M)

*DACT Tables: Reqtyp J, Directory Listing (ACT of N or R) (14.0A)*

**DACT= N: DL**

Conditional

AAI	CITY	DACT
DDANO	DDAPR	DDASD
DDASF	DDASN	DDASS
DDATH	DIRQTYA	DIRQTYNC
DIRTYP	LD1	LD2
LD3	LV1	LV2
LV3	NAME	STATE
ZIP		

Updated 9/10/2003

Page 7 of 8

*DACT Tables: Reqtyp J, Directory Listing (ACT of R) (14.0A)*

**DACT= N: DL**

Conditional

<del>AAI</del>	<del>CITY</del>	<del>DACT</del>
<del>DDANO</del>	<del>DDAPR</del>	<del>DDASD</del>
<del>DDASF</del>	<del>DDASN</del>	<del>DDASS</del>
<del>DDATH</del>	<del>DIRQTYA</del>	<del>DIRQTYNC</del>
<del>DIRTYP</del>	<del>LD1</del>	<del>LD2</del>
<del>LD3</del>	<del>LV1</del>	<del>LV2</del>
<del>LV3</del>	<del>NAME</del>	<del>STATE</del>
ZIP		

Updated 9/10/2003

Page 8 of 8

## CCP 1418 Attachment Listed Below

### REMARKS

#### Remarks (LSNP Page)

<b>Definition</b>	Identifies a free flowing field which can be used to expand upon and clarify other data on this form/screen.
<b>Def Notes</b>	None
<b>Valid Entries</b>	None
<b>VE Notes</b>	None
<b>Data Charact</b>	

#### Manual

Up to 160 alpha/numeric characters

Electronic:

Up to 240 alpha/numeric characters

<b>Examples</b>	SUP TO DELETE TN 111-222-3333
<b>CU Notes</b>	None
<b>Bus Rules</b>	<del>None</del>

Electronic:

Rule 1: When populated this field is ignored.

#### Remarks (LS Page)

<b>Definition</b>	Identifies a free flowing field which can be used to expand upon and clarify other data on this form/screen.
<b>Def Notes</b>	None
<b>Valid Entries</b>	None
<b>VE Notes</b>	None
<b>Data Charact</b>	<b>Manual</b>  Up to 160 alpha/numeric characters  <b>Electronic</b>  <b>Up to 240 alpha/numeric characters</b>
<b>Examples</b>	SUP TO DELETE TN 111-222-3333
<b>CU Notes</b>	None
<b>Bus Rules</b>	Electronic: Rule 1: This field is ignored on electronically submitted LSR's. Manual: Rule 2: If a 4-Wire loop is ordered on a manual LSR, the CHAN/PAIR 2 information is to be placed in REMARKS on the manual LS form. Rule 3: When ordering RS HFS Unbundled Line Share DLEC Owned this field must be populated as follows: REMARKS Remote Site DLEC Owned Requested.

Rule 4: When ordering UDF(Unbundled Dark Fiber) Local Channel, populate this field with SCFA's for 2 4-fiber terminations at the Collocation. When ordering UDF Interoffice Channel, populate this field with a 2nd /CFA and SCFA's for 2 4-fiber terminations at each Collocation. When ordering UDF Local Loop, populate this field CFA for 2 4-fiber terminations at the Collocation.

Rule 5: When ordering a OCU where the secondary address is a "POP" (Point Of Presence) location, provide in REMARKS a 'SPOT' field with the CLLI Code of the "POP".

Rule 6: When ordering a OCU where the primary address is a "POP" (Point Of Presence) location, provide in REMARKS a "APOT" field with the CLLI Code of the "POP".

Rule 7: When ordering a new EEL or OCU, populate this field with the name of the EEL or OCU (Type of LC, Type of IOC, Type of Mux, Type of Loop).

Rule 8: When ordering an EEL or OCU with channelization (a mux), specify the location in REMARKS field as MUXLOC with a CLLI for SWC the MUX is located.

## REMARKS

### Remarks (NP Page)

**Definition** Identifies a free flowing field which can be used to expand upon and clarify other data on this form/screen

**Def Notes** None

**Valid Entries** None

**VE Notes** None

#### Data Charact

#### Manual

Up to 160 alpha/numeric characters

#### Electronic:

Up to 240 alpha/numeric characters

**Examples** SUP TO DELETE TN 111-222-3333

**CU Notes** None

**Bus Rules** Manual:  
Rule 1: On a REQ TYP C, ACT of V; for PRI and Channelized Megalinks®; when ALL numbers are disconnecting or porting, the Remarks section must be populated with information concerning the disposition of the pipe.

#### Electronic:

Rule 2: When populated this field is ignored.

## DSGCON-ROOM/MAIL STOP

### Design / Engineering Contact Room / Mail Stop (LSR Page)

**Definition** Identifies the room or mail stop of the design / engineering contact's address.

**Def Notes** None

**Valid Entries** None

**VE Notes** None

**Data Charact** Up to 10 alpha/numeric characters

**Examples** K-151A

**CU Notes** Note 1: Optional when DSGCON field is populated.

**Bus Rules** Rule 1: When the REQ TYP is A, and the information populated in the NC field begins with TY or TX, data in this field is not mapped to a service order.  
Electronic:  
Rule 2: [BULK] Optional for UNE to UNE Bulk Migration based on current REQ TYP B rules/notes.

**TC OPT**

## Transfer of Call Options (PS Page)

**Definition**

Identifies the type of transfer of call option requested by the end user for the disconnected telephone number when the standard intercept report is not desirable.

The following standard intercept recordings will automatically apply when this field is not populated.

Order or Line Activity: Standard Intercept Report

"D" - Disconnect: The number you have reached has been disconnected.

"C" or "T" - Number change to a Non-Pub number: The number you have reached XXX-XXXX has been changed to a non-published number.

"C" or "T" - Number change to a listed number: The number you have reached XXX-XXXX has been changed. The new number is XXX-XXXX.

"C" - Seasonal suspension: At the customer's request XXX-XXXX has been temporarily disconnected.

"C" - Disconnect RingMaster number refer calls to Main Number: The number you have reached XXX-XXXX has been changed. The new number is XXX-XXXX.

**Def Notes**

The following standard intercept recordings will automatically apply when this field is not populated.

Order or Line Activity Standard Intercept Report

"D" - Disconnect "The number you have reached has been disconnected."

"C" or "T" - Number change to a Non-Pub number "The number you have reached XXX-XXXX has been changed to a non-published number."

"C" or "T" - Number change to a listed number "The number you have reached XXX-XXXX has been changed. The new number is XXX-XXXX."

"C" - Seasonal suspension "At the customer's request XXX-XXXX has been temporarily disconnected."

"C" - Disconnect RingMaster number refer calls to Main Number "The number you have reached XXX-XXXX has been changed. The new number is XXX-XXXX."

NOTE 1: For Multi Line disconnects when a TC OPT is not selected a Transfer of Calls Intercept message may be received such as:

Example:

"We're sorry, you have reached a number that has been disconnected or is no longer in service. If

you

feel you have reached this recording in error please check the number and try your call again."

or

The Transfer of Calls Intercept message will reflect the status of the main number:

Example:

"The number you have reached XXX-XXXX (disconnected number) has been changed to XXX-XXXX (main tn)."

or

When the main TN is non-published, the recording will reflect:

"The number you have reached XXX-XXXX (disconnected number) has been changed to a Non-published number."

**Valid Entries**

TC: Transfer of Calls. "The number you have reached XXX-XXXX has been changed. The new number is XXX-XXXX."

NO: None "The number you have reached has been disconnected."

ST: Split "The called number is routed to an operator/recording who verifies the number being called and then quotes the new number(s)."

CA: Used to cancel a transfer of call option when a number is disconnected. "The number you have reached has been disconnected."

**VE Notes**

Manual:

NOTE 1: When REQTYP is M and the TC OPT is populated with CA, LNA must be C, N, T, V or G.

**Data Charact**

2 alpha/numeric characters

**Examples**

TC

**CU Notes**

Note 1: Prohibited if TC FR is not populated when LNA is N, C or V.

Note 2: Prohibited if OTN is not populated when LNA is X, G or T.

Note 3: Prohibited if TNS is not populated for LNA is D or L.

**LSCP**

## Local Service Provider Change Prohibited (NP Page)

**Definition** Identifies that the end user has requested the option of prohibiting the change of their current service provider or removing the option.  
This field is NOT supported in this practice by BellSouth®.

**Def Notes**

**Valid Entries**

**VE Notes**

**Data Charact**

**Examples**

**CU Notes**

**Bus Rules**

**TCMESS**

## Transfer of Calls Message (NP Page)

**Definition** Allows for a personalized message when requesting the transfer of calls.  
This field is NOT supported by BellSouth®.

**Def Notes**

**Valid Entries**

**VE Notes**

**Data Charact**

**Examples**

**CU Notes**

**Bus Rules**

**TCMI**

## Transfer of Call Message Indicator (NP Page)

**Definition** Associates the transfer of call message with the TCID of the telephone number for which the message is being received.  
This field is NOT supported by BellSouth®.

**Def Notes**

**Valid Entries**

**VE Notes**

**Data Charact**

**Examples**

**CU Notes**

**Bus Rules**



## CCP 1419 Attachment Listed Below 14.0 & 15.0

### CHC

Coordinated Hot Cut (LSR Page)

#### Definition

Indicates the customer is requesting near seamless cutover activity.

#### Definition Notes:

*NOTE 1: This field may require manual intervention and coordination between BellSouth® and the Customer.*

*NOTE 2: This field is used with a cutover coordination of two services (e.g., switch lines to number portability).*

#### Valid Entries

Manual: Y = Hot Cut Authorized, or blank

Electronic: Y = Yes, N = No

#### Valid Entry Notes:

None

#### Data Characteristics

1 alpha character

#### Examples

Y

#### Conditional Usage Notes

Note 1: Prohibited when the CC or NNSP field is populated with a wireless OCN.

Electronic:

Note 2: This field is required when the REQ TYP is A or B, and the information populated in the NC field begins with TY or TX, and the DFDT field is populated, otherwise prohibited.

Note 3: [BULK] Prohibited when the BOPI field is populated.

Note 4: Prohibited when the request is an LNP to Resale/UNE P Migration for REQ TYP E, M, P, and N. And when the "SC" is "LSCP".

#### Business Rules

None

**DFDT**

## Desired Frame Due Time (LSR Page)

**Definition**

Identifies the desired frame cutover time.

**Definition Notes:**

*NOTE 1: The time indicated in this field will reflect the local time of the end user's location(s).*

**Valid Entries**

HHMM, HHMM-HHMM

Military format: where HH must be numerics from 01-24 and MM must be numerics ranging from 00-59.

**Valid Entry Notes:**

*NOTE 1: When the CHC field is populated with a Y, the DFDT must be a single time entry.*

**Data Characteristics**

Manual: Up to 6 alpha/numeric characters

Electronic: Up to 9 alpha/numeric characters

**Examples**

Manual: 1300

Electronic: 1300 1300-1700

**Conditional Usage Notes**

Note 1: This field is prohibited when the ACT is N.

Note 2: Prohibited when the REQTYP is A and the ACT = C and LNA is N.

Note 3: Prohibited when the REQTYP is E (Non-Complex) or M (Non-Complex) and the ACT is B, L, S, W or Y.

Note 4: Prohibited when the REQTYP is E with 2nd character TOS of H and the ACT is C, D, T, V or W.

Note 5: Prohibited when the REQTYP is N and the ACT is W.

Note 6: Prohibited when the CC or NNSP field is populated with a wireless OCN.

Electronic:

Note 7: [BULK] Prohibited when the BOPI field is populated.

Note 8: Prohibited when the request is an LNP to Resale/UNE P Migration for REQTYP E, M, P, and N. And when the "SC" is "LSCP".

**Business Rules**

Rule 1: For projects, frame due times are negotiated with the CLEC.

Rule 2: For non-projects, frame due time indicates the specific time the request is to be worked.

Rule 3: When the CHC is populated and the DFDT is populated, the DFDT field must be a single entry; of an hour and minute and not a span of time.

Rule 4: When DFDT is populated with a time requested for time specific hot-cut, the time requested may be changed by BST to the next available time slot. This time slot assignment may be the same day or next business day. If assigned a different time and/or due date, the changed appointment will be reflected in the FOC.

Rule 5: When the REQTYP is A or B, and the information populated in the NC field begins with TY or TX, the CHC field is also required.

