
BellSouth Interconnection Services

675 West Peachtree Street
Atlanta, Georgia 30375

**Carrier Notification
SN91085264**

Date: December 13, 2005

To: Competitive Local Exchange Carriers (CLEC)

Subject: CLECs – (Documentation/Guides) - Update to the BellSouth Local Ordering Handbook (LOH) Version 21.0 for Telecommunications Industry Forum 9 (TCIF 9) Release 21.0

This is to advise that BellSouth has identified the need for updating documentation in the LOH Version 21.0 for TCIF 9 Release 21.0.

CCP Number	Description Of The Change
2314	REQTYP A and B (Jack Codes): Indicate specific Jack Codes for individual products for both 'electronic' and 'manual' LSR processing.
2317	BA Block Activity field: Add Valid Entry Note: "When more than 1 BA is associated on the same LNUM, the only valid combinations are A/A, A/D or A/Z." for the BA field in the Data Dictionary.
2318	DDD field: Add 8 character Valid Entry Note description for Manual LSR.
2319	REQTYP B INP R/C/O tables: Update REQTYP B INP R/C/O tables to add 'manual' (M) indicator to all fields that don't have them -and remove the 'electronic' only fields.
2322	REQTYP A - DS1 can be ordered electronically for ACT = D and N, Update R/C/O tables (by removing the manual-only indicator '(M)' next to the affected fields) to indicate that the fields on these tables for this product are for both manual <i>and</i> electronic ordering.
2323	Interval Guide for Frame Relay: Change Interval Guide to show types of speed changes.

Please refer to the attachment for specific details of the changes listed above.

These changes will be reflected in the next update of the TCIF 9 Release 21.0/LOH Version **21.0a** scheduled to be posted Friday, January 6, 2006.

A summary of all changes within this document will be listed in the **Summary of Changes** section.

This update can be found on the BellSouth Interconnection Services Web site in the Customer Guides Section at:

<http://www.interconnection.bellsouth.com/guides/html/leo.html>

Please contact your BellSouth local support manager with any questions.

Sincerely,

Original signed by Kristen E. Shore

Kristen E. Shore – Director
BellSouth Interconnection Services

Attachments

CCP 2314 Attachment Listed Below

CRB: 4803
CCP: 2314
MAP: TCIF9
LOH: 21.0A

LS - Loop Service

JK CODE

Jack Code
LS Form / Screen
LSOG4 / TCIF9

Definition

Indicates the standard code for the particular registered or non-registered jack used to terminate the service.

Definition Notes

Note 1: Familiarization with the FCC's registration rules is requisite for all parties involved for the determination of the proper jack code for a given registered service.

Note 2: Registered jacks used to terminate category 1 and 3 services begin with the designation RJ.

Valid Entries

None

Valid Entry Notes

Note 1: The following USOCs are valid **for all other REQTYP A products not listed in Valid Entry Notes 2, 3, 4, & 5**: RJ11C, RJ11W, RJ11D, RJ14C, RJ14W, RJ12C, RJ12W, RJ13C, RJ13W, RJ17C, RJ18C, RJ18W, RJ19C, RJ19W, RJ25C, RJ61X, RJ31X, RJ32X, RJ33X, RJ34X, RJ35X, RJ36X, RJ37X, RJ38X, RJ71C, RJ2EM, RJ2FM, RJ2MZ, RJ21M, RJ2DM, RJ2GM, RJ2HM, RJ22X, RJ23X, RJ24X, RJ21X, RJ2DX, RJ2FX, RJ2HX, RJ2GX, RJ41Q, RJ41Z, RJ45Z, RJ45Q, RJ16X, RJ48Z, RJ41S, RJ45S, RJ26X, RJ26S, RJ27X, RJ48C, RJ48H, RJ48M, RJ48S, RJ48T, RJ48X, RJ26M, RJ27M, RJ48Y, RJ48A, RJ48B, RJM3X, RJM4X, RJ1DC, RJ2EX

Electronic:

Note 2: When an LSR is submitted electronically for REQTYP A with LNAs of N, C, or V, where service types are: Analog Voice Non-Designed, Analog Voice Designed, Enhanced Extended Links (EELS), UCL - (2W) Non-Designed; the NIDR field is populated with 'Y', the JK CODE (Jack Code) field must be submitted with the following:

Voice Jack Type USOCs: RJ11C, RJ11W, RJ11D, RJ14C, RJ14W, RJ1DC, RJ12C, RJ12W, RJ13C, RJ13W, RJ17C, RJ18C, RJ18W, RJ19C, RJ19W, RJ25C, RJ61X, RJ31X, RJ21X

Note 3: When an LSR is submitted electronically for REQTYP A with LNAs N, C, or V, where

service types are: Digital Data Designed (DS0), Digital Data Designed (DS1), Digital Designed Basic Rate ISDN, Universal Digital Channel (UDC), ADSL (2W) Designed, HDSL (2W) Designed, HDSL (4W) Designed, UCL - Short (2W) Designed, UCL - Long (2W) Designed, UCL - Short (4W) Designed, UCL - Long (4W) Designed; and NIDR field is populated with 'Y', the JK CODE field must be submitted with the following: Data Jack Type USOCs: RJ14Q, RJ41Z, RJ45Q, RJ45Z, RJ16X, RJ48Z, RJ41S, RJ45S, RJ26X, RJ26S, RJ27X, RJ48C, RJ48H, RJ48M, RJ48S, RJ48T, RJ48X, RJM3X, RJM4X, RJ26S, RJ21X

Manual:

Note 4: When an LSR is submitted manually for REQ TYP A with LNAs of N, C, or V, where service types are: Analog Voice Non-Designed, Analog Voice Designed, Enhanced Extended Links (EELS), UCL - (2W) Non-Designed; the NIDR field is populated with 'Y', the JK CODE (Jack Code) field must be submitted with the following: Data Jack Type USOCs: RJ14Q, RJ41Z, RJ45Q, RJ45Z, RJ16X, RJ48Z, RJ41S, RJ45S, RJ26X, RJ26S, RJ27X, RJ48C, RJ48H, RJ48M, RJ48S, RJ48T, RJ48X, RJM3X, RJM4X, RJ26S, RJ21X

Note 5: When an LSR is submitted manually for REQ TYP A with LNAs N, C, or V, where service types are: Digital Data, Designed (DS0), Digital Data, Designed (DS1), Digital Designed Basic Rate ISDN, Universal Digital Channel (UDC), ADSL (2W) Designed, HDSL (2W) Designed, HDSL (4W) Designed, UCL - Short (2W) Designed, UCL - Long (2W) Designed, UCL - Short (4W) Designed, UCL - Long (4W) Designed; and NIDR field is populated with 'Y', the JK CODE field must be submitted with the following: Voice Jack Type USOCs: RJ11C, RJ11W, RJ11D, RJ14C, RJ14W, RJ1DC, RJ12C, RJ12W, RJ13C, RJ13W, RJ17C, RJ18C, RJ18W, RJ19C, RJ19W, RJ25C, RJ61X, RJ31X, RJ21X.

Data Characteristics

5 alpha/numeric characters

Examples

RJ21X

Conditional Usage Notes

- Note 1: Required when the NIDR field is populated with Y, otherwise prohibited.
- Note 2: Required when the JK NUM or JK POS field is populated.

Business Rules

None

***** End of definition for field JK CODE *****

LSNP - Loop Service

JK CODE

Jack Code
LSNP Form / Screen
LSOG4 / TCIF9

Definition

Indicates the standard code for the particular registered or non-registered jack used to terminate the service.

Definition Notes

Note 1: Familiarization with the FCC's registration rules is requisite for all parties involved for the determination of the proper jack code for a given registered service.

Note 2: Registered jacks used to terminate category 1 and 3 services begin with the designation RJ.

Valid Entries

None

Valid Entry Notes

Note 1: The following USOCs are valid for all other REQTYP B (INP or LNP) products not listed in Valid Entry Notes 2, 3, 4, & 5: RJ11C, RJ11W, RJ11D, RJ14C, RJ14W, RJ12C, RJ12W, RJ13C, RJ13W, RJ17C, RJ18C, RJ18W, RJ19C, RJ19W, RJ25C, RJ61X, RJ31X, RJ32X, RJ33X, RJ34X, RJ35X, RJ36X, RJ37X, RJ38X, RJ71C, RJ2EM, RJ2FM, RJ2MZ, RJ21M, RJ2DM, RJ2GM, RJ2HM, RJ22X, RJ23X, RJ24X, RJ21X, RJ2DX, RJ2FX, RJ2HX, RJ2GX, RJ41Q, RJ41Z, RJ45Z, RJ45Q, RJ16X, RJ48Z, RJ41S, RJ45S, RJ26X, RJ26S, RJ27X, RJ48C, RJ48H, RJ48M, RJ48S, RJ48T, RJ48X, RJ26M, RJ27M, RJ48Y, RJ48A, RJ48B, RJM3X, RJM4X, RJ1DC, RJ2EX

Electronic:

Note 2: When an LSR is submitted electronically for REQTYP B (LNP) with LNAs of N, or V, where service types are: LNP - Designed Analog Loop, LNP - Non-Designed Analog Loop, LNP - UCL-ND, LNP - EELS, the NIDR field is populated with 'Y', the JK CODE (Jack Code) field must be submitted with the following: Voice Jack Type USOCs: RJ11C, RJ11W, RJ11D, RJ14C, RJ14W, RJ1DC, RJ12C, RJ12W, RJ13C, RJ13W, RJ17C, RJ18C, RJ18W, RJ19C, RJ19W, RJ25C, RJ61X, RJ31X, RJ21X

Note 3: When an LSR is submitted electronically for REQTYP B (LNP) with LNAs N, or V, where service types are: LNP - UCL-D, LNP - xDSL, LNP - ISDN, and NIDR field is populated with 'Y', the JK CODE field must be submitted with the following: Data Jack Type USOCs: RJ14Q, RJ41Z, RJ45Q, RJ45Z, RJ16X, RJ48Z, RJ41S, RJ45S, RJ26X, RJ26S, RJ27X, RJ48C, RJ48H, RJ48M, RJ48S, RJ48T, RJ48X, RJM3X, RJM4X, RJ26S, RJ21X

Manual

Note 4: When an LSR is submitted manually for REQTYP B (INP and LNP) with LNAs of N, or V, where service types are: INP - Designed Analog Loop, INP - Non-Designed Analog Loop, INP - UCL-ND, LNP - Designed Analog Loop, LNP - Non-Designed Analog Loop, LNP - UCL-ND, LNP

- EELS; the NIDR field is populated with 'Y', the JK CODE (Jack Code) field must be submitted with the following: Data Jack Type USOCs: RJ14Q, RJ41Z, RJ45Q, RJ45Z, RJ16X, RJ48Z, RJ41S, RJ45S, RJ26X, RJ26S, RJ27X, RJ48C, RJ48H, RJ48M, RJ48S, RJ48T, RJ48X, RJM3X, RJM4X, RJ26S, RJ21X

Note 5: When an LSR is submitted manually for REQTYP B (INP and LNP) with LNAs N, or V, where service types are: INP - UCL-D, INP - xDSL, INP - ISDN, INP - DS0, LNP - UCL-D, LNP - xDSL, LNP - ISDN; and NIDR field is populated with 'Y', the JK CODE field must be submitted with the following: Voice Jack Type USOCs: RJ11C, RJ11W, RJ11D, RJ14C, RJ14W, RJ1DC, RJ12C, RJ12W, RJ13C, RJ13W, RJ17C, RJ18C, RJ18W, RJ19C, RJ19W, RJ25C, RJ61X, RJ31X, RJ21X.

Data Characteristics

5 alpha/numeric characters

Examples

RJ21X

Conditional Usage Notes

Note 1: Required when the NIDR field is populated with Y.

Note 2: Required when the JK NUM or JK POS field is populated.

Business Rules

None

***** End of definition for field JK CODE *****

CCP 2317 Attachment Listed Below

CRB: 4812
CCP: 2317
MAP: TCIF9
LOH: 21.0A

TCIF9**BA**

Blocking Activity
DRS Form / Screen
LSOG4 / TCIF9

Definition

Indicates the activity for the blocking of calls.

Definition Notes

None

Valid Entries

A = Add
D = Delete
N = No change
Z = Remove all blocking

Valid Entry Notes

~~None~~

Note 1: When more than 1 BA field is associated on the same LNUM, the only valid combinations are A/A, A/D or A/Z.

Data Characteristics

1 alpha character

Examples

A

Conditional Usage Notes

None

Business Rules

Rule 1: When LNA = N the only valid entry is A.

***** End of definition for field BA *****

BA

Blocking Activity
LSNP Form / Screen
LSOG4 / TCIF9

Definition

Indicates the activity for the blocking of calls.

Definition Notes

None

Valid Entries

A = Add
D = Delete
N = No change
Z = Remove all blocking

Valid Entry Notes

~~None~~

Note 1: When more than 1 BA field is associated on the same LNUM, the only valid combinations are A/A, A/D or A/Z.

Data Characteristics

1 alpha character

Examples

A

Conditional Usage Notes

Note 1: When LNA = N the only valid entry is A.
Note 2: Prohibited when NPT is D (LNP).

Business Rules

None

***** End of definition for field BA *****

BA

Blocking Activity
NP Form / Screen
LSOG4 / TCIF9

Definition

Indicates the activity for the blocking of calls.

Definition Notes

None

Valid Entries

A = Add
D = Delete
N = No change
Z = Remove all blocking

Valid Entry Notes

~~None~~

Electronic

Note 1: When more than 1 BA field is associated on the same LNUM, the only valid combinations are A/A, A/D or A/Z.

Data Characteristics

1 alpha character

Examples

A

Conditional Usage Notes

Note 1: Prohibited when NPT = D (LNP).

Business Rules

None

***** End of definition for field BA *****

BA

Blocking Activity
PS Form / Screen
LSOG4 / TCIF9

Definition

Indicates the activity for the blocking of calls.

Definition Notes

None

Valid Entries

A = Add
D = Delete
N = No change
Z = Remove all blocking
blank

Valid Entry Notes

Note 1: When LNA = G or N the only valid entry is A.

Note 2: When more than 1 BA field is associated on the same LNUM, the only valid combinations are A/A, A/D or A/Z.

Data Characteristics

1 alpha character

Examples

A

Conditional Usage Notes

None

Business Rules

None

***** End of definition for field BA *****

BA

Blocking Activity
RS Form / Screen
LSOG4 / TCIF9

Definition

Indicates the activity for the blocking of calls.

Definition Notes

None

Valid Entries

A = Add
D = Delete
N = No change
Z = Remove all blocking

Valid Entry Notes

Note 1: When LNA = G or N the only valid entry is A.
Note 2: To change blocking on an existing account, the valid entry is A, with the desired block.
Note 3: (The existing block will be automatically removed.)

Note 4: When more than 1 BA field is associated on the same LNUM, the only valid combinations are A/A, A/D or A/Z.

Data Characteristics

1 alpha character

Examples

A

Conditional Usage Notes

None

Business Rules

None

***** End of definition for field BA *****

CCP 2318 Attachment Listed Below

CRB: 4813
CCP: 2318
MAP: TCIF9
LOH: 21.0A

DDD

Desired Due Date
LSR Form / Screen
LSOG4 / TCIF9

Definition

Identifies the customer's desired due date. On disconnect requests, this date represents the date billing is to stop on the involved service and can be no earlier than the date the request is received by the LCSC.

Definition Notes

None

Valid EntriesElectronic

1 and 2 = Two Digit Century (CC) 20 - 99
3 and 4 = Two Digit Year (YY) 00 - 99
5 and 6 = Two Digit Month (MM) 01 - 12
7 and 8 = Two Digit Day (DD) 01 - 31

Manual

1 and 2 = Two Digit Month (01-12)
3 = Hyphen or slash [Virgule]
4 and 5 = Two Digit Day (01-31)
6 = Hyphen or slash [Virgule]
7 and 8 = Two Digit Year (00-99)

1 and 2 = Two Digit Month (01-12)
3 = Hyphen or slash [Virgule]
4 and 5 = Two Digit Day (01-31)
6 = Hyphen or slash [Virgule]
7 and 8 = Two Digit Century (20-99)
9 and 10 = Two Digit Year (00-99)

Valid Entry Notes

None

Data CharacteristicsElectronic

8 numeric characters

Manual

8 or 10 alpha/numeric characters

ExamplesElectronic

20010522

Manual

03/22/01

03-22-2001

Conditional Usage Notes

None

Business Rules

Rule 1: Must be greater than or equal to D/TSENT.

Rule 2: Must be a valid date.

Rule 3: If the requested DDD is not available then the next available date is assigned and returned on the FOC.

Rule 4: Due dates will not normally be appointed on Sunday, or holidays.

Rule 5: There may be times when, due to work load and abnormal weather conditions in an area, such as a hurricane, flood or other natural disaster, the due date returned will be longer than the standard intervals.

Rule 6: When the REQYTP is C, Type 1 Wireless Port, porting 1-50 TNs please refer to the BellSouth interval guide.

Rule 7: For REQYTP A Analog Non-Design Loops ACT=C, N, P, Q or V, this field must be greater than one business day from the D/TSENT when the EXP field is populated with a Y.

Electronic

Rule 8: [BULK] When the request is for a UNE to UNE Bulk order the request is project managed, and the DDD cannot be less than 8 business days from the D/TSENT on the initial submission of the LSR.

Rule 9: (BULK) On BULK requests, the DDD provided on SUP 02 LSR's with a BOPI populated must be greater than or equal to 8 business days from the supplemental LSR D/TSENT.

Rule 10: (BULK) On BULK order requests for SUP 03 when the DDD is changing and BOPI populated, the DDD must be greater than or equal to 8 business days from the supplemental LSR D/TSENT.

Rule 11: (BULK) On BULK order requests for SUP 03 when the DDD is not changing and the BOPI field is populated, the original DDD field should not be altered.

***** End of definition for field DDD *****

CCP 2319 Attachment Listed Below

CRB: 4815
CCP: 2319
MAP: TCIF9
LOH: 21.0A

Reqtyp B**RCO Tables**

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored. Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the field in the Data Dictionary for additional clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqtyp B, INP, Designed Analog Loop**ACT= P: LSR****Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		



Attachment
SN91085264

Conditional

AI (M)

CHC (M)

DSGCON-CITY (M)

DSGCON-ROOM (M)

DSGCON-TEL NO. (M)

SUP (M)

ALT-IMPCON-TEL NO. (M)

CUST (M)

DSGCON-FAX NO. (M)

DSGCON-STATE (M)

DSGCON-ZIP CODE (M)

VER (M)

APOT (M)

DSGCON (M)

DSGCON-FLOOR (M)

DSGCON-STREET (M)

PROJECT (M)

ACT Tables: Reqtvp B, INP, Designed Analog Loop**Optional**

ALT-IMPCON* (M)

DFDT* (M)

DRC* (M)

EXP (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= P: EU**Required**

AN (M)

ATN (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

EAN (M)

EATN (M)

EUMI (M)

IWBAN (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

ACT Tables: Reqtvp B, INP, Designed Analog Loop**ACT= Q: LSR****Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHC (M)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

Optional

ALT-IMPCON* (M)	DFDT* (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= Q: EU**Required**

AN (M)	ATN (M)	EU-CITY (M)
EU-NAME (M)	EU-STATE (M)	EU-ZIP CODE (M)
PG_OF_ (M)	PON (M)	SASN (M)

ACT Tables: Reqtvp B, INP, Designed Analog Loop**Conditional**

EATN (M)	EUMI (M)	IWBAN (M)
IWCON (M)	IWCON-TEL NO. (M)	SADLO (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	IWO* (M)	LCON-NAME (M)
LCON-TEL NO. (M)		

ACT= V: LSR**Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHG (E)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

ACT Tables: Reqtvp B, INP, Designed Analog Loop**Optional**

ALT-IMPCON* (M)

DFDT* (M)

DRC* (M)

EXP (M)

LST (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= V: EU**Required**

AN (M)

ATN (M)

ERL (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

DNUM (M)

EATN (M)

EUMI (M)

FB-BILLCON (M)

FB-BILLCON TEL NO. (M)

FB-BILLNM (M)

FB-CITY (M)

FB-FLOOR (M)

FB-ROOM (M)

FB-SBILLNM (M)

FB-STATE (M)

FB-STREET (M)

FB-ZIP CODE (M)

IWBAN (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

FBI* (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

LNA Tables: Reqtvp B, INP, Designed Analog Loop**LNA= N: LSNP****Required**

AN (M)	ATN (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)		

Conditional

CABLE ID (M)	CFA (M)	CHAN/PAIR (M)
CHAN/PAIR 2 (E)	IWJK (M)	IWJQ (M)
JK CODE (M)	JK NUM (M)	JK POS (M)
VER (M)		

Optional

JR* (M)	NIDR* (M)	TSP (M)
---------	-----------	---------

LNA= V: LSNP**Required**

LNA (M)	LNUM (M)	LQTY (M)
NPQTY (M)	NPT (M)	PG_OF_ (M)
PON (M)	PORTED NBR (M)	

Conditional

AN (M)	ATN (M)	BLOCK
CABLE ID (M)	CFA (M)	CFTN (M)
CHAN/PAIR (M)	CHAN/PAIR 2 (E)	IWJK (M)
IWJQ (M)	JK CODE (M)	JK NUM (M)
JK POS (M)	LEAN (M)	LEATN (M)
NPTG (M)	RTI (M)	TNP (M)
VER (M)		

Optional

BA*	JR* (M)	NIDR*
TSP (M)		

RCO Tables

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored. Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the field in the Data Dictionary for additional clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqttyp B, INP, Non-Designed Analog Loop

ACT= P: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHC (M)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

ACT Tables: Reqtvp B, INP, Non-Designed Analog Loop**Optional**

ALT-IMPCON* (M)

DFDT* (M)

DRC* (M)

EXP (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= P: EU**Required**

AN (M)

ATN (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

EAN (M)

EATN (M)

EUMI (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

ACT Tables: Reqty B, INP, Non-Designed Analog Loop**ACT= Q: LSR****Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHC (M)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

Optional

ALT-IMPCON* (M)	DFDT* (M)	DRC* (M)
EXP (M)	REMARKS (M)	RPON (M)

ACT= Q: EU**Required**

AN (M)	ATN (M)	EU-CITY (M)
EU-NAME (M)	EU-STATE (M)	EU-ZIP CODE (M)
PG_OF_ (M)	PON (M)	SASN (M)

ACT Tables: Reqtvp B, INP, Non-Designed Analog Loop**Conditional**

EATN (M)	EUMI (M)	IWBAN (M)
IWCON (M)	IWCON-TEL NO. (M)	SADLO (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	IWO* (M)	LCON-NAME (M)
LCON-TEL NO. (M)		

ACT= V: LSR**Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
PG_OF_ (M)	PON (M)	REQTYP (M)
SC (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHC (M)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

ACT Tables: Reqtvp B, INP, Non-Designed Analog Loop**Optional**

ALT-IMPCON* (M)	DFDT* (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= V: EU**Required**

AN (M)	ATN (M)	ERL (M)
EU-CITY (M)	EU-NAME (M)	EU-STATE (M)
EU-ZIP CODE (M)	PG_OF_ (M)	PON (M)
SASN (M)		

Conditional

DNUM (M)	EAN (M)	EATN (M)
EUMI (M)	FB-BILLCON (M)	FB-BILLCON TEL NO. (M)
FB-BILLNM (M)	FB-CITY (M)	FB-FLOOR (M)
FB-ROOM (M)	FB-SBILLNM (M)	FB-STATE (M)
FB-STREET (M)	FB-ZIP CODE (M)	IWBAN (M)
IWCON (M)	IWCON-TEL NO. (M)	SADLO (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	FBI* (M)	IWO* (M)
LCON-NAME (M)	LCON-TEL NO. (M)	

LNA Tables: Reqtvp B, INP, Non-Designed Analog Loop**LNA= N: LSNP****Required**

AN (M)	ATN (M)	CABLE ID (M)
CHAN/PAIR (M)	LNA (M)	LNUM (M)
LQTY (M)	PG_OF_ (M)	PON (M)

Conditional

IWJK (M)	IWJQ (M)	JK CODE (M)
JK NUM (M)	JK POS (M)	VER (M)

Optional

JR* (M)	NIDR* (M)	TSP (M)
---------	-----------	---------

LNA= V: LSNP**Required**

AN (M)	ATN (M)	CABLE ID (M)
CHAN/PAIR (M)	LNA (M)	LNUM (M)
LQTY (M)	NPQTY (M)	NPT (M)
PG_OF_ (M)	PON (M)	PORTED NBR (M)

Conditional

BLOCK (M)	CFTN (M)	IWJK (M)
IWJQ (M)	JK CODE (M)	JK NUM (M)
JK POS (M)	LEAN (M)	LEATN (M)
NPTG (M)	RTI (M)	TNP (M)
VER (M)		

Optional

BA* (M)	JR* (M)	NIDR* (M)
TSP (M)		

RCO Tables

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored. Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the field in the Data Dictionary for additional clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqtyp B, INP, Unbundled Copper Loop

ACT= P: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	RESID (E)	SC (M)
SECNCI (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CUST (M)	DSGCON (M)	DSGCON-CITY (M)
DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)	DSGCON-ROOM (M)
DSGCON-STATE (M)	DSGCON-STREET (M)	DSGCON-TEL NO. (M)
DSGCON-ZIP CODE (M)	PROJECT (M)	SUP (M)
VER (M)		

ACT Tables: Reqtvp B, INP, Unbundled Copper Loop**Optional**

ALT-IMPCON* (M)

CHC (M)

DRC* (M)

EXP (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= P: EU**Required**

AN (M)

ATN (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

EATN (M)

EUMI (M)

IWBAN (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

ACT Tables: Reqtyp B, INP, Unbundled Copper Loop**ACT= Q: LSR****Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	RESID (E)	SC (M)
SECNCI (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CUST (M)	DSGCON (M)	DSGCON-CITY (M)
DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)	DSGCON-ROOM (M)
DSGCON-STATE (M)	DSGCON-STREET (M)	DSGCON-TEL NO. (M)
DSGCON-ZIP CODE (M)	PROJECT (M)	SUP (M)
VER (M)		

Optional

ALT-IMPCON* (M)	CHC (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= Q: EU**Required**

AN (M)	ATN (M)	EU-CITY (M)
EU-NAME (M)	EU-STATE (M)	EU-ZIP CODE (M)
PG_OF_ (M)	PON (M)	SASN (M)

ACT Tables: Reqtvp B, INP, Unbundled Copper Loop**Conditional**

EATN (M)	EUMI (M)	IWBAN (M)
IWCON (M)	IWCON-TEL NO. (M)	SADLO (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	IWO* (M)	LCON-NAME (M)
LCON-TEL NO. (M)		

ACT= V: LSR**Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	RESID (E)	SC (M)
SECNCI (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CUST (M)	DSGCON (M)	DSGCON-CITY (M)
DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)	DSGCON-ROOM (M)
DSGCON-STATE (M)	DSGCON-STREET (M)	DSGCON-TEL NO. (M)
DSGCON-ZIP CODE (M)	PROJECT (M)	SUP (M)
VER (M)		

ACT Tables: Reqtyp B, INP, Unbundled Copper Loop**Optional**

ALT-IMPCON* (M)	CHC (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= V: EU**Required**

AN (M)	ATN (M)	ERL (M)
EU-CITY (M)	EU-NAME (M)	EU-STATE (M)
EU-ZIP CODE (M)	PG_OF_ (M)	PON (M)
SASN (M)		

Conditional

EATN (M)	EUMI (M)	FB-BILLCON (M)
FB-BILLCON TEL NO. (M)	FB-BILLNM (M)	FB-CITY (M)
FB-FLOOR (M)	FB-ROOM (M)	FB-SBILLNM (M)
FB-STATE (M)	FB-STREET (M)	FB-ZIP CODE (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
SADLO (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	FBI* (M)	IWO* (M)
LCON-NAME (M)	LCON-TEL NO. (M)	

LNA Tables: Reqtyp B, INP, Unbundled Copper Loop**LNA= D: LSNP****Required**

AN (M)	ECCKT (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)		

Conditional

VER (M)

LNA= N: LSNP**Required**

AN (M)	ATN (M)	CABLE ID (M)
CHAN/PAIR (M)	LNA (M)	LQTY (M)
PG_OF_ (M)	PON (M)	

Conditional

CHAN/PAIR 2 (E)	IWJK (M)	IWJQ (M)
JK CODE (M)	JK NUM (M)	JK POS (M)
VER (M)		

Optional

JR* (M)	NIDR* (M)
---------	-----------

LNA= V: LSNP**Required**

AN (M)	ATN (M)	CABLE ID (M)
CFTN (M)	CHAN/PAIR (M)	LNA (M)
LNUM (M)	LQTY (M)	NPQTY
NPT (M)	PG_OF_ (M)	PON (M)
PORTED NBR (M)	TNP (M)	



LNA Tables: Reqty B, INP, Unbundled Copper Loop

Conditional

BLOCK	CHAN/PAIR 2 (E)	IWJK (M)
IWJQ (M)	JK CODE (M)	JK NUM (M)
JK POS (M)	LEATN (M)	RTI (M)
VER (M)		

Optional

BA* (M)	JR* (M)	NIDR* (M)
---------	---------	-----------

RCO Tables

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored. Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the field in the Data Dictionary for additional clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqtyp B, INP, xDSL Loops

ACT= P: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	RESID (E)	SC (M)
SECNCI (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CUST (M)	DSGCON (M)	DSGCON-CITY (M)
DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)	DSGCON-ROOM (M)
DSGCON-STATE (M)	DSGCON-STREET (M)	DSGCON-TEL NO. (M)
DSGCON-ZIP CODE (M)	PROJECT (M)	SUP (M)
VER (M)		

ACT Tables: Reqtvp B, INP, xDSL Loops**Optional**

ALT-IMP CON* (M)	DFDT (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= P: EU**Required**

AN (M)	ATN (M)	EU-CITY (M)
EU-NAME (M)	EU-STATE (M)	EU-ZIP CODE (M)
PG_OF_ (M)	PON (M)	SASN (M)

Conditional

EATN (M)	EUMI (M)	FB-BILLCON (M)
FB-BILLCON TEL NO. (M)	FB-BILLNM (M)	FB-CITY (M)
FB-FLOOR (M)	FB-ROOM (M)	FB-SBILLNM (M)
FB-STATE (M)	FB-STREET (M)	FB-ZIP CODE (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
SADLO (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	FBI* (M)	IWO* (M)
LCON-NAME (M)	LCON-TEL NO. (M)	

ACT Tables: Reqtvp B, INP, xDSL Loops**ACT= Q: LSR****Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	RESID (E)	SC (M)
SECNCI (M)	TOS (M)	

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CUST (M)	DSGCON (M)	DSGCON-CITY (M)
DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)	DSGCON-ROOM (M)
DSGCON-STATE (M)	DSGCON-STREET (M)	DSGCON-TEL NO. (M)
DSGCON-ZIP CODE (M)	PROJECT (M)	SUP (M)
VER (M)		

Optional

ALT-IMPCON* (M)	DFDT (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= Q: EU**Required**

AN (M)	ATN (M)	EU-CITY (M)
EU-NAME (M)	EU-STATE (M)	EU-ZIP CODE (M)
PG_OF_ (M)	PON (M)	SASN (M)

ACT Tables: Reqtvp B, INP, xDSL Loops**Conditional**

EATN (M)	EUMI (M)	FB-BILLCON (M)
FB-BILLCON TEL NO. (M)	FB-BILLNM (M)	FB-CITY (M)
FB-FLOOR (M)	FB-ROOM (M)	FB-SBILLNM (M)
FB-STATE (M)	FB-STREET (M)	FB-ZIP CODE (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
SADLO (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	FBI* (M)	IWO* (M)
LCON-NAME (M)	LCON-TEL NO. (M)	

ACT= V: LSR**Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	RESID (E)	SC (M)
SECNCI (M)	TOS	

ACT Tables: Reqtvp B, INP, xDSL Loops**Conditional**

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CUST (M)	DSGCON (M)	DSGCON-CITY (M)
DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)	DSGCON-ROOM (M)
DSGCON-STATE (M)	DSGCON-STREET (M)	DSGCON-TEL NO (M).
DSGCON-ZIP CODE (M)	PROJECT (M)	SUP (M)
VER (M)		

Optional

ALT-IMPCON* (M)	DFDT (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= V: EU**Required**

AN (M)	ATN (M)	ERL (M)
EU-CITY (M)	EU-NAME (M)	EU-STATE (M)
EU-ZIP CODE (M)	PG_OF_ (M)	PON (M)
SASN (M)		

Conditional

EATN (M)	EUMI (M)	FB-BILLCON (M)
FB-BILLCON TEL NO. (M)	FB-BILLNM (M)	FB-CITY (M)
FB-FLOOR (M)	FB-ROOM (M)	FB-SBILLNM (M)
FB-STATE (M)	FB-STREET (M)	FB-ZIP CODE (M)
IWBAN (M)	IWCON (M)	IWCON-TEL NO. (M)
SADLO (M)	SANO (M)	SASD (M)
SASF (M)	SASS (M)	SATH (M)
VER (M)		



Attachment
SN91085264

ACT Tables: Reqtvp B, INP, xDSL Loops

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

FBI* (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

LNA Tables: Reqtvp B, INP, xDSL Loops**LNA= D: LSNP****Required**

AN (M)	ECCKT (M)	LNA (M)
LNUM (M)	LQTY (M)	PG_OF_ (M)
PON (M)		

Conditional

VER (M)

LNA= N: LSNP**Required**

AN (M)	ATN (M)	CABLE ID (M)
CHAN/PAIR (M)	LNA (M)	LNUM (M)
LQTY (M)	PG_OF_ (M)	PON (M)

Conditional

CHAN/PAIR 2 (E)	IWJK (M)	IWJQ (M)
JK CODE (M)	JK NUM (M)	JK POS (M)
VER (M)		

Optional

JR* (M)	NIDR* (M)	TSP (M)
---------	-----------	---------

LNA= V: LSNP**Required**

AN (M)	ATN (M)	CABLE ID (M)
CHAN/PAIR (M)	LNA (M)	LNUM (M)
NPQTY (M)	NPT (M)	PG_OF_ (M)
PON (M)	PORTED NBR (M)	

LNA Tables: Reqtvp B, INP, xDSL Loops**Conditional**

BLOCK (M)	CFTN (M)	CHAN/PAIR 2 (E)
IWJK (M)	IWJQ (M)	JK CODE (M)
JK NUM (M)	JK POS (M)	LEAN (M)
LEATN (M)	NPTG (M)	RTI (M)
TNP (M)	VER (M)	

Optional

BA* (M)	JR* (M)	NIDR* (M)
TSP (M)		

RCO Tables

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored. Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the field in the Data Dictionary for additional clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqttyp B, INP, Digital Designed Basic Rate ISDN

ACT= P: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHC (M)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

ACT Tables: Reqtvp B, INP, Digital Designed Basic Rate ISDN**Optional**

ALT-IMP CON* (M)

DFDT* (M)

DRC* (M)

EXP (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= P: EU**Required**

AN (M)

ATN (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

EAN (M)

EATN (M)

EUMI (M)

IWBAN (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

ACT Tables: Reqtvp B, INP, Digital Designed Basic Rate ISDN**ACT= Q: LSR****Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHC (M)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

Optional

ALT-IMPCON* (M)	DFDT* (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= Q: EU**Required**

AN (M)	ATN (M)	EU-CITY (M)
EU-NAME (M)	EU-STATE (M)	EU-ZIP CODE (M)
PG_OF_ (M)	PON (M)	SASN (M)

ACT Tables: Reqtvp B, INP, Digital Designed Basic Rate ISDN**Conditional**

EATN (M)	EUMI (M)	IWBAN (M)
IWCON (M)	IWCON-TEL NO. (M)	SADLO (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	IWO* (M)	LCON-NAME (M)
LCON-TEL NO. (M)		

ACT= V: LSR**Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHG (E)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

ACT Tables: Reqtvp B, INP, Digital Designed Basic Rate ISDN**Optional**

ALT-IMP CON* (M)

DFDT* (M)

DRC* (M)

EXP (M)

LST (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= V: EU**Required**

AN (M)

ATN (M)

ERL (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

DNUM (M)

EATN (M)

EUMI (M)

FB-BILLCON (M)

FB-BILLCON TEL NO. (M)

FB-BILLNM (M)

FB-CITY (M)

FB-FLOOR (M)

FB-ROOM (M)

FB-SBILLNM (M)

FB-STATE (M)

FB-STREET (M)

FB-ZIP CODE (M)

IWBAN (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

FBI* (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

LNA Tables: Reqtvp B, INP, Digital Designed Basic Rate ISDN**LNA= N: LSNP****Required**

AN (M)	ATN (M)	LNA (M)
LQTY (M)	PG_OF_ (M)	PON (M)

Conditional

CABLE ID (M)	CFA (M)	CHAN/PAIR (M)
CHAN/PAIR 2 (E)	JK CODE (M)	JK NUM (M)
JK POS (M)	VER (M)	

Optional

NIDR*

LNA= V: LSNP**Required**

LNA (M)	LNUM (M)	NPQTY (M)
NPT (M)	PG_OF_ (M)	PON (M)
PORTED NBR (M)		

Conditional

AN (M)	ATN (M)	BLOCK (M)
CABLE ID (M)	CFA (M)	CFTN (M)
CHAN/PAIR (M)	CHAN/PAIR 2 (E)	JK CODE (M)
JK NUM (M)	JK POS (M)	RTI (M)
TNP (M)	VER (M)	

Optional

BA* (M)	ECCKT (M)	NIDR* (M)
JR* (M)		

RCO Tables

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored. Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the field in the Data Dictionary for additional clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqttyp B, INP, Digital Data Designed Loop (DS0)

ACT= P: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHC (M)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

ACT Tables: Reqtvp B, INP, Digital Data Designed Loop (DS0)**Optional**

ALT-IMPCON* (M)

DFDT* (M)

DRC* (M)

EXP (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= P: EU**Required**

AN (M)

ATN (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

EAN (M)

EATN (M)

EUMI (M)

IWBAN (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

ACT Tables: Reqtvp B, INP, Digital Data Designed Loop (DS0)**ACT= Q: LSR****Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M) (M)
CHC (M)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO.	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

Optional

ALT-IMPCON* (M)	DFDT* (M)	DRC* (M)
EXP (M)	REMARKS (M)	RORD (M)
RPON (M)		

ACT= Q: EU**Required**

AN (M)	ATN (M)	EU-CITY (M)
EU-NAME (M)	EU-STATE (M)	EU-ZIP CODE (M)
PG_OF_ (M)	PON (M)	SASN (M)

ACT Tables: Reqtvp B, INP, Digital Data Designed Loop (DS0)**Conditional**

EATN (M)	EUMI (M)	IWBAN (M)
IWCON (M)	IWCON-TEL NO. (M)	SADLO (M)
SANO (M)	SASD (M)	SASF (M)
SASS (M)	SATH (M)	VER (M)

Optional

ACC (M)	EU-BLDG (M)	EU-FLOOR (M)
EU-ROOM (M)	IWO* (M)	LCON-NAME (M)
LCON-TEL NO. (M)		

ACT= V: LSR**Required**

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	ATN (M)	BAN1 (M)
BAN2 (M)	BI1 (M)	BI2 (M)
CC (M)	CCNA (M)	CIC (M)
D/TSENT (M)	DDD (M)	IMPCON (M)
IMPCON-TEL NO. (M)	INIT (M)	INIT-FAX NO. (M)
INIT-TEL NO. (M)	LSO (M)	NC (M)
NCI (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	SECNCI (M)
TOS (M)		

Conditional

AI (M)	ALT-IMPCON-TEL NO. (M)	APOT (M)
CHG (E)	CUST (M)	DSGCON (M)
DSGCON-CITY (M)	DSGCON-FAX NO. (M)	DSGCON-FLOOR (M)
DSGCON-ROOM (M)	DSGCON-STATE (M)	DSGCON-STREET (M)
DSGCON-TEL NO. (M)	DSGCON-ZIP CODE (M)	PROJECT (M)
SUP (M)	VER (M)	

ACT Tables: Reqtvp B, INP, Digital Data Designed Loop (DS0)**Optional**

ALT-IMPCON* (M)

DFDT* (M)

DRC* (M)

EXP (M)

LST (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= V: EU**Required**

AN (M)

ATN (M)

ERL (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

DNUM (M)

EATN (M)

EUMI (M)

FB-BILLCON (M)

FB-BILLCON TEL NO. (M)

FB-BILLNM (M)

FB-CITY (M)

FB-FLOOR (M)

FB-ROOM (M)

FB-SBILLNM (M)

FB-STATE (M)

FB-STREET (M)

FB-ZIP CODE (M)

IWBAN (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR (M)

EU-ROOM (M)

FBI* (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

LNA Tables: Reqtvp B, INP, Digital Data Designed Loop (DS0)**LNA= N: LSNP****Required**

AN (M)	ATN (M)	LNA (M)
LQTY (M)	PG_OF_ (M)	PON (M)

Conditional

CHAN/PAIR 2 (E)	JK CODE (M)	JK NUM (M)
JK POS (M)	VER (M)	

Optional

NIDR* (M)	TSP (M)	
-----------	---------	--

LNA= V: LSNP**Required**

LNA (M)	LNUM (M)	LQTY (M)
NPQTY (M)	NPT (M)	PG_OF_ (M)
PON (M)		

Conditional

AN (M)	ATN (M)	BLOCK (M)
CHAN/PAIR 2 (E)	JK CODE (M)	JK NUM (M)
JK POS (M)	VER (M)	

Optional

BA* (M)	NIDR* (M)	TSP (M)
---------	-----------	---------

CCP 2322 Attachment Listed Below

CRB: 4804
CCP: 2322
MAP: TCIF9
LOH 21.0A
REQTYP=A DS1 R/C/O tables

Digital, Data, Designed Loop (DS1) and (Non-Channelized) DS1 Local Loop

RCO Tables

The following tables show the Required, Conditional and Optional (R/C/O) fields on the valid forms/screens for this product. All unmentioned fields are either invalid, not applicable, prohibited or not supported. When fields are populated which are not supported by BellSouth, these not supported fields will be ignored. Populating any other fields may result in a fatal reject or a clarification of the service request.

Please note the following codes:

- Optional fields marked with an asterisk (*) force at least one of the conditional fields to become required when populated.
- Fields used only for manual orders are followed by (M).
- Fields used only for electronic orders are followed by (E).
- For fields marked with a DOUBLE asterisk (**) please refer to the field in the Data Dictionary for additional clarification.

See the Data Dictionary Section for additional information on each field.

ACT Tables: Reqtvp A, Digital Data Designed Loop (DS1)

ACT= D: LSR

Required

ACNA (M)	ACT (M)	ACTL (M)
AN (M)	BAN1 (M)	CC (M)
CCNA (M)	D/TSENT (M)	DDD (M)
IMPCON (M)	IMPCON-TEL NO. (M)	INIT (M)
INIT-FAX NO. (M)	INIT-TEL NO. (M)	LSO (M)
NC (M)	PG_OF_ (M)	PON (M)
REQTYP (M)	SC (M)	TOS (M)

Conditional

CUST (M)	NCI (M)	PROJECT (M)
SECNCI (M)	SUP (M)	VER (M)

OptionalCIC ~~(M)~~RORD ~~(M)~~RPON ~~(M)~~**ACT= D: EU****Required**

AN (M)

EU-NAME ~~(M)~~

PG_OF_ (M)

PON (M)

ConditionalEU-CITY ~~(M)~~EU-STATE ~~(M)~~EU-ZIP CODE ~~(M)~~SADLO ~~(M)~~SANO ~~(M)~~SASD ~~(M)~~SASF ~~(M)~~SASS ~~(M)~~SATH ~~(M)~~

VER (M)

OptionalEU-BLDG ~~(M)~~EU-FLOOR ~~(M)~~EU-ROOM ~~(M)~~SASN* ~~(M)~~**ACT= N: LSR****Required**ACNA ~~(M)~~ACT ~~(M)~~ACTL ~~(M)~~AN ~~(M)~~BAN1 ~~(M)~~CC ~~(M)~~CCNA ~~(M)~~D/TSENT ~~(M)~~DDD ~~(M)~~IMP CON ~~(M)~~IMP CON-TEL NO. ~~(M)~~INIT ~~(M)~~INIT-FAX NO. ~~(M)~~INIT-TEL NO. ~~(M)~~LSO ~~(M)~~NC ~~(M)~~NCI ~~(M)~~

PG_OF_ (M)

PON ~~(M)~~REQ TYP ~~(M)~~SC ~~(M)~~SECNCI ~~(M)~~TOS ~~(M)~~**Conditional**AI ~~(M)~~ALT-IMP CON-TEL NO. ~~(M)~~APOT ~~(M)~~CUST ~~(M)~~DSG CON ~~(M)~~DSG CON-CITY ~~(M)~~DSG CON-FAX NO. ~~(M)~~DSG CON-FLOOR ~~(M)~~DSG CON-ROOM ~~(M)~~DSG CON-STATE ~~(M)~~DSG CON-STREET ~~(M)~~DSG CON-TEL NO. ~~(M)~~DSG CON-ZIP CODE ~~(M)~~PROJECT ~~(M)~~SUP ~~(M)~~VER ~~(M)~~

ACT Tables: Reqtyp A, Digital Data Designed Loop (DS1)**Optional**

ALT-IMPCON* (M)

CIC (M)

DRC* (M)

EXP (M)

REMARKS (M)

RORD (M)

RPON (M)

ACT= N: EU**Required**

AN (M)

EU-CITY (M)

EU-NAME (M)

EU-STATE (M)

EU-ZIP CODE (M)

PG_OF_ (M)

PON (M)

SASN (M)

Conditional

IWBAN (M)

IWCON (M)

IWCON-TEL NO. (M)

SADLO (M)

SANO (M)

SASD (M)

SASF (M)

SASS (M)

SATH (M)

VER (M)

Optional

ACC (M)

EU-BLDG (M)

EU-FLOOR FLOOR (M)

EU-ROOM (M)

IWO* (M)

LCON-NAME (M)

LCON-TEL NO. (M)

CCP 2323 Attachment Listed Below

CRB: 4805
CCP: 2323
MAP: TCIF9
LOH: 21.0A

INTERVAL GUIDE

Complex Resale	Frame Relay® Add/Changes	C, V	1 - 4	3 business days	2 business days
Complex Resale	Frame Relay® Add/Changes	C, V	5+	3 business days + 1 business day for each additional circuit	3 business days
Complex Resale	Frame Relay®	W	1 - 5	3 business days	2 business days
Complex Resale	Frame Relay®	W	6 - 14	3 business days + 1 business day for each additional circuit	2 business days
Complex Resale	Frame Relay®	W	15+	Negotiated	Negotiated
Complex Resale	Frame Relay ACT = C Speed Changes Frac T1, DS0, DS1, DS3, Multilink	C	1-4	10 business days	2 business day
Complex Resale	Frame Relay ACT = C Speed Changes Frac T1, DS0, DS1, DS3, Multilink	C	5+	10 business days + 1 business day for each additional circuit	2 business day + 1 for each additional circuit
Complex Resale	Frame Relay ACT = C Speed Changes Subrate T1, T3	C	1-4	2 Business days	2 business days
Complex Resale	Frame Relay® >>>> 56K, 64K, T1	N, T	1 - 5	10 business days	3 business days
Complex Resale	Frame Relay® >>>> 56K, 64K, T1	N, T	6 - 14	10 business days + 1 business day for each additional circuit	11 business days
Complex Resale	Frame Relay® >>>> 56K, 64K, T1	N, T	15+	Negotiated	Negotiated
Complex Resale	Frame Relay® >>>> DS3	N, T	1+	Negotiated	Negotiated
Complex Resale	Frame Relay® >>>> Fractional T1	N, T	1 - 5	10 business days	6 business days
Complex Resale	Frame Relay® >>>> Fractional T1	N, T	6 - 14	10 business days + 1 business day for each additional circuit	11 business days
Complex Resale	Frame Relay® >>>> Fractional T1	N, T	15+	Negotiated	Negotiated



Attachment
SN91085264

CCP 0000 Attachment Listed Below